

BEFORE THE FLORIDA PUBLIC SERVICE COMMISSION

In re: Petition of Duke Energy Florida, LLC
for approval of a negotiated as-available energy
agreement with Placid Solar II, LLC

Docket No.

Filed: July 15, 2025

**DUKE ENERGY FLORIDA, LLC'S
PETITION FOR APPROVAL OF A NEGOTIATED
AS-AVAILABLE ENERGY AGREEMENT WITH PLACID SOLAR II, LLC**

Duke Energy Florida, LLC (“DEF” or “the Company”), pursuant to Rules 25-17.0825 and 25-17.230, F.A.C., hereby petitions the Florida Public Service Commission (“the Commission”) for approval of a negotiated as-available energy agreement between Placid Solar II, LLC (“Placid II”) and DEF, dated July 8, 2025 (“the Contract”). A copy of the Contract is attached hereto as Exhibit A. In support of this Petition, DEF states the following:

1. DEF¹ is an investor-owned utility operating under the jurisdiction of the Commission pursuant to the provisions of Chapter 366, Fla. Stat. DEF’s principal place of business is located at 299 1st Avenue North, St. Petersburg, Florida 33701.

2. For purposes of this Petition DEF’s address shall be that of its undersigned counsel. Any pleading, motion, notice, order or other document required to be served upon DEF or filed by any party to this proceeding should be served upon DEF’s undersigned counsel.

3. DEF serves more than 2 million retail customers in Florida. Its service area comprises approximately 20,000 square miles in 35 of the state’s 67 counties, including the

¹ DEF is a wholly-owned subsidiary of Duke Energy Corporation (“Duke Energy”).

densely populated areas of Pinellas and western Pasco Counties and the Greater Orlando area in Orange, Osceola, and Seminole Counties.

4. DEF maintains an As-Available Tariff Agreement for the purchase of as-available energy from Qualifying Facilities (“QFs”).² This tariff includes, among other terms and conditions, the rates to be calculated and paid by DEF to the QF, and it is approved by the Commission. DEF’s customers pay the costs for any as-available energy payments through the annual Fuel and Purchased Power Cost Recovery Clause.

5. Placid II desires to sell as-available energy from its 74.9 MW renewable generating solar facility. Placid II has not filed for QF self-certification or requested QF status from the Federal Energy Regulatory Commission (“FERC”) under 18 C.F.R. § 292.207. Rather, Placid II has attested that its facility is a Renewable Generating Facility, as that term is defined in Chapter 25-17, F.A.C. *See* Appendix B to Contract, filed as Exhibit A. Per Rule 25-17.220, F.A.C., a renewable generating facility “shall be deemed a [Florida] qualifying facility pursuant to subsection 25-17.080(1), F.A.C., and shall have all the rights, privileges, and responsibilities specified in Rules 25-17.082 through 25-17.091, F.A.C.” Rule 25-17.230(3), F.A.C. states: “Each investor-owned utility shall interconnect with any renewable generating facility in accordance with Rule 25-17.087.” Rule 25-17.087(1) provides that “Each utility shall interconnect with any qualifying facility which: (a) Is in its service area; (b) Requests interconnection; (c) Agrees to meet system standards specified in this rule; (d) *Agrees to pay the cost of interconnection*; and (e) Signs an interconnection agreement.” (emphasis added).

6. To legally engage in the sale of renewable wholesale electricity to DEF, on November 22, 2024, Placid II made an application for Market-Based Rate Authorization (“MBR”)

² Pursuant to FERC’s authority and regulations (18 C.F.R. § 131.80 and Part 292).

with FERC under Docket No. ER25-538-000. FERC approved Placid II's FERC Electric Tariff No. 1 on January 15, 2025, with an effective date of January 22, 2025 (*see* Appendix C to Contract, filed as Exhibit A). The interconnection of Placid II's facility to DEF's transmission system is subject to the jurisdiction of FERC, because Placid II is not a FERC certified QF and must make wholesale market sales as an independent power producer pursuant to its MBR tariff recently approved by the FERC. Accordingly, DEF and Placid II executed a Large Generator Interconnection Agreement ("LGIA"), pursuant to DEF's FERC approved Open Access Transmission Tariff, (OATT) which is a FERC-jurisdictional interconnection agreement. The executed LGIA is attached to this Petition as Exhibit B. Please note that portions of the LGIA are confidential and subject to the Company's separately filed Request for Confidential Classification.

7. While Placid II will legally make wholesale sales of as-available energy to DEF using its FERC approved Market-Based Rate Authorization, DEF seeks confirmation that the Commission agrees that the transmission service requirements for FERC QFs: under Rule 25-17.0889(1), F.A.C., regarding the FERC certification required for any transmission service wheeling and Rule 25-17.230(5), F.A.C. is not applicable, under 25-17.0889(3) regarding transmission service curtailments on a non-discriminatory basis remains applicable to Placid II, and both Rule sections are satisfied under the Contract because Placid II is not a FERC QF, but rather a Renewable Generating Facility and has elected that all of its output, i.e., its deliveries of As-Available Energy from the Renewable Generating Facility will be made only to DEF, and therefore, no other wheeling will be allowed throughout the Term of this Agreement.

8. The attached Contract includes the same as-available energy rate that DEF includes in its already-approved As-Available Tariff. However, given Placid II's unique status as a Florida Renewable Generating Facility, DEF had to make limited changes to its form tariff and

thus seeks approval of the Contract in this Petition. In addition, because DEF is treating Placid II as a Renewable Generating Facility (and thus a [Florida] qualifying facility) for purposes of this Commission's rules, and must therefore accept Placid II's as-available energy as if it were a FERC certified QF except during specific periods specified in Chapter 25-17, F.A.C., DEF seeks confirmation that: (1) DEF's tariffed as-available energy payments for all output, delivered as-available energy from Placid II shall be recoverable by DEF under its Fuel and Purchased Power Cost Recovery Clause and DEF's customers remain unharmed under Rules 25-17.0825 and 25-17.086, F.A.C.; and (2) the Commission agrees that the interconnection standards and procedures set forth in the FERC LGIA fully satisfy the requirements of Rule 25-17.087, F.A.C., as required by Rules 25-17.082(1), 25-17.084, and 25-17.230(3), F.A.C.

9. The FERC LGIA includes several operational and safety requirements that are similar to the requirements included in the state interconnection rule, Rule 25-17.087, F.A.C. DEF submits that the safety and operational standards required by the FERC LGIA are robust enough to meet or exceed the requirements of Rule 25-17.087(5)-(8), F.A.C. (related to Personnel Safety, Protection and Operation, Quality of Service, and Metering). For example, safety is addressed under Good Utility Practice protocols, and emergency coordination under Article 13. System Protection and Operation is addressed under section 9.7. Quality of Service is addressed in section 9.7.6 and robustly supported by ANSI and IEEE standards. Metering is specified in Article 7.

10. There is one material difference between the requirements of the state interconnection rule and the FERC LGIA, specifically Rule 25-17.087(9), F.A.C., relating to cost responsibility. The state rule obligates the interconnecting QF to "*bear all costs* associated with the change-out, upgrading or addition of protective devices, transformers, lines, services, meters, switches, and associated equipment and devices beyond that which would be required to provide

normal service to the qualifying facility if the qualifying facility were a non-generating customer.” The detailed list of items outlined in Rule 25-17.087(9), F.A.C. spells out interconnection assets required for direct-interconnection and network upgrades that may benefit all users of the transmission grid. By contrast, the FERC LGIA process only requires interconnecting generators to fund the specific interconnection costs associated with the transmission customer’s direct interconnection, but any costs for network upgrades to DEF’s system, though initially paid by the interconnecting transmission customers, are then reimbursed by DEF’s customers back to the interconnecting transmission customers. *See* Article 11.4.1³ of Exhibit B. To comply with the state interconnection rule, and for the benefit of its customers, ensuring DEF’s customers are not paying higher costs than they would otherwise for DEF to provide normal service if Placid II was a non-generating customer, DEF has requested that Placid II return to DEF the network upgrade costs that it otherwise would be reimbursed under the FERC LGIA.

11. DEF is not aware of any disputed issue of material fact pertaining to the Petition.

WHEREFORE, Duke Energy Florida, LLC, requests that:

- (a) the Commission approve the Contract, attached as Exhibit A, for negotiated as-available energy with Placid II; and
- (b) issue an order affirming that DEF has fully complied with the Commission’s rules in 25-17 with respect to the execution of the Contract.

³ **Repayment of Amounts Advanced for Network Upgrades.** Interconnection Customer shall be entitled to a cash repayment, equal to the total amount paid to Transmission Provider and Affected System Operator, if any, for the Network Upgrades, including any tax gross-up or other tax-related payments associated with Network Upgrades, and not refunded to Interconnection Customer pursuant to Article 5.17.8 or otherwise, to be paid to Interconnection Customer on a dollar-for-dollar basis for the non-usage sensitive portion of transmission charges, as payments are made under Transmission Provider’s Tariff and Affected System’s Tariff for transmission services with respect to the Large Generating Facility. Any repayment shall include interest calculated in accordance with the methodology set forth in FERC’s regulations at 18 C.F.R. § 35.19a(a)(2)(iii) from the date of any payment for Network Upgrades through the date on which the Interconnection Customer receives a repayment of such payment pursuant to this subparagraph.

Respectfully submitted,

/s/ Dianne M. Triplett

DIANNE M. TRIPLETT

299 First Avenue North

St. Petersburg, FL 33701

T: 727.820.4692

E: Dianne.Triplett@Duke-Energy.com

MATTHEW R. BERNIER

STEPHANIE CUELLO

106 East College Avenue, Suite 800

Tallahassee, FL 32301

T: 850.521.1428; T: 850.521.1425

E: Matt.Bernier@Duke-Energy.com

Stephanie.Cuello@Duke-Energy.com

FLRegulatoryLegal@duke-energy.com

Attorneys for Duke Energy Florida, LLC

Exhibit A

Contract



**NEGOTIATED AGREEMENT FOR THE PURCHASE OF
AS-AVAILABLE ENERGY AND/OR PARALLEL OPERATION FROM
A QUALIFYING FACILITY, PURSUANT TO COMMISSION RULE 25-
17.220, F.A.C.**

between

PLACID SOLAR II, LLC

and

DUKE ENERGY FLORIDA, LLC



Table of Contents

AGREEMENT	3
ARTICLE I: DEFINITIONS	5
ARTICLE II: FACILITY	7
ARTICLE III: TERM	7
ARTICLE IV: PURCHASE OF AS-AVAILABLE ENERGY	8
ARTICLE V: INTERCONNECTION	9
ARTICLE VI: ENERGY PAYMENTS	9
ARTICLE VII: CHARGES TO THE QF	9
ARTICLE VIII: METERING	9
ARTICLE IX: PAYMENT PROCEDURE	10
ARTICLE X: INSURANCE	11
ARTICLE XI: REGULATORY CHANGES	12
ARTICLE XII: FACILITY RESPONSIBILITY AND ACCESS	12
ARTICLE XIII: INDEMNIFICATION	13
ARTICLE XIV: EXCLUSION OF INCIDENTAL, CONSEQUENTIAL, AND INDIRECT DAMAGES	14
ARTICLE XV: COMMUNICATIONS	14
ARTICLE XVI: SECTION HEADINGS FOR CONVENIENCE	15
ARTICLE XVII: GOVERNING LAW	15
APPENDIX A	17
APPENDIX B	24
APPENDIX C	28

AGREEMENT

This Agreement ("Agreement") is made and entered by and between Placid Solar II, LLC, a Limited Liability Company, having its principal place of business at 3500 South Dupont Highway, Dover, DE 19901 (hereinafter referred to as the "QF"), and Florida Power Corporation d.b.a. Duke Energy Florida, LLC, a private utility corporation organized under the laws of the State of Florida, having its principal place of business at St. Petersburg, Florida (hereinafter referred to as the "Company"). The QF and the Company may be hereinafter referred to individually as a "Party" and collectively as the "Parties."

WITNESSETH:

WHEREAS, the QF desires Parallel Operation with the Company and the Company desires to purchase any as available energy to be generated by the Facility and made available for sale to the Company, consistent with FPSC Rules 25-17.220, 25-17.080, 25-17.082, 25-17.0825, 25-17.084, 26-17.086, 25-17.087, 25-17.0883, and 25-17.0889, as such rules may be amended from time to time;

WHEREAS, pursuant to Rule 25-17.220, the QF has provided an attestation to the Company, (attached hereto in Appendix B) that it is a Renewable Generating Facility, as that term is defined in Chapter 25-17, and is therefore afforded all the rights, privileges, and responsibilities provided in Rules 25-17.082 through 25-17.091;

WHEREAS, on November 22, 2024, the QF made an application for Market-Based Rate Authorization ("MBR") with the Federal Energy Regulatory Commission ("FERC") under Docket No. ER25-538-000, and FERC approved the FERC Electric Tariff No.1, (attached hereto in Appendix C) on January 22, 2025 so the QF can legally engage in the sale of renewable electricity contemplated by this agreement with the Company;

WHEREAS, the QF has agreed to comply with all interconnection requirements set forth in Rule 25-17.087; and

WHEREAS, the QF has acquired or will acquire an interconnection and transmission service agreements with the utility in whose service territory the Facility is to be located, pursuant to which the QF assumes contractual responsibility to make any and all transmission-related arrangements (including ancillary services) between the QF and the Transmission Provider for delivery of the Facility's energy to the Company. The Parties recognize that the Transmission Provider may be the Company and, in such event, that the transmission service will be provided under a separate agreement and as set forth in Rule 25-17.0889;

NOW, THEREFORE, for mutual consideration, the Parties covenant and agree as follows:

ARTICLE I: DEFINITIONS

As used in this Agreement and in the Appendices hereto, the following capitalized terms shall have the following meanings:

- 1.1 **Appendices** means the schedules, exhibits and attachments which are appended hereto and are hereby incorporated by reference and made a part of this Agreement.
 - 1.1.1 **Appendix A** sets forth the Company's Rates for Purchase of As-Available Energy.
 - 1.1.2 **Appendix B** includes the QF's attestation to the Company that it is a Renewable Generating Facility.
 - 1.1.3 **Appendix C** includes the QF's FERC approved Market Based Rate Electric Tariff No. 1.
- 1.2 **Company's Interconnection Facilities** means all equipment located on the Company's side of the Point of Delivery, (including without limitation), equipment for connection, switching, transmission, distribution, protective relaying and safety provisions which in the Company's judgment is required to be installed for the delivery and measurement of electric energy into the Company's system on behalf of the QF, including all metering and telemetering equipment installed for the measurement of such energy regardless of its location in relation to the Point of Delivery.
- 1.3 **As-Available Energy** means energy produced and sold by a QF on an hour-by-hour basis for which contractual commitments as to quantity, time, or reliability of delivery are not required.
- 1.4 **Distributed Resource** means a facility that is defined as a Distributed Resource in the Institute of Electrical and Electronics Engineers ("IEEE") Standard 1547 for Interconnecting Distributed Resources with Electric Power Systems.
- 1.5 **Execution Date** means the date on which the Company executes this Agreement.

- 1.6 **Facility** means all equipment, as described in this Agreement, used to produce electric energy and, for a cogeneration facility, used to produce useful thermal energy through the sequential use of energy.
- 1.7 **FERC** means the Federal Energy Regulatory Commission and any successor.
- 1.8 **FPSC** means the Florida Public Service Commission and any successor.
- 1.9 **Force Majeure Event** means an event or occurrence that is not reasonably foreseeable by a Party, is beyond its reasonable control, and is not caused by its negligence or lack of due diligence, including, but not limited to, natural disasters, fire, lightning, wind, perils of the sea, flood, explosions, acts of God or the public enemy, strikes, lockouts, vandalism, blockages, insurrections, riots, war, sabotage, action of a court or public authority, or accidents to or failure of equipment or machinery, including, if applicable, equipment of the Transmission Provider.
- 1.10 **KW** means one (1) kilowatt of electric capacity.
- 1.11 **KWH** means one (1) kilowatt-hour of electric energy.
- 1.12 **Parallel Operation** means the QF will engage in interconnected operation of the QF's generating facility with the Company.
- 1.13 **Point of Delivery** means the point(s) where electric energy delivered to the Company pursuant to this Agreement enters the Company's system.
- 1.14 **Point of Metering** means the point(s) where electric energy made available for delivery to the Company, subject to adjustment for losses, is measured.
- 1.15 **Point of Interconnection** means the interconnection point(s) between the Facility and the interconnected utility.
- 1.16 **Qualifying [Small Power Production or Cogeneration] Facility ("QF")** for the purposes of this agreement means a Renewable Generating Facility defined in FPSC Rule 25-17.210(1), and where the Renewable Generating Facility and the Company are proceeding pursuant to the rights, privileges, and responsibilities identified in FPSC Rule 25-17.220.

ARTICLE II: FACILITY

- 2.1 The Facility shall be located in Highlands County, Florida, Sections 4 and 5 of Township 37 South, Range 29 East. The Facility shall meet all other specifications identified in the Appendices hereto in all material respects and no change in the designated location of the Facility shall be made by the QF. The Facility shall be designed and constructed by the QF or its agents at the QF's sole expense.
- 2.2 Throughout the Term of this Agreement, the Facility shall be a Qualifying Facility. In the event the Facility does not maintain its status as a Qualifying Facility, or if the Facility does not maintain its MBR tariff approval from FERC, this Agreement shall be immediately deemed null and void as of said date and of no further effect.
- 2.3 Unless the QF is already interconnected to a transmission or distribution system, no later than sixty (60) days after the Execution Date, the QF shall apply to its Transmission Provider for transmission service including a system impact study, if required. The QF shall continue the interconnection process in a timely manner so as to maintain its position in the interconnection queue.
- 2.4 The QF intends to begin deliveries to the Company by December 31, 2026.

ARTICLE III: TERM

The Term of this Agreement shall begin once the FPSC has issued a final, non-appealable order approving the Agreement and shall continue until terminated by the Company for good cause or by the QF. Upon termination or expiration of this Agreement, the Parties shall be relieved of their obligations under this Agreement except for the obligation to pay each other all monies under this Agreement, which obligation shall survive termination or expiration.

ARTICLE IV: PURCHASE OF AS-AVAILABLE ENERGY

- 4.1 The QF shall sell and arrange for delivery of the As-Available Energy to the Company and the Company agrees to purchase, accept and pay for the As-Available Energy made available to the Company and which the Company is able to receive at the Point of Delivery in accordance with the terms and conditions of this Agreement, or a separately negotiated contract.
- 4.2 The QF shall not commence initial deliveries of energy to the Point of Delivery without the prior written consent of the Company, which consent shall not unreasonably be withheld.
- 4.3 The QF shall retain any and all rights to own and to sell any and all Environmental Attributes associated with the electric generation of the Facility.
- 4.4 During minimum load conditions on the Company's system the QF shall comply with the Company's Minimum Load Emergency Curtailment Procedures as approved by the FPSC and as updated from time to time.
- 4.5 In the event that the Company has not received any deliveries of energy from the QF by the date in Section 2.4 or for a period of two years or more then the Company will contact the QF in writing using the information in Section 15 requesting the QFs future plans. The Company shall have the right to terminate this Agreement unless the QF replies in writing within a reasonable timeframe that it would like this Agreement to continue.
- 4.6 Deliveries of As-Available Energy to the Company shall be made in accordance to the following one-time-only option.
- (X) All deliveries of As-Available Energy from this Facility will be made to the Company.
- () As-Available Energy deliveries from this Facility will be made to the Company and to other parties.



ARTICLE V: INTERCONNECTION

- 5.1 The QF's interconnection scheduling and parallel operating procedures shall be those specified in a separate interconnection agreement, specifically the FERC Large Generator Interconnection Agreement (LGIA), executed between Company and QF on November 25, 2024], as set forth in Rule 25-17.087.
- 5.2 The location and voltage of the Point of Interconnection and the Point of Metering will be specified by the LGIA.
- 5.3 As required by Rule 25-17.087(9), QF shall pay Company all costs associated with interconnecting the QF Facility.

ARTICLE VI: ENERGY PAYMENTS

- 6.1 For that electric energy received by the Company at the Point of Delivery each month, the Company will pay the QF an amount as computed in Appendix A.
- 6.2 Energy payments pursuant to sections 9.1.1 and 9.1.2 hereof shall be subject to the delivery voltage adjustment value applicable to the Facility and approved from time to time by the FPSC pursuant to Appendix A.
- 6.3 Upon agreement by the Company and the QF and subject to approval by the FPSC, an alternative rate for the purchase of As-Available Energy may be negotiated in a separate agreement.

ARTICLE VII: CHARGES TO THE QF

The Company shall bill and the QF shall pay all charges applicable under Appendix A.

ARTICLE VIII: METERING

- 8.1 All electric energy shall be capable of being measured as described in Appendix A, Determination of Payment, at the Point of Metering. All

electric energy delivered to the Company shall be adjusted for losses from the Point of Metering to the Point of Delivery. Any additional required metering equipment to measure electric energy and the telemetering equipment necessary to transmit such measurements to a location specified by the Company shall be installed, calibrated and maintained by the Company and all related costs shall be charged to the QF, pursuant to Appendix A, as part of the Company's Interconnection Facilities.

- 8.2 All meter testing and related billing corrections, for electricity sold and purchased by the Company, shall conform to the metering and billing guidelines contained in FPSC Rules 25-6.052 through 25-6.060 and FPSC Rule 25-6.103, as they may be amended from time to time, notwithstanding that such guidelines apply to the utility as the seller of electricity.

ARTICLE IX: PAYMENT PROCEDURE

- 9.1 Bills shall be issued and payments shall be made monthly to the QF and by the QF in accordance with the following procedures:
- 9.1.1 The electric energy payment calculated for a given month shall be tendered, with cost tabulations showing the basis for payment, by the Company to the QF as a single payment. Such payments to the QF shall be due and payable twenty (20) business days following the end of the billing period.
- 9.1.2 When any amount is owing from the QF, the Company shall issue a monthly bill to the QF with cost tabulations showing the basis for the charges. All amounts owing to the Company from the QF shall be due and payable twenty (20) business days after the date of the Company's billing statement. Amounts owing to the Company for retail electric service shall be payable in accordance with the provisions of the applicable rate schedule.
- 9.1.3 At the option of the QF, the Company will provide a net payment or net bill, whichever is applicable, that consolidates amounts owing to the QF with amounts owing to the Company.



- 9.1.4 Except for charges for retail electric service, any amount due and payable from either Party to the other pursuant to this Agreement that is not received by the due date shall accrue interest from the due date at the rate equal to the thirty (30) day highest grade commercial paper as published in the Wall Street Journal on the first business day of each month. Such interest shall be compounded monthly.
- 9.1.5 The QF may elect net sale or simultaneous purchase and sale in accordance with the provisions of FPSC Rule 25-17.082, such election not to be changed more often than every twelve (12) months.
- 9.1.6 Payments to be made under this Agreement shall, for a period of not longer than two (2) years, remain subject to adjustment based on billing adjustments due to error or omission by either Party.

ARTICLE X: INSURANCE

The provisions of this Article do not apply to a QF whose Facility is not directly interconnected with the Company's system.

- 10.1 The QF shall deliver to the Company, at least fifteen (15) days prior to the commencement of any work on the Company's Interconnection Facilities, a certificate of insurance certifying the QF's coverage under a liability insurance policy issued by a reputable insurance company authorized to do business in the State of Florida naming the QF as a named insured and the Company as an additional named insured, which policy shall contain a broad form contractual endorsement specifically covering liabilities arising out of the interconnection with the Facility, or caused by the operation of the Facility or by the QF's failure to maintain the Facility in satisfactory and safe operating condition.

- 10.2 The insurance policy providing such coverage shall provide public liability insurance, including property damage, in an amount not less than \$1,000,000 for each occurrence. The required insurance policy shall be endorsed with a provision requiring the insurance company to notify the Company at least thirty (30) days prior to the effective date of any cancellation or material change in the policy.
- 10.3 The QF shall pay all premiums and other charges due on said insurance policy and shall keep said policy in force during the entire period of interconnection with the Company.

ARTICLE XI: REGULATORY CHANGES

The Parties agree that the Company's payment obligations under this Agreement are expressly conditioned upon the mutual commitments set forth in this Agreement. Payments for as-available energy made to QFs pursuant to this Agreement shall be recovered by the Company through the Commission's periodic review of fuel and purchased power.

ARTICLE XII: FACILITY RESPONSIBILITY AND ACCESS

- 12.1 Representatives of the Company shall at all reasonable times have access to the Facility and to property owned or controlled by the QF and having relationship to the interconnection for the purpose of inspecting, testing, and obtaining other technical information deemed necessary by the Company in connection with this Agreement. Any inspections or testing by the Company shall not relieve the QF of its obligation to maintain the Facility.

- 12.2 In no event shall any Company statement, representation, or lack thereof, either express or implied, relieve the QF of its exclusive responsibility for the Facility and its exclusive obligations, if applicable, with the Transmission Provider. Any Company inspection of property or equipment owned or controlled by the QF or the Transmission Provider, or any Company review of or consent to the QF's or the Transmission Provider's plans, shall not be construed as endorsing the design, fitness or operation of the Facility or the Transmission Provider's equipment nor as a warranty or guarantee.
- 12.3 The Company shall reactivate the Company's Interconnection Facilities at its own expense if the same are rendered inoperable due to actions of the Company or its agents, or a Force Majeure Event.

ARTICLE XIII: INDEMNIFICATION

The QF agrees to indemnify and save harmless the Company and its employees, officers, and directors against any and all liability, loss, damage, costs or expense which the Company, its employees, officers and directors may hereafter incur, suffer or be required to pay by reason of negligence on the part of the QF in performing its obligations pursuant to this Agreement or the QF's failure to abide by the provisions of this Agreement. The Company agrees to indemnify and save harmless the QF and its employees, officers, and directors against any and all liability, loss, damage, cost or expense which the QF, its employees, officers, and directors may hereafter incur, suffer, or be required to pay by reason of negligence on the part of the Company in performing its obligations pursuant to this Agreement or the Company's failure to abide by the provisions of this Agreement. The QF agrees to include the Company as an additional insured in any liability insurance policy or policies the QF obtains to protect the QF's interests with respect to the QF's indemnity and hold harmless assurance to the Company contained in this Article.



ARTICLE XIV: EXCLUSION OF INCIDENTAL, CONSEQUENTIAL, AND INDIRECT DAMAGES

Neither Party shall be liable to the other for incidental, consequential or indirect damages, including, but not limited to, the cost of replacement power, whether arising in contract, tort, or otherwise.

ARTICLE XV: COMMUNICATIONS

15.1 Any non-emergency or operational notice, request, consent, payment or other communication made pursuant to this Agreement to be given by one Party to the other Party shall be in writing, either personally delivered or mailed to the representative of said other Party designated in this section, and shall be deemed to be given when received. Notices and other communications by the Company to the QF shall be addressed to:

Placid Solar II, LLC
3500 South Dupont Highway
Dover, DE 19901

Notices to the Company shall be addressed to:

Manager-Cogeneration Contracts & Administration
Duke Energy Florida
P.O. Box 14042
St. Petersburg, FL 33733

15.2 Communications made for emergency or operational reasons may be made to the following persons and shall thereafter be confirmed promptly in writing.

To The Company: System Dispatcher on Duty
Title: System Dispatcher
Telephone: (727) 866-5888
Telecopier: (727) 384-7865

To The QF: Name: Enrique Guillen
Title: Site Manager
Telephone: (561) 445-6606
Telecopier: () _____

15.3 Either Party may change its representatives' names in this section by prior written notice to the other Party.

15.4 The Parties' representatives designated above shall have full authority to act for their respective principals in all technical matters relating to the performance of this Agreement. However, they shall not have the authority to amend, modify, or waive any provision of this Agreement.

ARTICLE XVI: SECTION HEADINGS FOR CONVENIENCE

Article or section headings appearing in this Agreement are inserted for convenience only and shall not be construed as interpretations of text.

ARTICLE XVII: GOVERNING LAW

The interpretation and performance of this Agreement and each of its provisions shall be governed by the laws of the State of Florida.



IN WITNESS WHEREOF, the QF has caused this Agreement to be executed by its duly authorized representatives on the day and year below.

The Qualifying Facility:

By: Felice Basile _____

Title: Authorized Signatory _____

Date: 07 July 2025 _____

ATTEST:

Signed by:

Felice Basile

AEBB045701AC471...

IN WITNESS WHEREOF, the Company has acknowledged receipt of this executed Agreement.

The Company:

By: _____

Title: _____

Date: _____



IN WITNESS WHEREOF, the QF has caused this Agreement to be executed by its duly authorized representatives on the day and year below.

The Qualifying Facility:

By: _____

Title: _____

Date: _____

ATTEST:

IN WITNESS WHEREOF, the Company has acknowledged receipt of this executed Agreement.

The Company:

By: Jimmy Camp

Title: WHOLESALE RENEWABLE MANAGER

Date: 7/8/25

APPENDIX A RATES

TABLE OF CONTENTS

SCHEDULE 1 Payments for As-Available Energy

SCHEDULE 2 Methodology for Calculating Avoided Energy Costs

SCHEDULE 3 Charges to Qualifying Facility

APPENDIX A RATES

SCHEDULE 1

PAYMENTS FOR AS-AVAILABLE ENERGY

Payments:

As-Available Energy is purchased at a unit cost, in cents per kilowatt-hour, based on the Company's actual hourly avoided energy costs which are calculated by the Company in accordance with the methodology described in Schedule 2 of this Appendix. Customer charges directly attributable to the purchase of As-Available Energy from the Qualifying Facility are deducted from the Qualifying Facility's total monthly energy payment. Avoided energy costs include incremental fuel and identifiable variable operation and maintenance expenses, and identifiable variable utility power purchases. An adjustment for line losses reflecting delivery voltage shall also be included. When interchange transactions take place, the incremental costs are calculated after the purchase or before the sale of the interchange energy. All sales shall be adjusted for losses from the point of metering to the Point of Interconnection.

Estimated As-Available Energy Cost:

Upon request by a qualifying facility or any interested person, each utility shall provide within 30 days its most current projections of its generation mix, fuel price by type of fuel, and at least a five year projection of fuel forecasts to estimate future as-available energy prices as well as any other information reasonably required by the qualifying facility to project future avoided cost prices including, but not limited to, a 24 hour advance forecast of hour-by-hour avoided energy costs. The Company may charge an appropriate fee, not to exceed the actual cost of production and copying, for providing such information.

APPENDIX A RATES

SCHEDULE 2

METHODOLOGY FOR CALCULATING AVOIDED ENERGY COSTS

Introduction:

A unit commitment computer program is utilized to determine the hourly avoided energy cost as the basis for purchase of as-available energy from qualifying facilities. All economic, unit constraint, and system requirements data necessary for program execution is based on real time data accumulated during the hour that energy was received.

Determination of Energy Block Size:

The energy received from all as-available QFs is determined by the Company's Meter Department for metered energy and the Company's Energy Control Department for telemetered energy. The Energy Control Department combines these inputs to determine the total energy received by the Company from QFs for the period. The energy block size will be the equivalent of this total divided by the number of hours in the period, rounded to the nearest five MW. The energy price payable to the QFs will be based on this energy block size. A time aligned matrix of energy received from each QF excluding non-time-of-day QFs (less than 100 KW) is produced from this data (Energy Received Matrix).

Unit Commitment Program Execution:

The Unit Commitment Program is executed with the following hourly input data for the desired period:

1. Unit constraint data to simulate actual unit operating conditions and availability.
2. Resource economic data consistent with the data used in the actual dispatch of energy resources. This includes a replacement cost of fuel based on an average forecast price from the Company's suppliers for oil, the price for interruptible gas, and the spot market price of coal.
3. System load and operating/spinning reserve requirements actually experienced.
4. Interchange purchases in the magnitude and at the average variable cost actually incurred. The cost of emergency purchases shall be assumed equal to that of the average unit cost of emergency purchases made during the prior twelve months' period for which emergency purchase information is available.

The unit commitment program is executed a second time for the same period with an increase in the hourly system load equal to the energy block size. All other data remain the same.

Determination of Energy Price:

A comparison of the unit commitment program executions described above produces the energy prices. The hourly cost of the second execution minus the corresponding hourly cost of the first execution equals the hourly energy cost avoided by the Company as a result of the energy supplied by the QFs. These hourly avoided energy costs will be arranged into a time aligned matrix of energy prices (Energy Price Matrix).

APPENDIX A RATES

SCHEDULE 2 METHODOLOGY FOR CALCULATING AVOIDED ENERGY COSTS

Determination of Identifiable Variable Operation & Maintenance Cost:

The Company's Fossil Plant Performance Department examines for a five year historic period all the Company's production operation and maintenance expenses excluding fuel costs and identifies the variable component. A ratio of variable costs to total O&M costs excluding fuel is derived for various fossil generating types. The appropriate ratio is applied to each fossil generating type's unit cost (on a KWH basis) for the most current twelve months' period to establish the current variable O&M unit cost for each generating type. These unit costs are then weighted according to the current twelve months' generation output of each generating type to determine the average current variable O&M unit cost.

Determination of Line Loss (Delivery Voltage) Adjustment:

The Company's average system line losses are analyzed annually for the prior calendar year, and delivery efficiencies are developed for the transmission, distribution primary, and distribution secondary voltage levels. This analysis is provided in the Company's fuel cost recovery filing with the FPSC and/or the Company's filing of its Open Access Transmission Tariff with FERC. An adjustment factor, calculated as the reciprocal of the appropriate delivery efficiency factor, is applicable to the above determined avoided costs to reflect the delivery voltage level at which QF energy is received by the Company.

Determination of Payment:

The actual payment to each QF for the period is determined by one of the following methods:

1. For QFs (less than 100 KW) Time-of-Day Metered

Average On-Peak and Off-Peak energy prices derived from the "Energy Price Matrix" are applied to the QF's corresponding On-Peak and Off-Peak energy contained in the "Energy Received Matrix." Added to this amount is an amount representing avoided variable O&M cost which is calculated by applying the Company's variable O&M cost per KWH to the total energy received by the Company from the QF. The total amount derived is then adjusted by the delivery voltage adjustment.

2. For QFs (less than 100 KW) Non-Time-of-Day Metered

The average Off-Peak energy price derived from the "Energy Price Matrix" is applied to the QF's energy contained in the "Energy Received Matrix." Added to this amount is an amount

representing avoided variable O&M cost which is calculated by applying the Company's variable O&M cost per KWH to the total energy received by the Company from the QF. The total amount derived is then adjusted by the delivery voltage adjustment.

3. For QFs (100 KW or Greater) Hourly Metered

The "Energy Price Matrix" is applied to corresponding elements of the QF's "Energy Received Matrix." Added to this amount is an amount representing avoided variable O&M cost which is calculated by applying the Company's variable O&M cost per KWH to the total energy received by the Company from the QF. The total amount derived is then adjusted by the delivery voltage adjustment.

APPENDIX A RATES

SCHEDULE 3 CHARGES TO QUALIFYING FACILITY

Customer Charges:

The Qualifying Facility shall be responsible for all FPSC approved charges for any retail service that may be provided by the Company. The Qualifying Facility shall be billed at the customer charge rate stated in DEF's applicable standby tariff monthly for the costs of meter reading, billing, and other appropriate administrative costs.

Operation, Maintenance, and Repair Charges:

The Qualifying Facility shall pay for operation, maintenance and repair charges in accordance with its interconnection and transmission service agreements.

Taxes and Assessments:

The Qualifying Facility shall be billed or credited monthly an amount equal to the taxes, assessments, or other impositions, if any, for which the Company is liable as a result of its installation of facilities in connection with this Agreement, its purchase of As-Available Energy produced by the Qualifying Facility, or any other activity undertaken pursuant to this Agreement. Such amount billed shall not include any amounts (i) for which the Company would have been liable had it generated or purchased from other sources an equivalent amount of electric energy; or (ii) which are recovered by the Company.

APPENDIX B
QF's
ATTESTATION

ATTESTATION FOR A FLORIDA RENEWABLE GENERATING FACILITY

I, Felice Basile, as the Authorized Signatory of Placid Solar II, LLC, provide this attestation regarding status of the Highlands Solar North solar electric generating facility with respect to its status as a Renewable Generating Facility pursuant to Rule 25-17.210 , Florida Administrative Code (“F.A.C.”). In my capacity as the Authorized Signatory of Placid Solar II, LLC, I have full power and authority to sign this attestation on behalf of Placid Solar II, LLC, and I hereby attest that the following facts are true and correct.

1. Placid Solar II, LLC, is the owner of the Highlands Solar North solar electric generating facility (the “Facility”). Placid Solar II, LLC (“Placid Solar II”), is a Delaware limited liability company authorized to do business in the state of Florida. The full mailing address of Placid Solar II, LLC, is 3500 South Dupont Highway, Dover, Delaware 19901. All of the membership interests in Placid Solar II, LLC, are owned by GREENSEED HOLDINGS I LLC, and all of the membership interests in GREENSEED HOLDINGS I LLC, a limited liability company organized in accordance with the Delaware Limited Liability Company Act, are owned by NEXTPOWER III US HOLDCO INC., a Delaware corporation, which is the sole member of GREENSEED HOLDINGS I LLC.
2. The Facility, located at 3100 Lake Crews Avenue, Lake Placid, Florida 33852, in Highlands County, Florida, is a solar generating facility with 74.9 megawatts

(alternating current), generally stated as 74.9 MW_{ac}, of solar generating capacity, and will be interconnected to the Fisheating Creek substation of Duke Energy Florida pursuant to Rule 25-17.087, F.A.C., and pursuant to the Large Generator Interconnection Agreement between Duke Energy Florida, LLC, and Placid Solar II (the “LGIA”). Placid Solar II applied to the Federal Energy Regulatory Commission for approval of its Market Based Rates Tariff No. 1 and received the FERC’s approval of that Tariff on January 22, 2025. Pursuant to the Tariff and the LGIA, I further attest that all energy from the Facility will only be delivered to and available to purchase by Duke Energy Florida, LLC. The Facility will generate energy solely using solar photovoltaic generating equipment and will therefore be a Renewable Generating Facility as that term is defined and used in Rule 25-17.210, F.A.C.

3. Further, for the purposes of Rules 25-17.200 through 25-17.310, F.A.C., as applicable, the Highlands Solar North Facility is deemed a state jurisdictional qualifying facility pursuant to Rule 25-17.220, F.A.C., and subject, to the extent applicable, to the state’s jurisdictional qualifying facility Rules, including but not limited to Rule 25-17.0889, F.A.C.
4. I further attest that neither the Facility nor Placid Solar II, LLC, has filed a FERC Form 556 for FERC jurisdictional Qualifying Facility status.

5. Finally, I understand that this attestation, as presented, does not create any obligation or entitlement for either party to enter into any future contract or business relationship with the other party.

Signed by:

Felice Basile

AEBBD45791AC471...
Felice Basile

Authorized Representative of Placid Solar II, LLC

27 June 2025

Date

APPENDIX C

QF's MBR ELECTRIC TARIFF NO. 1

Placid Solar II, LLC
FERC Electric Tariff No. 1

1. Availability. Placid Solar II, LLC (“Seller”) will make available under this Tariff:

- (a) electric energy and/or capacity to any purchaser for resale; and
- (b) the following ancillary services to any purchaser:
 - (i) PJM: Seller offers regulation and frequency response service, energy imbalance service, and operating reserve service (which includes spinning, 10-minute, and 30-minute reserves) for sale into the market administered by PJM Interconnection, L.L.C. ("PJM") and, where the PJM Open Access Transmission Tariff permits, the self-supply of these services to purchasers for a bilateral sale that is used to satisfy the ancillary services requirements of the PJM Office of Interconnection.
 - (ii) New York: Seller offers regulation and frequency response service, and operating reserve service (which include 10-minute non-synchronous, 30- minute operating reserves, 10-minute spinning reserves, and 10-minute non-spinning reserves) for sale to purchasers in the market administered by the New York Independent System Operator, Inc.
 - (iii) New England: Seller offers regulation and frequency response service (automatic generator control), operating reserve service (which includes 10- minute spinning reserve, 10-minute non-spinning reserve, and 30- minute operating reserve service) to purchasers within the markets administered by the ISO New England, Inc.
 - (iv) California: Seller offers regulation service, spinning reserve service, and non-spinning reserve service to the California Independent System Operator Corporation ("CAISO") and to others that are self-supplying ancillary services to the CAISO.
 - (v) MISO: Seller offers regulation service and operating reserve service (which include 10-minute spinning reserve and 10-minute supplemental reserve) for sale to the Midcontinent Independent System Operator, Inc. (“MISO”) and to others that are self-supplying ancillary services to MISO.

- (vi) Southwest Power Pool: Seller offers regulation service and operating reserve service (which include 10-minute spinning reserve and 10-minute supplemental reserve) for sale to the Southwest Power Pool, Inc. (“SPP”) and to others that are self-supplying ancillary services to SPP.
 - (vii) Third-party Ancillary Services: Seller offers Regulation Service, Reactive Supply and Voltage Control Service, Energy and Generator Imbalance Service, Operating Reserve-Spinning, Operating Reserve-Supplemental, and Primary Frequency Response Service. Sales will not include the following: (1) sales to an RTO or an ISO, i.e., where that entity has no ability to self-supply ancillary services but instead depends on third parties; and (2) sales to a traditional, franchised public utility affiliated with the third-party supplier, or sales where the underlying transmission service is on the system of the public utility affiliated with the third-party supplier. Sales of Operating Reserve-Spinning and Operating Reserve-Supplemental will not include sales to a public utility that is purchasing ancillary services to satisfy its own open access transmission tariff requirements to offer ancillary services to its own customers, except where the Commission has granted authorization. Sales of Regulation Service and Reactive Supply and Voltage Control Service will not include sales to a public utility that is purchasing ancillary services to satisfy its own open access transmission tariff requirements to offer ancillary services to its own customers, except at rates not to exceed the buying public utility transmission provider’s OATT rate for the same service or where the Commission has granted authorization.
2. Applicability. This Tariff is applicable to all sales of energy, capacity, and ancillary services by Seller, which are (a) subject to the jurisdiction of the Commission, and (b) not made pursuant to another tariff on file with the Commission.
 3. Rates. All sales shall be made at rates established by agreement between the purchaser and Seller.
 4. Other Terms and Conditions. All other terms and conditions of sales shall be established by agreement between the purchaser and Seller.
 5. Revisions. This Tariff may be revised by Seller by unilaterally making the appropriate filing with the Commission pursuant to the provisions of Section 205 of the Federal Power Act.

6. Duration. This Tariff shall continue to be effective until terminated or changed. Such termination or change shall take effect in accordance with the applicable regulatory requirements.
7. Compliance with Commission Regulations. Seller shall comply with the provisions of 18 CFR Part 35, Subpart H, as applicable, and with any conditions the Commission imposes in its orders concerning Seller's market-based rate authority, including orders in which the Commission authorizes Seller to engage in affiliate sales under this tariff or otherwise restricts or limits the Seller's market-based rate authority. Failure to comply with the applicable provisions of 18 CFR Part 35, Subpart H, and with any orders of the Commission concerning Seller's market-based rate authority, will constitute a violation of this tariff.
8. Limitations and Exemptions Regarding Market-Based Rate Authority. In *Placid Solar II, LLC*, Docket No. ER25-___-00_ (2025), the Commission granted Seller the following waivers and blanket authorization: (i) waiver of the accounting, reporting, and other requirements of 18 C.F.R. Parts 41, 101 (with the exception that waiver of the provisions of Part 101 that apply to hydropower licensees is not granted with respect to licensed hydropower projects), and 141 with the exception of Sections 141.14 and 141.15; (ii) waiver of the requirements of Subparts B and C of Part 35 of the Commission's regulations, except Sections 35.12(a), 35.13(b), 35.15 and 35.16; and (iii) Blanket authorization under 18 C.F.R. Part 34 of all future issuances of securities and assumptions of liability.
9. Seller Category. Seller is a Category 1 Seller, as defined in 18 C.F.R. § 35.36(a), in the Northeast, Southeast, Central, Southwest Power Pool, Northwest and Southwest Regions.
10. Effective Date. This Tariff shall become effective on the date specified by the Commission.

Exhibit B

Large Generator Interconnection Agreement

OATT SERVICE AGREEMENT NO. 295

UNDER

TARIFF VOLUME NO. 4

AMENDED AND RESTATED

AMENDED AND RESTATED LARGE GENERATOR INTERCONNECTION

AGREEMENT

BETWEEN

DUKE ENERGY FLORIDA, LLC (TRANSMISSION PROVIDER)

AND

PLACID SOLAR II, LLC (INTERCONNECTION

CUSTOMER)

GENERATING FACILITY: DEF – Q259 Highlands Solar North

Table of Contents

Article 1.	Definitions.....	
Article 2.	Effective Date, Term, and Termination	
2.1	Effective Date.....	
2.2	Term of Agreement.....	
2.3	Termination Procedures.....	
2.3.1	Written Notice.....	
2.3.2	Default.....	
2.3.3	
2.4	Termination Costs.....	
2.4.1	
2.4.2	
2.4.3	
2.5	Disconnection.....	
2.6	Survival.....	
Article 3.	Regulatory Filings	
3.1	Filing.....	
Article 4.	Scope of Service.....	
4.1	Interconnection Product Options.....	
4.1.1	Energy Resource Interconnection Service.....	
4.1.1.1	The Product.....	
4.1.1.2	Transmission Delivery Service Implications.....	
4.1.2	Network Resource Interconnection Service.....	
4.1.2.1	The Product.....	
4.1.2.2	Transmission Delivery Service Implications.....	
4.2	Provision of Service.....	
4.3	Performance Standards.....	
4.4	No Transmission Delivery Service.....	
4.5	Interconnection Customer Provided Services.....	
Article 5.	Interconnection Facilities Engineering, Procurement, & Construction.....	
5.1	Options.....	
5.1.1	Standard Option.....	
5.1.2	Alternate Option.....	
5.1.3	Option to Build.....	
5.1.4	Negotiated Option.....	
5.2	General Conditions Applicable to Option to Build.....	
5.3	Liquidated Damages.....	
5.4	Power System Stabilizers.....	

5.5	Equipment Protection.
5.5.1
5.5.2
5.5.3
5.6	Construction Commencement.....
5.6.1
5.6.2
5.6.3
5.6.4
5.7	Work Progress.....
5.8	Information Exchange.....
5.9	Other Interconnection Options.
5.9.1	Limited Operation.....
5.9.2	Provisional Interconnection Service.
5.10	Interconnection Customer’s Interconnection Facilities (‘ICIF’).
5.10.1	Interconnection Customer’s Interconnection Facility Specifications.....
5.10.2	Transmission Provider’s Review.
5.10.3	ICIF Construction.
5.11	Transmission Provider’s Interconnection Facilities Construction.
5.12	Access Rights.
5.13	Lands of Other Property Owners.
5.14	Permits.
5.15	Early Construction of Base Case Facilities.
5.16	Suspension.....
5.17	Taxes.
5.17.1	Interconnection Customer Payments Not Taxable.
5.17.2	Representations and Covenants.
5.17.3	Indemnification for the Cost Consequences of Current Tax Liability Imposed Upon the Transmission Provider.
5.17.4	Tax Gross-Up Amount.
5.17.5	Private Letter Ruling or Change or Clarification of Law.
5.17.6	Subsequent Taxable Events.
5.17.7	Contests.
5.17.8	Refund.....
5.17.9	Taxes Other Than Income Taxes.
5.17.10	Transmission Owners Who Are Not Transmission Providers.....
5.18	Tax Status.....
5.19	Modification.....
5.19.1	General.....
5.19.2	Standards.....

5.19.3	Modification Costs.
Article 6. Testing and Inspection.....		
6.1	Pre-Commercial Operation Date Testing and Modifications.
6.2	Post-Commercial Operation Date Testing and Modifications.
6.3	Right to Observe Testing.
6.4	Right to Inspect.
Article 7. Metering.....		
7.1	General.
7.2	Check Meters.
7.3	Standards.
7.4	Testing of Metering Equipment.
7.5	Metering Data.
Article 8. Communications.....		
8.1	Interconnection Customer Obligations.
8.2	Remote Terminal Unit.
8.3	No Annexation.
8.4	Provision of Data from a Variable Energy Resource.
Article 9. Operations.....		
9.1	General.
9.2	Balancing Authority Area Notification.
9.3	Transmission Provider Obligations.
9.4	Interconnection Customer Obligations.
9.5	Start-Up and Synchronization.
9.6	Reactive Power and Primary Frequency Response.
9.6.1	Power Factor Design Criteria.
9.6.1.1	Synchronous Generation.
9.6.1.2	Non-Synchronous Generation.
9.6.2	Voltage Schedules.
9.6.2.1	Voltage Regulators.
9.6.3	Payment for Reactive Power.
9.6.4	Primary Frequency Response.
9.6.4.1	Governor or Equivalent Controls.
9.6.4.2	Timely and Sustained Response.
9.6.4.3	Exemptions.
9.6.4.4	Electric Storage Resources.
9.7	Outages and Interruptions.
9.7.1	Outages.
9.7.1.1	Outage Authority and Coordination.
9.7.1.2	Outage Schedules.
9.7.1.3	Outage Restoration.

9.7.2	Interruption of Service.....	
9.7.2.1	
9.7.2.2	
9.7.2.3	
9.7.2.4	
9.7.2.5	
9.7.3	Ride Through Capability and Performance.....	
9.7.4	System Protection and Other Control Requirements.....	
9.7.4.1	System Protection Facilities.....	
9.7.4.2	
9.7.4.3	
9.7.4.4	
9.7.4.5	
9.7.4.6	
9.7.5	Requirements for Protection.....	
9.7.6	Power Quality.....	
9.8	Switching and Tagging Rules.....	
9.9	Use of Interconnection Facilities by Third Parties.....	
9.9.1	Purpose of Interconnection Facilities.....	
9.9.2	Third Party Users.....	
9.10	Disturbance Analysis Data Exchange.....	
Article 10.	Maintenance.....	
10.1	Transmission Provider Obligations.....	
10.2	Interconnection Customer Obligations.....	
10.3	Coordination.....	
10.4	Secondary Systems.....	
10.5	Operating and Maintenance Expenses.....	
Article 11.	Performance Obligation.....	
11.1	Interconnection Customer Interconnection Facilities.....	
11.2	Transmission Provider's Interconnection Facilities.....	
11.3	Network Upgrades and Distribution Upgrades.....	
11.4	Transmission Credits.....	
11.4.1	Repayment of Amounts Advanced for Network Upgrades.....	
11.4.2	Special Provisions for Affected Systems.....	
11.4.3	
11.5	Provision of Security.....	
11.5.1	
11.5.2	
11.5.3	
11.6	Interconnection Customer Compensation.....	

11.6.1	Interconnection Customer Compensation for Actions During Emergency Condition.	
Article 12.	Invoice.....	
12.1	General.....	
12.2	Final Invoice.....	
12.3	Payment.....	
12.4	Disputes.....	
Article 13.	Emergencies	
13.1	Definition.....	
13.2	Obligations.....	
13.3	Notice.....	
13.4	Immediate Action.....	
13.5	Transmission Provider Authority.....	
13.5.1	General.....	
13.5.2	Reduction and Disconnection.....	
13.6	Interconnection Customer Authority.....	
13.7	Limited Liability.....	
Article 14.	Regulatory Requirements and Governing Law	
14.1	Regulatory Requirements.....	
14.2	Governing Law.....	
14.2.1	
14.2.2	
14.2.3	
Article 15.	Notices.....	
15.1	General.....	
15.2	Billings and Payments.....	
15.3	Alternate Forms of Notice.....	
15.4	Operations and Maintenance Notice.....	
Article 16.	Force Majeure	
16.1	Force Majeure.....	
16.1.1	
16.1.2	
Article 17.	Default.....	
17.1	Default.....	
17.1.1	General.....	
17.1.2	Right to Terminate.....	
17.2	Violation of Operating Assumptions for Generating Facilities.....	
Article 18.	Indemnity, Consequential Damages, and Insurance.....	
18.1	Indemnity.....	
18.1.1	Indemnified Person.....	
18.1.2	Indemnifying Party.....	

18.1.3	Indemnity Procedures
18.2	Consequential Damages
18.3	Insurance
18.3.1	
18.3.2	
18.3.3	
18.3.4	
18.3.5	
18.3.6	
18.3.7	
18.3.8	
18.3.9	
18.3.10	
18.3.11	
Article 19.	Assignment
19.1	Assignment
Article 20.	Severability
20.1	Severability
Article 21.	Comparability
21.1	Comparability
Article 22.	Confidentiality
22.1	Confidentiality
22.1.1	Term
22.1.2	Scope
22.1.3	Release of Confidential Information
22.1.4	Rights
22.1.5	No Warranties
22.1.6	Standard of Care
22.1.7	Order of Disclosure
22.1.8	Termination of Agreement
22.1.9	Remedies
22.1.10	Disclosure to FERC, its Staff, or a State
22.1.11	
Article 23.	Environmental Releases
23.1	
Article 24.	Information Requirements
24.1	Information Acquisition
24.2	Information Submission by Transmission Provider
24.3	Updated Information Submission by Interconnection Customer
24.4	Information Supplementation

Article 25.	Information Access and Audit Rights
25.1	Information Access.....
25.2	Reporting of Non-Force Majeure Events.....
25.3	Audit Rights.....
25.4	Audit Rights Periods.....
25.4.1	Audit Rights Period for Construction-Related Accounts and Records.....
25.4.2	Audit Rights Period for All Other Accounts and Records.....
25.5	Audit Results.....
Article 26.	Subcontractors
26.1	General.....
26.2	Responsibility of Principal.....
26.3	No Limitation by Insurance.....
Article 27.	Disputes.....
27.1	Submission.....
27.2	External Arbitration Procedures.....
27.3	Arbitration Decisions.....
27.4	Costs.....
Article 28.	Representations, Warranties, and Covenants
28.1	General.....
28.1.1	Good Standing.....
28.1.2	Authority.....
28.1.3	No Conflict.....
28.1.4	Consent and Approval.....
Article 29.	Joint Operating Committee.....
29.1	Joint Operating Committee.....
29.1.1
29.1.2
29.1.3
29.1.4
29.1.5
29.1.6
Article 30.	Miscellaneous.....
30.1	Binding Effect.....
30.2	Conflicts.....
30.3	Rules of Interpretation.....
30.4	Entire Agreement.....
30.5	No Third Party Beneficiaries.....
30.6	Waiver.....
30.7	Headings.....
30.8	Multiple Counterparts.....

30.9	Amendment.....	
30.10	Modification by the Parties.....	
30.11	Reservation of Rights.....	
30.12	No Partnership.....	
Appendix A.	Interconnection Facilities, Network Upgrades and Distribution Upgrades.....	
Appendix B.	Milestones	
Appendix C.	Interconnection Details.....	
Appendix D.	Security Arrangements Details	
Appendix E.	Commercial Operation Date	
Appendix F.	Addresses for Delivery of Notices and Billings	
Appendix G.	Interconnection Requirements for a Wind Generating Plant	
Appendix H.	Operating Assumptions for Generating Facility.....	

**AMENDED AND RESTATED AMENDED AND RESTATED LARGE GENERATOR
INTERCONNECTION AGREEMENT**

THIS AMENDED AND RESTATED AMENDED AND RESTATED LARGE GENERATOR INTERCONNECTION AGREEMENT (“Agreement” or “LGIA”) is made and entered into this 25th day of November 2024, by and between Placid Solar II, LLC, a limited liability company organized and existing under the laws of the State/Commonwealth of Delaware (“Interconnection Customer” with a Large Generating Facility), and Duke Energy Florida, LLC, a limited liability company organized and existing under the laws of the State/Commonwealth of Florida (“Transmission Provider and/or Transmission Owner”). Interconnection Customer and Transmission Provider each may be referred to as a “Party” or collectively as the “Parties.”

Recitals

WHEREAS, Transmission Provider operates the Transmission System; and,

WHEREAS, Interconnection Customer intends to own, lease and/or control and operate the Generating Facility identified as a Large Generating Facility in Appendix C to this Agreement; and,

WHEREAS, Interconnection Customer and Transmission Provider have agreed to enter into this Agreement for the purpose of interconnecting the Large Generating Facility with the Transmission System;

NOW, THEREFORE, in consideration of and subject to the mutual covenants contained herein, it is agreed:

When used in this Standard Amended and Restated Large Generator Interconnection Agreement, terms with initial capitalization that are not defined in Article 1 shall have the meanings specified in the Article in which they are used or the Open Access Transmission Tariff (Tariff).

Article 1. Definitions

Adverse System Impact shall mean the negative effects due to technical or operational limits on conductors or equipment being exceeded that may compromise the safety and reliability of the electric system.

Affected System shall mean an electric system other than Transmission Provider's Transmission System that may be affected by the proposed interconnection.

Affected System Operator shall mean the entity that operates an Affected System.

Affiliate shall mean, with respect to a corporation, partnership, or other entity, each such other corporation, partnership, or other entity that directly or indirectly, through one or more intermediaries, controls, is controlled by, or is under common control with, such corporation, partnership, or other entity.

Ancillary Services shall mean those services that are necessary to support the transmission of capacity and energy from resources to loads while maintaining reliable operation of the Transmission Provider's Transmission System in accordance with Good Utility Practice.

Applicable Laws and Regulations shall mean all duly promulgated applicable federal, state, and local laws, regulations, rules, ordinances, codes, decrees, judgments, directives, or judicial or administrative orders, permits and other duly authorized actions of any Governmental Authority.

Applicable Reliability Standards shall mean the requirements and guidelines of the Electric Reliability Organization and the Balancing Authority Area of the Transmission System to which the Generating Facility is directly interconnected.

Balancing Authority shall mean an entity that integrates resource plans ahead of time, maintains demand and resource balance within a Balancing Authority Area, and supports interconnection frequency in real time.

Balancing Authority Area shall mean the collection of generation, transmission, and loads within the metered boundaries of the Balancing Authority. The Balancing Authority maintains load-resource balance within this area.

Base Case shall mean the base case power flow, short circuit, and stability data bases used for the Interconnection Studies by Transmission Provider or Interconnection Customer.

Breach shall mean the failure of a Party to perform or observe any material term or condition of the Standard Amended and Restated Large Generator Interconnection Agreement.

Breaching Party shall mean a Party that is in Breach of the Standard Amended and Restated Large Generator Interconnection Agreement.

Business Day shall mean Monday through Friday, excluding Federal Holidays.

Calendar Day shall mean any day including Saturday, Sunday or a Federal Holiday.

Cluster shall mean a group of one or more Interconnection Requests that are studied together for the purpose of conducting a Cluster Study.

Cluster Restudy shall mean a restudy of a Cluster Study conducted pursuant to Section 7.5 of the LGIP.

Cluster Study shall mean the evaluation of one or more Interconnection Requests within a Cluster as described in Section 7 of the LGIP.

Clustering shall mean the process whereby one or more Interconnection Requests are studied together, instead of serially, as described in Section 7 of the LGIP.

Commercial Operation shall mean the status of a Generating Facility that has commenced generating electricity for sale, excluding electricity generated during Trial Operation.

Commercial Operation Date of a unit shall mean the date on which the Generating Facility commences Commercial Operation as agreed to by the Parties pursuant to Appendix E to the Standard Amended and Restated Large Generator Interconnection Agreement.

Confidential Information shall mean any confidential, proprietary or trade secret information of a plan, specification, pattern, procedure, design, device, list, concept, policy or compilation relating to the present or planned business of a Party, which is designated as confidential by the Party supplying the information, whether conveyed orally, electronically, in writing, through inspection, or otherwise.

Contingent Facilities shall mean those unbuilt Interconnection Facilities and Network Upgrades upon which the Interconnection Request's costs, timing, and study findings are dependent, and if delayed or not built, could cause a need for restudies of the Interconnection Request or a reassessment of the Interconnection Facilities and/or Network Upgrades and/or costs and timing.

Default shall mean the failure of a Breaching Party to cure its Breach in accordance with Article 17 of the Standard Amended and Restated Large Generator Interconnection Agreement.

Dispute Resolution shall mean the procedure for resolution of a dispute between the Parties in which they will first attempt to resolve the dispute on an informal basis.

Distribution System shall mean the Transmission Provider's facilities and equipment used to transmit electricity to ultimate usage points such as homes and industries directly from nearby generators or from interchanges with higher voltage transmission networks which transport bulk power over longer distances. The voltage levels at which distribution systems operate differ among areas.

Distribution Upgrades shall mean the additions, modifications, and upgrades to the Transmission Provider's Distribution System at or beyond the Point of Interconnection to facilitate interconnection of the Generating Facility and render the transmission service necessary to effect Interconnection Customer's wholesale sale of electricity in interstate commerce. Distribution Upgrades do not include Interconnection Facilities.

Effective Date shall mean the date on which the Standard Amended and Restated Large Generator Interconnection Agreement becomes effective upon execution by the Parties subject to acceptance by FERC, or if filed unexecuted, upon the date specified by FERC.

Electric Reliability Organization shall mean the North American Electric Reliability Corporation or its successor organization.

Emergency Condition shall mean a condition or situation: (1) that in the judgment of the Party making the claim is imminently likely to endanger life or property; or (2) that, in the case of a Transmission Provider, is imminently likely (as determined in a non-discriminatory manner) to cause a material adverse effect on the security of, or damage to Transmission Provider's Transmission System, Transmission Provider's Interconnection Facilities or the electric systems of others to which the Transmission Provider's Transmission System is directly connected; or (3) that, in the case of Interconnection Customer, is imminently likely (as determined in a non-discriminatory manner) to cause a material adverse effect on the security of, or damage to, the Generating Facility or Interconnection Customer's Interconnection Facilities. System restoration and black start shall be considered Emergency Conditions; provided, that Interconnection Customer is not obligated by the Standard Amended and Restated Large Generator Interconnection Agreement to possess black start capability.

Energy Resource Interconnection Service shall mean an Interconnection Service that allows the Interconnection Customer to connect its Generating Facility to the Transmission Provider's Transmission System to be eligible to deliver the Generating Facility's electric output using the existing firm or nonfirm capacity of the Transmission Provider's Transmission System on an as available basis. Energy Resource Interconnection Service in and of itself does not convey transmission service.

Engineering & Procurement (E&P) Agreement shall mean an agreement that authorizes the Transmission Provider to begin engineering and procurement of long lead-time items necessary for the establishment of the interconnection in order to advance the implementation of the Interconnection Request.

Environmental Law shall mean Applicable Laws or Regulations relating to pollution or protection of the environment or natural resources.

Federal Power Act shall mean the Federal Power Act, as amended, 16 U.S.C. §§ 791a et seq.

FERC shall mean the Federal Energy Regulatory Commission (Commission) or its successor.

Force Majeure shall mean any act of God, labor disturbance, act of the public enemy, war, insurrection, riot, fire, storm or flood, explosion, breakage or accident to machinery or equipment, any order, regulation or restriction imposed by governmental, military or lawfully established civilian authorities, or any other cause beyond a Party's control. A Force Majeure event does not include acts of negligence or intentional wrongdoing by the Party claiming Force Majeure.

Generating Facility shall mean Interconnection Customer's device(s) for the production and/or storage for later injection of electricity identified in the Interconnection Request, but shall not include Interconnection Customer's Interconnection Facilities.

Generating Facility Capacity shall mean the net capacity of the Generating Facility or the aggregate net capacity of the Generating Facility where it includes more than one device for the production and/or storage for later injection of electricity.

Good Utility Practice shall mean any of the practices, methods and acts engaged in or approved by a significant portion of the electric industry during the relevant time period, or any of the practices, methods, and acts which, in the exercise of reasonable judgment in light of the facts known at the time the decision was made, could have been expected to accomplish the desired result at a reasonable cost consistent with good business practices, reliability, safety and expedition. Good

Utility Practice is not intended to be limited to the optimum practice, method, or act to the exclusion of all others, but rather to be acceptable practices, methods, or acts generally accepted in the region.

Governmental Authority shall mean any federal, state, local or other governmental regulatory or administrative agency, court, commission, department, board, or other governmental subdivision, legislature, rulemaking board, tribunal, or other governmental authority having jurisdiction over the Parties, their respective facilities, or the respective services they provide, and exercising or entitled to exercise any administrative, executive, police, or taxing authority or power; provided, however, that such term does not include Interconnection Customer, Transmission Provider, or any Affiliate thereof.

Hazardous Substances shall mean any chemicals, materials or substances defined as or included in the definition of “hazardous substances,” “hazardous wastes,” “hazardous materials,” “hazardous constituents,” “restricted hazardous materials,” “extremely hazardous substances,” “toxic substances,” “radioactive substances,” “contaminants,” “pollutants,” “toxic pollutants” or words of similar meaning and regulatory effect under any applicable Environmental Law, or any other chemical, material or substance, exposure to which is prohibited, limited or regulated by any applicable Environmental Law.

Initial Synchronization Date shall mean the date upon which the Generating Facility is initially synchronized and upon which Trial Operation begins.

In-Service Date shall mean the date upon which the Interconnection Customer reasonably expects it will be ready to begin use of the Transmission Provider’s Interconnection Facilities to obtain back feed power.

Interconnection Customer shall mean any entity, including the Transmission Provider, Transmission Owner or any of the Affiliates or subsidiaries of either, that proposes to interconnect its Generating Facility with the Transmission Provider’s Transmission System.

Interconnection Customer’s Interconnection Facilities shall mean all facilities and equipment, as identified in Appendix A of the Standard Amended and Restated Large Generator Interconnection Agreement, that are located between the Generating Facility and the Point of Change of Ownership, including any modification, addition, or upgrades to such facilities and equipment necessary to physically and electrically interconnect the Generating Facility to the Transmission Provider’s Transmission System. Interconnection Customer’s Interconnection Facilities are sole use facilities.

Interconnection Facilities shall mean Transmission Provider’s Interconnection Facilities and Interconnection Customer’s Interconnection Facilities. Collectively, Interconnection Facilities include all facilities and equipment between the Generating Facility and the Point of Interconnection, including any modification, additions or upgrades that are necessary to physically and electrically interconnect the Generating Facility to Transmission Provider’s Transmission System. Interconnection Facilities are sole use facilities and shall not include Distribution Upgrades, Stand Alone Network Upgrades or Network Upgrades.

Interconnection Facilities Study shall mean a study conducted by Transmission Provider or a third party consultant for Interconnection Customer to determine a list of facilities (including Transmission Provider’s Interconnection Facilities and Network Upgrades as identified in the Cluster Study), the cost of those facilities, and the time required to interconnect the Generating Facility with Transmission Provider’s Transmission System. The scope of the study is defined in Section 8 of the LGIP.

Interconnection Facilities Study Agreement shall mean the form of agreement contained in Appendix 3 of the Standard Large Generator Interconnection Procedures for conducting the Interconnection Facilities Study.

Interconnection Request shall mean an Interconnection Customer's request, in the form of Appendix 1 to the LGIP, in accordance with the Tariff, to interconnect a new Generating Facility, or to increase the capacity of, or make a Material Modification to the operating characteristics of, an existing Generating Facility that is interconnected with the Transmission Provider's Transmission System.

Interconnection Service shall mean the service provided by the Transmission Provider associated with interconnecting the Interconnection Customer's Generating Facility to the Transmission Provider's Transmission System and enabling it to receive electric energy and capacity from the Generating Facility at the Point of Interconnection, pursuant to the terms of the Standard Amended and Restated Large Generator Interconnection Agreement and, if applicable, the Transmission Provider's Tariff.

Interconnection Study shall mean any of the following studies: the Cluster Study, the Cluster Restudy, the Surplus Interconnection Service System Impact Study, and the Interconnection Facilities Study, described in the LGIP.

IRS shall mean the Internal Revenue Service.

Joint Operating Committee shall be a group made up of representatives from Interconnection Customers and the Transmission Provider to coordinate operating and technical considerations of Interconnection Service.

Large Generating Facility shall mean a Generating Facility having a Generating Facility Capacity of more than 20 MW.

LGIA Deposit shall mean the deposit Interconnection Customer submits when returning the executed LGIA, or within ten 10 Business Days of requesting that the LGIA be filed unexecuted at the Commission, in accordance with Section 11.3 of the LGIP.

Loss shall mean any and all losses relating to injury to or death of any person or damage to property, demand, suits, recoveries, costs and expenses, court costs, attorney fees, and all other obligations by or to third parties, arising out of or resulting from the other Party's performance, or non-performance of its obligations under the Standard Amended and Restated Large Generator Interconnection Agreement on behalf of the Indemnifying Party, except in cases of gross negligence or intentional wrongdoing by the Indemnifying Party.

Material Modification shall mean those modifications that have a material impact on the cost or timing of any Interconnection Request with an equal or later Queue Position.

Metering Equipment shall mean all metering equipment installed or to be installed at the Generating Facility pursuant to the Standard Amended and Restated Large Generator Interconnection Agreement at the metering points, including but not limited to instrument transformers, MWh-meters, data acquisition equipment, transducers, remote terminal unit, communications equipment, phone lines, and fiber optics.

Network Resource shall mean any designated generating resource owned, purchased, or leased by a Network Customer under the Network Integration Transmission Service Tariff. Network

Resources do not include any resource, or any portion thereof, that is committed for sale to third parties or otherwise cannot be called upon to meet the Network Customer's Network Load on a non-interruptible basis.

Network Resource Interconnection Service shall mean an Interconnection Service that allows the Interconnection Customer to integrate its Large Generating Facility with the Transmission Provider's Transmission System (1) in a manner comparable to that in which the Transmission Provider integrates its generating facilities to serve native load customers; or (2) in an RTO or ISO with market based congestion management, in the same manner as Network Resources. Network Resource Interconnection Service in and of itself does not convey transmission service.

Network Upgrades shall mean the additions, modifications, and upgrades to the Transmission Provider's Transmission System required at or beyond the point at which the Interconnection Facilities connect to the Transmission Provider's Transmission System to accommodate the interconnection of the Large Generating Facility to the Transmission Provider's Transmission System.

Notice of Dispute shall mean a written notice of a dispute or claim that arises out of or in connection with the Standard Amended and Restated Large Generator Interconnection Agreement or its performance.

Optional Interconnection Study shall mean a sensitivity analysis based on assumptions specified by the Interconnection Customer in the Optional Interconnection Study Agreement.

Optional Interconnection Study Agreement shall mean the form of agreement contained in Appendix 4 of the LGIP for conducting the Optional Interconnection Study.

Party or Parties shall mean Transmission Provider, Transmission Owner, Interconnection Customer or any combination of the above.

Point of Change of Ownership shall mean the point, as set forth in Appendix A to the Standard Amended and Restated Large Generator Interconnection Agreement, where the Interconnection Customer's Interconnection Facilities connect to the Transmission Provider's Interconnection Facilities.

Point of Interconnection shall mean the point, as set forth in Appendix A to the Standard Amended and Restated Large Generator Interconnection Agreement, where the Interconnection Facilities connect to the Transmission Provider's Transmission System.

Proportional Impact Method shall mean a technical analysis conducted by Transmission Provider to determine the degree to which each Generating Facility in the Cluster Study contributes to the need for a specific System Network Upgrade.

Provisional Interconnection Service shall mean Interconnection Service provided by Transmission Provider associated with interconnecting the Interconnection Customer's Generating Facility to Transmission Provider's Transmission System and enabling that Transmission System to receive electric energy and capacity from the Generating Facility at the Point of Interconnection, pursuant to the terms of the Provisional Amended and Restated Large Generator Interconnection Agreement and, if applicable, the Tariff.

Provisional Amended and Restated Large Generator Interconnection Agreement shall mean the interconnection agreement for Provisional Interconnection Service established between

Transmission Provider and/or the Transmission Owner and the Interconnection Customer. This agreement shall take the form of the Amended and Restated Large Generator Interconnection Agreement, modified for provisional purposes.

Queue Position shall mean the order of a valid Interconnection Request, relative to all other pending valid Interconnection Requests, established pursuant to Section 4.1 of the LGIP.

Reasonable Efforts shall mean, with respect to an action required to be attempted or taken by a Party under the Standard Amended and Restated Large Generator Interconnection Agreement, efforts that are timely and consistent with Good Utility Practice and are otherwise substantially equivalent to those a Party would use to protect its own interests.

Scoping Meeting shall mean the meeting between representatives of Interconnection Customer(s) and Transmission Provider conducted for the purpose of discussing the proposed Interconnection Request and any alternative interconnection options, exchanging information including any transmission data and earlier study evaluations that would be reasonably expected to impact such interconnection options, refining information and models provided by Interconnection Customer(s), discussing the Cluster Study materials posted to OASIS pursuant to Section 3.5 of the LGIP, and analyzing such information.

Site Control shall mean the exclusive land right to develop, construct, operate, and maintain the Generating Facility over the term of expected operation of the Generating Facility. Site Control may be demonstrated by documentation establishing: (1) ownership of, a leasehold interest in, or a right to develop a site of sufficient size to construct and operate the Generating Facility; (2) an option to purchase or acquire a leasehold site of sufficient size to construct and operate the Generating Facility for such purpose; or (3) any other documentation that clearly demonstrates the right of Interconnection Customer to exclusively occupy a site of sufficient size to construct and operate the Generating Facility. Transmission Provider will maintain acreage requirements for each Generating Facility type on its OASIS or public website.

Small Generating Facility shall mean a Generating Facility that has a Generating Facility Capacity of no more than 20 MW.

Stand Alone Network Upgrades shall mean Network Upgrades that are not part of an Affected System that an Interconnection Customer may construct without affecting day-to-day operations of the Transmission System during their construction and the following conditions are met: (1) a Substation Network Upgrade must only be required for a single Interconnection Customer in the Cluster and no other Interconnection Customer in that Cluster is required to interconnect to the same Substation Network Upgrades, and (2) a System Network Upgrade must only be required for a single Interconnection Customer in the Cluster, as indicated under Transmission Provider's Proportional Impact Method. Both Transmission Provider and Interconnection Customer must agree as to what constitutes Stand Alone Network Upgrades and identify them in Appendix A to the Standard Amended and Restated Large Generator Interconnection Agreement. If Transmission Provider and Interconnection Customer disagree about whether a particular Network Upgrade is a Stand Alone Network Upgrade, Transmission Provider must provide Interconnection Customer a written technical explanation outlining why Transmission Provider does not consider the Network Upgrade to be a Stand Alone Network Upgrade within 15 days of its determination.

Standard Amended and Restated Large Generator Interconnection Agreement (LGIA) shall mean the form of interconnection agreement applicable to an Interconnection Request pertaining to a Large Generating Facility that is included in the Transmission Provider's Tariff.

Standard Large Generator Interconnection Procedures (LGIP) shall mean the interconnection procedures applicable to an Interconnection Request pertaining to a Large Generating Facility that are included in the Transmission Provider's Tariff.

Substation Network Upgrades shall mean Network Upgrades that are required at the substation located at the Point of Interconnection.

Surplus Interconnection Service shall mean any unneeded portion of Interconnection Service established in a Amended and Restated Large Generator Interconnection Agreement, such that if Surplus Interconnection Service is utilized the total amount of Interconnection Service at the Point of Interconnection would remain the same.

System Network Upgrades shall mean Network Upgrades that are required beyond the substation located at the Point of Interconnection.

System Protection Facilities shall mean the equipment, including necessary protection signal communications equipment, required to protect (1) the Transmission Provider's Transmission System from faults or other electrical disturbances occurring at the Generating Facility and (2) the Generating Facility from faults or other electrical system disturbances occurring on the Transmission Provider's Transmission System or on other delivery systems or other generating systems to which the Transmission Provider's Transmission System is directly connected.

Tariff shall mean the Transmission Provider's Tariff through which open access transmission service and Interconnection Service are offered, as filed with FERC, and as amended or supplemented from time to time, or any successor tariff.

Transmission Owner shall mean an entity that owns, leases or otherwise possesses an interest in the portion of the Transmission System at the Point of Interconnection and may be a Party to the Standard Amended and Restated Large Generator Interconnection Agreement to the extent necessary.

Transmission Provider shall mean the public utility (or its designated agent) that owns, controls, or operates transmission or distribution facilities used for the transmission of electricity in interstate commerce and provides transmission service under the Tariff. The term Transmission Provider should be read to include the Transmission Owner when the Transmission Owner is separate from the Transmission Provider.

Transmission Provider's Interconnection Facilities shall mean all facilities and equipment owned, controlled, or operated by Transmission Provider from the Point of Change of Ownership to the Point of Interconnection as identified in Appendix A to the Standard Amended and Restated Large Generator Interconnection Agreement, including any modifications, additions or upgrades to such facilities and equipment. Transmission Provider's Interconnection Facilities are sole use facilities and shall not include Distribution Upgrades, Stand Alone Network Upgrades or Network Upgrades.

Transmission System shall mean the facilities owned, controlled or operated by the Transmission Provider or Transmission Owner that are used to provide transmission service under the Tariff.

Trial Operation shall mean the period during which Interconnection Customer is engaged in on-site test operations and commissioning of the Generating Facility prior to Commercial Operation.

Variable Energy Resource shall mean a device for the production of electricity that is characterized by an energy source that: (1) is renewable; (2) cannot be stored by the facility owner or operator; and (3) has variability that is beyond the control of the facility owner or operator.

Withdrawal Penalty shall mean the penalty assessed by Transmission Provider to an Interconnection Customer that chooses to withdraw or is deemed withdrawn from Transmission Provider's interconnection queue or whose Generating Facility does not otherwise reach Commercial Operation. The calculation of the Withdrawal Penalty is set forth in Section 3.7.1 of the LGIP.

Article 2. Effective Date, Term, and Termination

2.1 Effective Date. This LGIA shall become effective upon execution by the Parties subject to acceptance by FERC (if applicable), or if filed unexecuted, upon the date specified by FERC. Transmission Provider shall promptly file this LGIA with FERC upon execution in accordance with Article 3.1, if required.

2.2 Term of Agreement. Subject to the provisions of Article 2.3, this LGIA shall remain in effect for a period of ten (10) years from the Effective Date or such other longer period as Interconnection Customer may request (Term to be specified in individual agreements) and shall be automatically renewed for each successive one-year period thereafter.

2.3 Termination Procedures.

2.3.1 Written Notice. This LGIA may be terminated by Interconnection Customer after giving Transmission Provider ninety (90) Calendar Days advance written notice, or by Transmission Provider notifying FERC after the Generating Facility permanently ceases Commercial Operation.

2.3.2 Default. Either Party may terminate this LGIA in accordance with Article 17.

2.3.3 Notwithstanding Articles 2.3.1 and 2.3.2, no termination shall become effective until the Parties have complied with all Applicable Laws and Regulations applicable to such termination, including the filing with FERC of a notice of termination of this LGIA, which notice has been accepted for filing by FERC.

2.4 Termination Costs. If a Party elects to terminate this Agreement pursuant to Article 2.3 above, each Party shall pay all costs incurred (including any cancellation costs relating to orders or contracts for Interconnection Facilities and equipment) or charges assessed by the other Party, as of the date of the other Party's receipt of such notice of termination, that are the responsibility of the Terminating Party under this LGIA. In the event of termination by a Party, the Parties shall use commercially Reasonable Efforts to mitigate the costs, damages and charges arising as a consequence of termination. Upon termination of this LGIA, unless otherwise ordered or approved by FERC:

2.4.1 With respect to any portion of Transmission Provider's Interconnection Facilities that have not yet been constructed or installed, Transmission Provider shall to the extent possible and with

Interconnection Customer's authorization cancel any pending orders of, or return, any materials or equipment for, or contracts for construction of, such facilities; provided that in the event Interconnection Customer elects not to authorize such cancellation, Interconnection Customer shall assume all payment obligations with respect to such materials, equipment, and contracts, and Transmission Provider shall deliver such material and equipment, and, if necessary, assign such contracts, to Interconnection Customer as soon as practicable, at Interconnection Customer's expense. To the extent that Interconnection Customer has already paid Transmission Provider for any or all such costs of materials or equipment not taken by Interconnection Customer, Transmission Provider shall promptly refund such amounts to Interconnection Customer, less any costs, including penalties incurred by Transmission Provider to cancel any pending orders of or return such materials, equipment, or contracts.

If an Interconnection Customer terminates this LGIA, it shall be responsible for all costs incurred in association with that Interconnection Customer's interconnection, including any cancellation costs relating to orders or contracts for Interconnection Facilities and equipment, and other expenses including any Network Upgrades for which Transmission Provider has incurred expenses and has not been reimbursed by Interconnection Customer.

2.4.2 Transmission Provider may, at its option, retain any portion of such materials, equipment, or facilities that Interconnection Customer chooses not to accept delivery of, in which case Transmission Provider shall be responsible for all costs associated with procuring such materials, equipment, or facilities.

2.4.3 With respect to any portion of the Interconnection Facilities, and any other facilities already installed or constructed pursuant to the terms of this LGIA, Interconnection Customer shall be responsible for all costs associated with the removal, relocation or other disposition or retirement of such materials, equipment, or facilities.

2.5 Disconnection. Upon termination of this LGIA, the Parties will take all appropriate steps to disconnect the Large Generating Facility from the Transmission System. All costs required to effectuate such disconnection shall be borne by the terminating Party, unless such termination resulted from the non-terminating Party's Default of this LGIA or such non-terminating Party otherwise is responsible for these costs under this LGIA.

2.6 Survival. This LGIA shall continue in effect after termination to the extent necessary to provide for final billings and payments and for costs incurred hereunder, including billings and payments pursuant to this LGIA; to permit the determination and enforcement of liability and indemnification obligations arising from acts or events that occurred while this LGIA was in effect; and to permit each Party to have access to the lands of the other Party pursuant to this LGIA or other applicable agreements, to disconnect, remove or salvage its own facilities and equipment.

Article 3. Regulatory Filings

3.1 Filing. Transmission Provider shall file this LGIA (and any amendment hereto) with the appropriate Governmental Authority, if required. Interconnection Customer may request that any information so provided be subject to the confidentiality provisions of Article 22. If

Interconnection Customer has executed this LGIA, or any amendment thereto, Interconnection Customer shall reasonably cooperate with Transmission Provider with respect to such filing and to provide any information reasonably requested by Transmission Provider needed to comply with applicable regulatory requirements.

Article 4. Scope of Service

4.1 Interconnection Product Options. Interconnection Customer has selected the following (checked) type of Interconnection Service:

4.1.1 Energy Resource Interconnection Service.

4.1.1.1 The Product. Energy Resource Interconnection Service allows Interconnection Customer to connect the Large Generating Facility to the Transmission System and be eligible to deliver the Large Generating Facility's output using the existing firm or non-firm capacity of the Transmission System on an "as available" basis. To the extent Interconnection Customer wants to receive Energy Resource Interconnection Service, Transmission Provider shall construct facilities identified in Attachment A.

4.1.1.2 Transmission Delivery Service Implications. Under Energy Resource Interconnection Service, Interconnection Customer will be eligible to inject power from the Large Generating Facility into and deliver power across the interconnecting Transmission Provider's Transmission System on an "as available" basis up to the amount of MWs identified in the applicable stability and steady state studies to the extent the upgrades initially required to qualify for Energy Resource Interconnection Service have been constructed. Where eligible to do so (e.g., PJM, ISO-NE, NYISO), Interconnection Customer may place a bid to sell into the market up to the maximum identified Large Generating Facility output, subject to any conditions specified in the interconnection service approval, and the Large Generating Facility will be dispatched to the extent Interconnection Customer's bid clears. In all other instances, no transmission delivery service from the Large Generating Facility is assured, but Interconnection Customer may obtain Point-to-Point Transmission Service, Network Integration Transmission Service, or be used for secondary network transmission service, pursuant to Transmission Provider's Tariff, up to the maximum output identified in the stability and steady state studies. In those instances, in order for Interconnection Customer to obtain the right to deliver or inject energy beyond the Large Generating Facility Point of Interconnection or to improve its ability to do so, transmission delivery service must be obtained pursuant to the provisions of Transmission Provider's Tariff. The Interconnection Customer's ability to inject its Large Generating Facility output beyond the Point of Interconnection, therefore, will depend on the existing capacity of Transmission Provider's Transmission System at such time as a transmission service request is made that would accommodate such delivery. The provision of firm Point-to-Point Transmission Service or Network Integration Transmission Service may require the construction of additional Network Upgrades.

✓ 4.1.2 Network Resource Interconnection Service.

4.1.2.1 The Product. Transmission Provider must conduct the necessary studies and construct the Network Upgrades needed to integrate the Large Generating Facility (1) in a manner comparable to that in which Transmission Provider integrates its generating facilities to serve native load customers; or (2) in an ISO or RTO with market based congestion management, in the same manner as all Network Resources. To the extent Interconnection Customer wants to receive Network Resource Interconnection Service, Transmission Provider shall construct the facilities identified in Attachment A to this LGIA.

4.1.2.2 Transmission Delivery Service Implications. Network Resource Interconnection Service allows Interconnection Customer's Large Generating Facility to be designated by any Network Customer under the Tariff on Transmission Provider's Transmission System as a Network Resource, up to the Large Generating Facility's full output, on the same basis as existing Network Resources interconnected to Transmission Provider's Transmission System, and to be studied as a Network Resource on the assumption that such a designation will occur. Although Network Resource Interconnection Service does not convey a reservation of transmission service, any Network Customer under the Tariff can utilize its network service under the Tariff to obtain delivery of energy from the interconnected Interconnection Customer's Large Generating Facility in the same manner as it accesses Network Resources. A Large Generating Facility receiving Network Resource Interconnection Service may also be used to provide Ancillary Services after technical studies and/or periodic analyses are performed with respect to the Large Generating Facility's ability to provide any applicable Ancillary Services, provided that such studies and analyses have been or would be required in connection with the provision of such Ancillary Services by any existing Network Resource. However, if an Interconnection Customer's Large Generating Facility has not been designated as a Network Resource by any load, it cannot be required to provide Ancillary Services except to the extent such requirements extend to all generating facilities that are similarly situated. The provision of Network Integration Transmission Service or firm Point-to-Point Transmission Service may require additional studies and the construction of additional upgrades. Because such studies and upgrades would be associated with a request for delivery service under the Tariff, cost responsibility for the studies and upgrades would be in accordance with FERC's policy for pricing transmission delivery services.

Network Resource Interconnection Service does not necessarily provide Interconnection Customer with the capability to physically deliver the output of its Large Generating Facility to any particular load on Transmission Provider's Transmission System without incurring congestion costs. In the event of transmission constraints on Transmission Provider's Transmission System, Interconnection Customer's Large Generating Facility shall be subject to the applicable congestion management procedures in Transmission Provider's Transmission System in the same manner as Network Resources.

There is no requirement either at the time of study or interconnection, or at any point in the future, that Interconnection Customer's Large Generating Facility be designated as a Network Resource by a Network Service Customer under the Tariff or that Interconnection Customer identify a specific buyer (or sink). To the extent a Network Customer does designate the Large Generating Facility as a Network Resource, it must do so pursuant to Transmission Provider's Tariff.

Once an Interconnection Customer satisfies the requirements for obtaining Network Resource Interconnection Service, any future transmission service request for delivery from the Large Generating Facility within Transmission Provider's Transmission System of any amount of capacity and/or energy, up to the amount initially studied, will not require that any additional studies be performed or that any further upgrades associated with such Large Generating Facility be undertaken, regardless of whether or not such Large Generating Facility is ever designated by a Network Customer as a Network Resource and regardless of changes in ownership of the Large Generating Facility. However, the reduction or elimination of congestion or redispatch costs may require additional studies and the construction of additional upgrades.

To the extent Interconnection Customer enters into an arrangement for long term transmission service for deliveries from the Large Generating Facility outside Transmission Provider's Transmission System, such request may require additional studies and upgrades in order for Transmission Provider to grant such request.

4.2 Provision of Service. Transmission Provider shall provide Interconnection Service for the Large Generating Facility at the Point of Interconnection.

4.3 Performance Standards. Each Party shall perform all of its obligations under this LGIA in accordance with Applicable Laws and Regulations, Applicable Reliability Standards, and Good Utility Practice, and to the extent a Party is required or prevented or limited in taking any action by such regulations and standards, such Party shall not be deemed to be in Breach of this LGIA for its compliance therewith. If such Party is a Transmission Provider or Transmission Owner, then that Party shall amend the LGIA and submit the amendment to FERC for approval.

4.4 No Transmission Delivery Service. The execution of this LGIA does not constitute a request for, nor the provision of, any transmission delivery service under Transmission Provider's Tariff, and does not convey any right to deliver electricity to any specific customer or Point of Delivery.

4.5 Interconnection Customer Provided Services. The services provided by Interconnection Customer under this LGIA are set forth in Article 9.6 and Article 13.5.1. Interconnection Customer shall be paid for such services in accordance with Article 11.6.

Article 5. Interconnection Facilities Engineering, Procurement, & Construction

5.1 Options. Unless otherwise mutually agreed to between the Parties, Interconnection Customer shall select the In-Service Date, Initial Synchronization Date, and Commercial Operation Date; and either the Standard Option or Alternate Option set forth below, and such dates and selected option shall be set forth in Appendix B, Milestones. At the same time, Interconnection Customer shall indicate whether it elects to exercise the Option to Build set forth in Article 5.1.3 below. If the dates designated by Interconnection Customer are not acceptable to Transmission Provider, Transmission Provider shall so notify Interconnection Customer within thirty (30) Calendar Days. Upon receipt of the notification that Interconnection Customer's designated dates are not acceptable to Transmission Provider, the Interconnection Customer shall notify Transmission Provider within thirty (30) Calendar Days whether it elects to exercise the Option to Build if it has not already elected to exercise the Option to Build.

5.1.1 Standard Option. Transmission Provider shall design, procure, and construct Transmission Provider's Interconnection Facilities and Network Upgrades, using Reasonable Efforts to complete Transmission Provider's Interconnection Facilities and Network Upgrades by the dates set forth in Appendix B, Milestones. Transmission Provider shall not be required to undertake any action which is inconsistent with its standard safety practices, its material and equipment specifications, its design criteria and construction procedures, its labor agreements, and Applicable Laws and Regulations. In the event Transmission Provider reasonably expects that it will not be able to complete Transmission Provider's Interconnection Facilities and Network Upgrades by the specified dates, Transmission Provider shall promptly provide written notice to Interconnection Customer and shall undertake Reasonable Efforts to meet the earliest dates thereafter.

5.1.2 Alternate Option. If the dates designated by Interconnection Customer are acceptable to Transmission Provider, Transmission Provider shall so notify Interconnection Customer within thirty (30) Calendar Days, and shall assume responsibility for the design, procurement and construction of Transmission Provider's Interconnection Facilities by the designated dates.

If Transmission Provider subsequently fails to complete Transmission Provider's Interconnection Facilities by the In-Service Date, to the extent necessary to provide back feed power; or fails to complete Network Upgrades by the Initial Synchronization Date to the extent necessary to allow for Trial Operation at full power output, unless other arrangements are made by the Parties for such Trial Operation; or fails to complete the Network Upgrades by the Commercial Operation Date, as such dates are reflected in Appendix B, Milestones; Transmission Provider shall pay Interconnection Customer liquidated damages in accordance with Article 5.3, Liquidated Damages, provided, however, the dates designated by Interconnection Customer shall be extended day for day for each day that the applicable RTO or ISO refuses to grant clearances to install equipment.

5.1.3 Option to Build. Interconnection Customer shall have the option to assume responsibility for the design, procurement and construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades on the dates specified in Article 5.1.2. Transmission Provider and Interconnection Customer must agree as to what constitutes Stand Alone Network Upgrades and identify such Stand Alone Network Upgrades in Appendix A. Except for Stand Alone Network Upgrades, Interconnection Customer shall have no right to construct Network Upgrades under this option.

5.1.4 Negotiated Option. If the dates designated by Interconnection Customer are not acceptable to Transmission Provider, the Parties shall in good faith attempt to negotiate terms and conditions (including revision of the specified dates and liquidated damages, the provision of incentives, or the procurement and construction of all facilities other than Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades if the Interconnection Customer elects to exercise the Option to Build under Article 5.1.3). If the Parties are unable to reach agreement on such terms and conditions, then pursuant to Article 5.1.1 (Standard Option), Transmission Provider shall assume responsibility for the design, procurement, and construction of all facilities other than Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades if the Interconnection Customer elects to exercise the Option to Build.

5.2 General Conditions Applicable to Option to Build. If Interconnection Customer assumes responsibility for the design, procurement and construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades,

- (1) Interconnection Customer shall engineer, procure equipment, and construct Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades (or portions thereof) using Good Utility Practice and using standards and specifications provided in advance by Transmission Provider;
- (2) Interconnection Customer's engineering, procurement and construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades shall comply with all requirements of law to which Transmission Provider would be subject in the engineering, procurement or construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades;
- (3) Transmission Provider shall review and approve the engineering design, equipment acceptance tests, and the construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades;
- (4) prior to commencement of construction, Interconnection Customer shall provide to Transmission Provider a schedule for construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades, and shall promptly respond to requests for information from Transmission Provider;

(5) at any time during construction, Transmission Provider shall have the right to gain unrestricted access to Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades and to conduct inspections of the same;

(6) at any time during construction, should any phase of the engineering, equipment procurement, or construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades not meet the standards and specifications provided by Transmission Provider, Interconnection Customer shall be obligated to remedy deficiencies in that portion of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades;

(7) Interconnection Customer shall indemnify Transmission Provider for claims arising from Interconnection Customer's construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades under the terms and procedures applicable to Article 18.1 Indemnity;

(8) Interconnection Customer shall transfer control of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades to Transmission Provider;

(9) Unless Parties otherwise agree, Interconnection Customer shall transfer ownership of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades to Transmission Provider;

(10) Transmission Provider shall approve and accept for operation and maintenance Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades to the extent engineered, procured, and constructed in accordance with this Article 5.2; and

(11) Interconnection Customer shall deliver to Transmission Provider "as-built" drawings, information, and any other documents that are reasonably required by Transmission Provider to assure that the Interconnection Facilities and Stand Alone Network Upgrades are built to the standards and specifications required by Transmission Provider.

(12) If Interconnection Customer exercises the Option to Build pursuant to Article 5.1.3, Interconnection Customer shall pay Transmission Provider the agreed upon amount of [\$ PLACEHOLDER] for Transmission Provider to execute the responsibilities enumerated to Transmission Provider under Article 5.2. Transmission Provider shall invoice Interconnection Customer for this total amount to be divided on a monthly basis pursuant to Article 12.

5.3 Liquidated Damages. The actual damages to Interconnection Customer, in the event Transmission Provider's Interconnection Facilities or Network Upgrades are not completed by the dates designated by Interconnection Customer and accepted by Transmission Provider pursuant to subparagraphs 5.1.2 or 5.1.4, above, may include Interconnection Customer's fixed operation and maintenance costs and lost opportunity costs. Such actual damages are uncertain and impossible to determine at this time. Because of such uncertainty, any liquidated damages paid by Transmission Provider to Interconnection Customer in the event that Transmission Provider does not complete any portion of Transmission Provider's Interconnection Facilities or Network Upgrades by the applicable dates, shall be an amount equal to $\frac{1}{2}$ of 1 percent per day of the actual cost of Transmission Provider's Interconnection Facilities and Network Upgrades, in the aggregate, for which Transmission Provider has assumed responsibility to design, procure and construct.

However, in no event shall the total liquidated damages exceed 20 percent of the actual cost of Transmission Provider's Interconnection Facilities and Network Upgrades for which Transmission Provider has assumed responsibility to design, procure, and construct. The foregoing payments

will be made by Transmission Provider to Interconnection Customer as just compensation for the damages caused to Interconnection Customer, which actual damages are uncertain and impossible to determine at this time, and as reasonable liquidated damages, but not as a penalty or a method to secure performance of this LGIA. Liquidated damages, when the Parties agree to them, are the exclusive remedy for the Transmission Provider's failure to meet its schedule.

No liquidated damages shall be paid to Interconnection Customer if: (1) Interconnection Customer is not ready to commence use of Transmission Provider's Interconnection Facilities or Network Upgrades to take the delivery of power for the Large Generating Facility's Trial Operation or to export power from the Large Generating Facility on the specified dates, unless Interconnection Customer would have been able to commence use of Transmission Provider's Interconnection Facilities or Network Upgrades to take the delivery of power for Large Generating Facility's Trial Operation or to export power from the Large Generating Facility, but for Transmission Provider's delay; (2) Transmission Provider's failure to meet the specified dates is the result of the action or inaction of Interconnection Customer or any other Interconnection Customer who has entered into an LGIA with Transmission Provider or any cause beyond Transmission Provider's reasonable control or reasonable ability to cure; (3) the Interconnection Customer has assumed responsibility for the design, procurement and construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades; or (4) the Parties have otherwise agreed.

5.4 Power System Stabilizers. Interconnection Customer shall procure, install, maintain, and operate Power System Stabilizers in accordance with the guidelines and procedures established by the Electric Reliability Organization. Transmission Provider reserves the right to reasonably establish minimum acceptable settings for any installed Power System Stabilizers, subject to the design and operating limitations of the Large Generating Facility. If the Large Generating Facility's Power System Stabilizers are removed from service or not capable of automatic operation, Interconnection Customer shall immediately notify Transmission Provider's system operator, or its designated representative. The requirements of this paragraph shall not apply to wind generators.

5.5 Equipment Procurement. If responsibility for construction of Transmission Provider's Interconnection Facilities or Network Upgrades is to be borne by Transmission Provider, then Transmission Provider shall commence design of Transmission Provider's Interconnection Facilities or Network Upgrades and procure necessary equipment as soon as practicable after all of the following conditions are satisfied, unless the Parties otherwise agree in writing:

5.5.1 Transmission Provider has completed the Facilities Study pursuant to the Facilities Study Agreement;

5.5.2 Transmission Provider has received written authorization to proceed with design and procurement from Interconnection Customer by the date specified in Appendix B, Milestones; and

5.5.3 Interconnection Customer has provided security to Transmission Provider in accordance with Article 11.5 by the dates specified in Appendix B, Milestones.

5.6 Construction Commencement. Transmission Provider shall commence construction of Transmission Provider's Interconnection Facilities and Network Upgrades for which it is responsible as soon as practicable after the following additional conditions are satisfied:

5.6.1 Approval of the appropriate Governmental Authority has been obtained for any facilities requiring regulatory approval;

5.6.2 Necessary real property rights and rights-of-way have been obtained, to the extent required for the construction of a discrete aspect of Transmission Provider's Interconnection Facilities and Network Upgrades;

5.6.3 Transmission Provider has received written authorization to proceed with construction from Interconnection Customer by the date specified in Appendix B, Milestones; and

5.6.4 Interconnection Customer has provided security to Transmission Provider in accordance with Article 11.5 by the dates specified in Appendix B, Milestones.

5.7 Work Progress. The Parties will keep each other advised periodically as to the progress of their respective design, procurement, and construction efforts. Either Party may, at any time, request a progress report from the other Party. If, at any time, Interconnection Customer determines that the completion of Transmission Provider's Interconnection Facilities will not be required until after the specified In-Service Date, Interconnection Customer will provide written notice to Transmission Provider of such later date upon which the completion of Transmission Provider's Interconnection Facilities will be required.

5.8 Information Exchange. As soon as reasonably practicable after the Effective Date, the Parties shall exchange information regarding the design and compatibility of the Parties' Interconnection Facilities and compatibility of the Interconnection Facilities with Transmission Provider's Transmission System, and shall work diligently and in good faith to make any necessary design changes.

5.9 Other Interconnection Options.

5.9.1 Limited Operation. If any of Transmission Provider's Interconnection Facilities or Network Upgrades are not reasonably expected to be completed prior to the Commercial Operation Date of the Large Generating Facility, Transmission Provider shall, upon the request and at the expense of Interconnection Customer, perform operating studies on a timely basis to determine the extent to which the Large Generating Facility and Interconnection Customer's Interconnection Facilities may operate prior to the completion of Transmission Provider's Interconnection Facilities or Network Upgrades consistent with Applicable Laws and Regulations, Applicable Reliability Standards, Good Utility Practice, and this LGIA. Transmission Provider shall permit Interconnection Customer to operate the Large Generating Facility and Interconnection Customer's Interconnection Facilities in accordance with the results of such studies.

5.9.2 Provisional Interconnection Service. Upon the request of Interconnection Customer, and prior to completion of requisite Interconnection Facilities, Network Upgrades, Distribution Upgrades, or System Protection Facilities Transmission Provider may execute a Provisional Amended and Restated Large Generator Interconnection Agreement or Interconnection Customer may request the filing of an unexecuted Provisional Amended and Restated Large Generator Interconnection Agreement with the Interconnection Customer for limited Interconnection Service at the discretion of Transmission Provider based upon an evaluation that will consider the results of available studies. Transmission Provider shall determine, through available studies or additional studies as necessary, whether stability, short circuit, thermal, and/or voltage issues would arise if Interconnection Customer interconnects without modifications to the Generating Facility or Transmission System. Transmission Provider shall determine whether any Interconnection Facilities, Network Upgrades, Distribution Upgrades, or System Protection Facilities that are necessary to meet the requirements of the Electric Reliability Organization, or any applicable Regional Entity for the interconnection of a new, modified and/or expanded Generating Facility are in place prior to the commencement of Interconnection Service from the Generating Facility.

Where available studies indicate that such, Interconnection Facilities, Network Upgrades, Distribution Upgrades, and/or System Protection Facilities that are required for the interconnection of a new, modified and/or expanded Generating Facility are not currently in place, Transmission Provider will perform a study, at the Interconnection Customer's expense, to confirm the facilities that are required for Provisional Interconnection Service. The maximum permissible output of the Generating Facility in the Provisional Amended and Restated Large Generator Interconnection Agreement shall be studied and updated. Interconnection Customer assumes all risk and liabilities with respect to changes between the Provisional Amended and Restated Large Generator Interconnection Agreement and the Amended and Restated Large Generator Interconnection Agreement, including changes in output limits and Interconnection Facilities, Network Upgrades, Distribution Upgrades, and/or System Protection Facilities cost responsibilities.

5.10 Interconnection Customer's Interconnection Facilities ('ICIF'). Interconnection Customer shall, at its expense, design, procure, construct, own and install the ICIF, as set forth in Appendix A, Interconnection Facilities, Network Upgrades and Distribution Upgrades.

5.10.1 Interconnection Customer's Interconnection Facility Specifications. Interconnection Customer shall submit initial specifications for the ICIF, including System Protection Facilities, to Transmission Provider at least one hundred eighty (180) Calendar Days prior to the Initial Synchronization Date; and final specifications for review and comment at least ninety (90) Calendar Days prior to the Initial Synchronization Date. Transmission Provider shall review such specifications to ensure that the ICIF are compatible with the technical specifications, operational control, and safety requirements of Transmission Provider and comment on such specifications within thirty (30) Calendar Days of Interconnection Customer's submission. All specifications provided hereunder shall be deemed confidential.

5.10.2 Transmission Provider's Review. Transmission Provider's review of Interconnection Customer's final specifications shall not be construed as confirming, endorsing, or providing a warranty as to the design, fitness, safety, durability or reliability of the Large Generating Facility, or the ICIF. Interconnection Customer shall make such changes to the ICIF as may reasonably be required by Transmission Provider, in accordance with Good Utility Practice, to ensure that the ICIF are compatible with the technical specifications, operational control, and safety requirements of Transmission Provider.

5.10.3 ICIF Construction. The ICIF shall be designed and constructed in accordance with Good Utility Practice. Within one hundred twenty (120) Calendar Days after the Commercial Operation Date, unless the Parties agree on another mutually acceptable deadline, Interconnection Customer shall deliver to Transmission Provider "as-built" drawings, information and documents for the ICIF, such as: a one-line diagram, a site plan showing the Large Generating Facility and the ICIF, plan and elevation drawings showing the layout of the ICIF, a relay functional diagram, relaying AC and DC schematic wiring diagrams and relay settings for all facilities associated with Interconnection Customer's step-up transformers, the facilities connecting the Large Generating Facility to the step-up transformers and the ICIF, and the impedances (determined by factory tests) for the associated step-up transformers and the Large Generating Facility. The Interconnection Customer shall provide Transmission Provider specifications for the excitation system, automatic voltage regulator, Large Generating Facility control and protection settings, transformer tap settings, and communications, if applicable.

5.11 Transmission Provider's Interconnection Facilities Construction. Transmission Provider's Interconnection Facilities shall be designed and constructed in accordance with Good Utility Practice. Upon request, within one hundred twenty (120) Calendar Days after the Commercial Operation Date, unless the Parties agree on another mutually acceptable deadline,

Transmission Provider shall deliver to Interconnection Customer the following “as-built” drawings, information, and documents for Transmission Provider’s Interconnection Facilities.

Transmission Provider will obtain control of Transmission Provider’s Interconnection Facilities and Stand Alone Network Upgrades upon completion of such facilities.

5.12 Access Rights. Upon reasonable notice and supervision by a Party, and subject to any required or necessary regulatory approvals, a Party (“Granting Party”) shall furnish at no cost to the other Party (“Access Party”) any rights of use, licenses, rights of way and easements with respect to lands owned or controlled by the Granting Party, its agents (if allowed under the applicable agency agreement), or any Affiliate, that are necessary to enable the Access Party to obtain ingress and egress to construct, operate, maintain, repair, test (or witness testing), inspect, replace or remove facilities and equipment to: (i) interconnect the Large Generating Facility with the Transmission System; (ii) operate and maintain the Large Generating Facility, the Interconnection Facilities and the Transmission System; and (iii) disconnect or remove the Access Party’s facilities and equipment upon termination of this LGIA. In exercising such licenses, rights of way and easements, the Access Party shall not unreasonably disrupt or interfere with normal operation of the Granting Party’s business and shall adhere to the safety rules and procedures established in advance, as may be changed from time to time, by the Granting Party and provided to the Access Party.

5.13 Lands of Other Property Owners. If any part of Transmission Provider or Transmission Owner’s Interconnection Facilities and/or Network Upgrades is to be installed on property owned by persons other than Interconnection Customer or Transmission Provider or Transmission Owner, Transmission Provider or Transmission Owner shall at Interconnection Customer’s expense use efforts, similar in nature and extent to those that it typically undertakes on its own behalf or on behalf of its Affiliates, including use of its eminent domain authority, and to the extent consistent with state law, to procure from such persons any rights of use, licenses, rights of way and easements that are necessary to construct, operate, maintain, test, inspect, replace or remove Transmission Provider or Transmission Owner’s Interconnection Facilities and/or Network Upgrades upon such property.

5.14 Permits. Transmission Provider or Transmission Owner and Interconnection Customer shall cooperate with each other in good faith in obtaining all permits, licenses, and authorizations that are necessary to accomplish the interconnection in compliance with Applicable Laws and Regulations. With respect to this paragraph, Transmission Provider or Transmission Owner shall provide permitting assistance to Interconnection Customer comparable to that provided to Transmission Provider’s own, or an Affiliate’s generation.

5.15 Early Construction of Base Case Facilities. Interconnection Customer may request Transmission Provider to construct, and Transmission Provider shall construct, using Reasonable Efforts to accommodate Interconnection Customer’s In-Service Date, all or any portion of any Network Upgrades required for Interconnection Customer to be interconnected to the Transmission System which are included in the Base Case of the Facilities Study for Interconnection Customer, and which also are required to be constructed for another Interconnection Customer, but where such construction is not scheduled to be completed in time to achieve Interconnection Customer’s In-Service Date.

5.16 Suspension. Interconnection Customer reserves the right, upon written notice to Transmission Provider, to suspend at any time all work by Transmission Provider associated with the construction and installation of Transmission Provider’s Interconnection Facilities and/or Network Upgrades required under this LGIA with the condition that Transmission System shall be

left in a safe and reliable condition in accordance with Good Utility Practice and Transmission Provider's safety and reliability criteria. In such event, (a) all milestone dates occurring after the effective date of the suspension shall be suspended during the suspension period and (b) Interconnection Customer shall be responsible for all reasonable and necessary costs which Transmission Provider (i) has incurred pursuant to this LGIA prior to the suspension and (ii) incurs in suspending such work, including any costs incurred to perform such work as may be necessary to ensure the safety of persons and property and the integrity of the Transmission System during such suspension and, if applicable, any costs incurred in connection with the cancellation or suspension of material, equipment and labor contracts which Transmission Provider cannot reasonably avoid; provided, however, that prior to canceling or suspending any such material, equipment or labor contract, Transmission Provider shall obtain Interconnection Customer's authorization to do so.

Transmission Provider shall invoice Interconnection Customer for such costs pursuant to Article 12 and shall use due diligence to minimize its costs. In the event Interconnection Customer suspends work by Transmission Provider required under this LGIA pursuant to this Article 5.16, and has not requested Transmission Provider to recommence the work required under this LGIA on or before the expiration of three (3) years following commencement of such suspension, this LGIA shall be deemed terminated. The three-year period shall begin on the date the suspension is requested, or the date of the written notice to Transmission Provider, if no effective date is specified.

5.17 Taxes.

5.17.1 Interconnection Customer Payments Not Taxable. The Parties intend that all payments or property transfers made by Interconnection Customer to Transmission Provider for the installation of Transmission Provider's Interconnection Facilities and the Network Upgrades shall be non-taxable, either as contributions to capital, or as an advance, in accordance with the Internal Revenue Code and any applicable state income tax laws and shall not be taxable as contributions in aid of construction or otherwise under the Internal Revenue Code and any applicable state income tax laws.

5.17.2 Representations and Covenants. In accordance with IRS Notice 2001-82 and IRS Notice 88-129, Interconnection Customer represents and covenants that (i) ownership of the electricity generated at the Large Generating Facility will pass to another party prior to the transmission of the electricity on the Transmission System, (ii) for income tax purposes, the amount of any payments and the cost of any property transferred to Transmission Provider for Transmission Provider's Interconnection Facilities will be capitalized by Interconnection Customer as an intangible asset and recovered using the straight-line method over a useful life of twenty (20) years, and (iii) any portion of Transmission Provider's Interconnection Facilities that is a "dual-use intertie," within the meaning of IRS Notice 88-129, is reasonably expected to carry only a de minimis amount of electricity in the direction of the Large Generating Facility. For this purpose, "de minimis amount" means no more than 5 percent of the total power flows in both directions, calculated in accordance with the "5 percent test" set forth in IRS Notice 88-129. This is not intended to be an exclusive list of the relevant conditions that must be met to conform to IRS requirements for non-taxable treatment.

At Transmission Provider's request, Interconnection Customer shall provide Transmission Provider with a report from an independent engineer confirming its representation in clause (iii), above. Transmission Provider represents and covenants that the cost of Transmission Provider's Interconnection Facilities paid for by Interconnection Customer will have no net effect on the base upon which rates are determined.

5.17.3 Indemnification for the Cost Consequences of Current Tax Liability Imposed Upon the Transmission Provider. Notwithstanding Article 5.17.1, Interconnection Customer shall protect, indemnify and hold harmless Transmission Provider from the cost consequences of any current tax liability imposed against Transmission Provider as the result of payments or property transfers made by Interconnection Customer to Transmission Provider under this LGIA for Interconnection Facilities, as well as any interest and penalties, other than interest and penalties attributable to any delay caused by Transmission Provider.

Transmission Provider shall not include a gross-up for the cost consequences of any current tax liability in the amounts it charges Interconnection Customer under this LGIA unless (i) Transmission Provider has determined, in good faith, that the payments or property transfers made by Interconnection Customer to Transmission Provider should be reported as income subject to taxation or (ii) any Governmental Authority directs Transmission Provider to report payments or property as income subject to taxation; provided, however, that Transmission Provider may require Interconnection Customer to provide security for Interconnection Facilities, in a form reasonably acceptable to Transmission Provider (such as a parental guarantee or a letter of credit), in an amount equal to the cost consequences of any current tax liability under this Article 5.17. Interconnection Customer shall reimburse Transmission Provider for such costs on a fully grossed-up basis, in accordance with Article 5.17.4, within thirty (30) Calendar Days of receiving written notification from Transmission Provider of the amount due, including detail about how the amount was calculated.

The indemnification obligation shall terminate at the earlier of (1) the expiration of the ten year testing period and the applicable statute of limitation, as it may be extended by Transmission Provider upon request of the IRS, to keep these years open for audit or adjustment, or (2) the occurrence of a subsequent taxable event and the payment of any related indemnification obligations as contemplated by this Article 5.17.

5.17.4 Tax Gross-Up Amount. Interconnection Customer's liability for the cost consequences of any current tax liability under this Article 5.17 shall be calculated on a fully grossed-up basis. Except as may otherwise be agreed to by the parties, this means that Interconnection Customer will pay Transmission Provider, in addition to the amount paid for the Interconnection Facilities and Network Upgrades, an amount equal to (1) the current taxes imposed on Transmission Provider ("Current Taxes") on the excess of (a) the gross income realized by Transmission Provider as a result of payments or property transfers made by Interconnection Customer to Transmission Provider under this LGIA (without regard to any payments under this Article 5.17) (the "Gross Income Amount") over (b) the present value of future tax deductions for depreciation that will be available as a result of such payments or property transfers (the "Present Value Depreciation Amount"), plus (2) an additional amount sufficient to permit Transmission Provider to receive and retain, after the payment of all Current Taxes, an amount equal to the net amount described in clause (1).

For this purpose, (i) Current Taxes shall be computed based on Transmission Provider's composite federal and state tax rates at the time the payments or property transfers are received and Transmission Provider will be treated as being subject to tax at the highest marginal rates in effect at that time (the "Current Tax Rate"), and (ii) the Present Value Depreciation Amount shall be computed by discounting Transmission Provider's anticipated tax depreciation deductions as a result of such payments or property transfers by Transmission Provider's current weighted average cost of capital. Thus, the formula for calculating Interconnection Customer's liability to Transmission Owner pursuant to this Article 5.17.4 can be expressed as follows: $(\text{Current Tax Rate} \times (\text{Gross Income Amount} - \text{Present Value of Tax Depreciation})) / (1 - \text{Current Tax Rate})$.

Interconnection Customer's estimated tax liability in the event taxes are imposed shall be stated in Appendix A, Interconnection Facilities, Network Upgrades and Distribution Upgrades.

5.17.5 Private Letter Ruling or Change or Clarification of Law. At Interconnection Customer's request and expense, Transmission Provider shall file with the IRS a request for a private letter ruling as to whether any property transferred or sums paid, or to be paid, by Interconnection Customer to Transmission Provider under this LGIA are subject to federal income taxation. Interconnection Customer will prepare the initial draft of the request for a private letter ruling, and will certify under penalties of perjury that all facts represented in such request are true and accurate to the best of Interconnection Customer's knowledge. Transmission Provider and Interconnection Customer shall cooperate in good faith with respect to the submission of such request.

Transmission Provider shall keep Interconnection Customer fully informed of the status of such request for a private letter ruling and shall execute either a privacy act waiver or a limited power of attorney, in a form acceptable to the IRS, that authorizes Interconnection Customer to participate in all discussions with the IRS regarding such request for a private letter ruling. Transmission Provider shall allow Interconnection Customer to attend all meetings with IRS officials about the request and shall permit Interconnection Customer to prepare the initial drafts of any follow-up letters in connection with the request.

5.17.6 Subsequent Taxable Events. If, within 10 years from the date on which the relevant Transmission Provider's Interconnection Facilities are placed in service, (i) Interconnection Customer Breaches the covenants contained in Article 5.17.2, (ii) a "disqualification event" occurs within the meaning of IRS Notice 88-129, or (iii) this LGIA terminates and Transmission Provider retains ownership of the Interconnection Facilities and Network Upgrades, Interconnection Customer shall pay a tax gross-up for the cost consequences of any current tax liability imposed on Transmission Provider, calculated using the methodology described in Article 5.17.4 and in accordance with IRS Notice 90-60.

5.17.7 Contests. In the event any Governmental Authority determines that Transmission Provider's receipt of payments or property constitutes income that is subject to taxation, Transmission Provider shall notify Interconnection Customer, in writing, within thirty (30) Calendar Days of receiving notification of such determination by a Governmental Authority. Upon the timely written request by Interconnection Customer and at Interconnection Customer's sole expense, Transmission Provider may appeal, protest, seek abatement of, or otherwise oppose such determination. Upon Interconnection Customer's written request and sole expense, Transmission Provider may file a claim for refund with respect to any taxes paid under this Article 5.17, whether or not it has received such a determination. Transmission Provider reserves the right to make all decisions with regard to the prosecution of such appeal, protest, abatement or other contest, including the selection of counsel and compromise or settlement of the claim, but Transmission Provider shall keep Interconnection Customer informed, shall consider in good faith suggestions from Interconnection Customer about the conduct of the contest, and shall reasonably permit Interconnection Customer or an Interconnection Customer representative to attend contest proceedings.

Interconnection Customer shall pay to Transmission Provider on a periodic basis, as invoiced by Transmission Provider, Transmission Provider's documented reasonable costs of prosecuting such appeal, protest, abatement, or other contest. At any time during the contest, Transmission Provider may agree to a settlement either with Interconnection Customer's consent or after obtaining written advice from nationally recognized tax counsel, selected by Transmission Provider, but reasonably acceptable to Interconnection Customer, that the proposed settlement represents a reasonable

settlement given the hazards of litigation. Interconnection Customer's obligation shall be based on the amount of the settlement agreed to by Interconnection Customer, or if a higher amount, so much of the settlement that is supported by the written advice from nationally recognized tax counsel selected under the terms of the preceding sentence. The settlement amount shall be calculated on a fully grossed-up basis to cover any related cost consequences of the current tax liability. Any settlement without Interconnection Customer's consent or such written advice will relieve Interconnection Customer from any obligation to indemnify Transmission Provider for the tax at issue in the contest.

5.17.8 Refund. In the event that (a) a private letter ruling is issued to Transmission Provider which holds that any amount paid or the value of any property transferred by Interconnection Customer to Transmission Provider under the terms of this LGIA is not subject to federal income taxation, (b) any legislative change or administrative announcement, notice, ruling or other determination makes it reasonably clear to Transmission Provider in good faith that any amount paid or the value of any property transferred by Interconnection Customer to Transmission Provider under the terms of this LGIA is not taxable to Transmission Provider, (c) any abatement, appeal, protest, or other contest results in a determination that any payments or transfers made by Interconnection Customer to Transmission Provider are not subject to federal income tax, or (d) if Transmission Provider receives a refund from any taxing authority for any overpayment of tax attributable to any payment or property transfer made by Interconnection Customer to Transmission Provider pursuant to this LGIA, Transmission Provider shall promptly refund to Interconnection Customer the following:

- (i) any payment made by Interconnection Customer under this Article 5.17 for taxes that is attributable to the amount determined to be non-taxable, together with interest thereon,
- (ii) interest on any amounts paid by Interconnection Customer to Transmission Provider for such taxes which Transmission Provider did not submit to the taxing authority, calculated in accordance with the methodology set forth in FERC's regulations at 18 CFR § 35.19a(a)(2)(iii) from the date payment was made by Interconnection Customer to the date Transmission Provider refunds such payment to Interconnection Customer, and
- (iii) with respect to any such taxes paid by Transmission Provider, any refund or credit Transmission Provider receives or to which it may be entitled from any Governmental Authority, interest (or that portion thereof attributable to the payment described in clause (i), above) owed to Transmission Provider for such overpayment of taxes (including any reduction in interest otherwise payable by Transmission Provider to any Governmental Authority resulting from an offset or credit); provided, however, that Transmission Provider will remit such amount promptly to Interconnection Customer only after and to the extent that Transmission Provider has received a tax refund, credit or offset from any Governmental Authority for any applicable overpayment of income tax related to Transmission Provider's Interconnection Facilities.

The intent of this provision is to leave the Parties, to the extent practicable, in the event that no taxes are due with respect to any payment for Interconnection Facilities and Network Upgrades hereunder, in the same position they would have been in had no such tax payments been made.

5.17.9 Taxes Other Than Income Taxes. Upon the timely request by Interconnection Customer, and at Interconnection Customer's sole expense, Transmission Provider may appeal, protest, seek abatement of, or otherwise contest any tax (other than federal or state income tax) asserted or assessed against Transmission Provider for which Interconnection Customer may be required to reimburse Transmission Provider under the terms of this LGIA. Interconnection Customer shall

pay to Transmission Provider on a periodic basis, as invoiced by Transmission Provider, Transmission Provider's documented reasonable costs of prosecuting such appeal, protest, abatement, or other contest. Interconnection Customer and Transmission Provider shall cooperate in good faith with respect to any such contest. Unless the payment of such taxes is a prerequisite to an appeal or abatement or cannot be deferred, no amount shall be payable by Interconnection Customer to Transmission Provider for such taxes until they are assessed by a final, non-appealable order by any court or agency of competent jurisdiction. In the event that a tax payment is withheld and ultimately due and payable after appeal, Interconnection Customer will be responsible for all taxes, interest, and penalties, other than penalties attributable to any delay caused by Transmission Provider.

5.17.10 Transmission Owners Who Are Not Transmission Providers. If Transmission Provider is not the same entity as the Transmission Owner, then (i) all references in this Article 5.17 to Transmission Provider shall be deemed also to refer to and to include the Transmission Owner, as appropriate, and (ii) this LGIA shall not become effective until such Transmission Owner shall have agreed in writing to assume all of the duties and obligations of Transmission Provider under this Article 5.17 of this LGIA.

5.18 Tax Status. Each Party shall cooperate with the other to maintain the other Party's tax status. Nothing in this LGIA is intended to adversely affect any Transmission Provider's tax exempt status with respect to the issuance of bonds including, but not limited to, Local Furnishing Bonds.

5.19 Modification.

5.19.1 General. Either Party may undertake modifications to its facilities. If a Party plans to undertake a modification that reasonably may be expected to affect the other Party's facilities, that Party shall provide to the other Party sufficient information regarding such modification so that the other Party may evaluate the potential impact of such modification prior to commencement of the work. Such information shall be deemed to be confidential hereunder and shall include information concerning the timing of such modifications and whether such modifications are expected to interrupt the flow of electricity from the Large Generating Facility. The Party desiring to perform such work shall provide the relevant drawings, plans, and specifications to the other Party at least ninety (90) Calendar Days in advance of the commencement of the work or such shorter period upon which the Parties may agree, which agreement shall not unreasonably be withheld, conditioned, or delayed.

In the case of Large Generating Facility modifications that do not require Interconnection Customer to submit an Interconnection Request, Transmission Provider shall provide, within thirty (30) Calendar Days (or such other time as the Parties may agree), an estimate of any additional modifications to the Transmission System, Transmission Provider's Interconnection Facilities or Network Upgrades necessitated by such Interconnection Customer modification and a good faith estimate of the costs thereof.

5.19.2 Standards. Any additions, modifications, or replacements made to a Party's facilities shall be designed, constructed, and operated in accordance with this LGIA and Good Utility Practice.

5.19.3 Modification Costs. Interconnection Customer shall not be directly assigned for the costs of any additions, modifications, or replacements that Transmission Provider makes to Transmission Provider's Interconnection Facilities or the Transmission System to facilitate the interconnection of a third party to Transmission Provider's Interconnection Facilities or the Transmission System, or to provide transmission service to a third party under Transmission Provider's Tariff. Interconnection Customer shall be responsible for the costs of any additions, modifications, or

replacements to Interconnection Customer's Interconnection Facilities that may be necessary to maintain or upgrade such Interconnection Customer's Interconnection Facilities consistent with Applicable Laws and Regulations, Applicable Reliability Standards or Good Utility Practice.

Article 6. Testing and Inspection

6.1 Pre-Commercial Operation Date Testing and Modifications. Prior to the Commercial Operation Date, Transmission Provider shall test Transmission Provider's Interconnection Facilities and Network Upgrades and Interconnection Customer shall test the Large Generating Facility and Interconnection Customer's Interconnection Facilities to ensure their safe and reliable operation. Similar testing may be required after initial operation. Each Party shall make any modifications to its facilities that are found to be necessary as a result of such testing. Interconnection Customer shall bear the cost of all such testing and modifications. Interconnection Customer shall generate test energy at the Large Generating Facility only if it has arranged for the delivery of such test energy.

6.2 Post-Commercial Operation Date Testing and Modifications. Each Party shall at its own expense perform routine inspection and testing of its facilities and equipment in accordance with Good Utility Practice as may be necessary to ensure the continued interconnection of the Large Generating Facility with the Transmission System in a safe and reliable manner. Each Party shall have the right, upon advance written notice, to require reasonable additional testing of the other Party's facilities, at the requesting Party's expense, as may be in accordance with Good Utility Practice.

6.3 Right to Observe Testing. Each Party shall notify the other Party in advance of its performance of tests of its Interconnection Facilities. The other Party has the right, at its own expense, to observe such testing.

6.4 Right to Inspect. Each Party shall have the right, but shall have no obligation to: (i) observe the other Party's tests and/or inspection of any of its System Protection Facilities and other protective equipment, including Power System Stabilizers; (ii) review the settings of the other Party's System Protection Facilities and other protective equipment; and (iii) review the other Party's maintenance records relative to the Interconnection Facilities, the System Protection Facilities and other protective equipment. A Party may exercise these rights from time to time as it deems necessary upon reasonable notice to the other Party. The exercise or non-exercise by a Party of any such rights shall not be construed as an endorsement or confirmation of any element or condition of the Interconnection Facilities or the System Protection Facilities or other protective equipment or the operation thereof, or as a warranty as to the fitness, safety, desirability, or reliability of same. Any information that a Party obtains through the exercise of any of its rights under this Article 6.4 shall be deemed to be Confidential Information and treated pursuant to Article 22 of this LGIA.

Article 7. Metering

7.1 General. Each Party shall comply with the Electric Reliability Organization requirements. Unless otherwise agreed by the Parties, Transmission Provider shall install Metering Equipment at the Point of Interconnection prior to any operation of the Large Generating Facility and shall own, operate, test, and maintain such Metering Equipment. Power flows to and from the Large Generating Facility shall be measured at or, at Transmission Provider's option, compensated to, the

Point of Interconnection. Transmission Provider shall provide metering quantities, in analog and/or digital form, to Interconnection Customer upon request. Interconnection Customer shall bear all reasonable documented costs associated with the purchase, installation, operation, testing and maintenance of the Metering Equipment.

7.2 Check Meters. Interconnection Customer, at its option and expense, may install and operate, on its premises and on its side of the Point of Interconnection, one or more check meters to check Transmission Provider's meters. Such check meters shall be for check purposes only and shall not be used for the measurement of power flows for purposes of this LGIA, except as provided in Article 7.4 below. The check meters shall be subject at all reasonable times to inspection and examination by Transmission Provider or its designee. The installation, operation and maintenance thereof shall be performed entirely by Interconnection Customer in accordance with Good Utility Practice.

7.3 Standards. Transmission Provider shall install, calibrate, and test revenue quality Metering Equipment in accordance with applicable ANSI standards.

7.4 Testing of Metering Equipment. Transmission Provider shall inspect and test all Transmission Provider-owned Metering Equipment upon installation and at least once every two (2) years thereafter. If requested to do so by Interconnection Customer, Transmission Provider shall, at Interconnection Customer's expense, inspect or test Metering Equipment more frequently than every two (2) years. Transmission Provider shall give reasonable notice of the time when any inspection or test shall take place, and Interconnection Customer may have representatives present at the test or inspection. If at any time Metering Equipment is found to be inaccurate or defective, it shall be adjusted, repaired or replaced at Interconnection Customer's expense, in order to provide accurate metering, unless the inaccuracy or defect is due to Transmission Provider's failure to maintain, then Transmission Provider shall pay. If Metering Equipment fails to register, or if the measurement made by Metering Equipment during a test varies by more than two percent from the measurement made by the standard meter used in the test, Transmission Provider shall adjust the measurements by correcting all measurements for the period during which Metering Equipment was in error by using Interconnection Customer's check meters, if installed. If no such check meters are installed or if the period cannot be reasonably ascertained, the adjustment shall be for the period immediately preceding the test of the Metering Equipment equal to one-half the time from the date of the last previous test of the Metering Equipment.

7.5 Metering Data. At Interconnection Customer's expense, the metered data shall be telemetered to one or more locations designated by Transmission Provider and one or more locations designated by Interconnection Customer. Such telemetered data shall be used, under normal operating conditions, as the official measurement of the amount of energy delivered from the Large Generating Facility to the Point of Interconnection.

Article 8. Communications

8.1 Interconnection Customer Obligations. Interconnection Customer shall maintain satisfactory operating communications with Transmission Provider's Transmission System dispatcher or representative designated by Transmission Provider. Interconnection Customer shall provide standard voice line, dedicated voice line and facsimile communications at its Large Generating Facility control room or central dispatch facility through use of either the public telephone system, or a voice communications system that does not rely on the public telephone system. Interconnection Customer shall also provide the dedicated data circuit(s) necessary to provide Interconnection Customer data to Transmission Provider as set forth in Appendix D,

Security Arrangements Details. The data circuit(s) shall extend from the Large Generating Facility to the location(s) specified by Transmission Provider. Any required maintenance of such communications equipment shall be performed by Interconnection Customer. Operational communications shall be activated and maintained under, but not be limited to, the following events: system paralleling or separation, scheduled and unscheduled shutdowns, equipment clearances, and hourly and daily load data.

8.2 Remote Terminal Unit. Prior to the Initial Synchronization Date of the Large Generating Facility, a Remote Terminal Unit, or equivalent data collection and transfer equipment acceptable to the Parties, shall be installed by Interconnection Customer, or by Transmission Provider at Interconnection Customer's expense, to gather accumulated and instantaneous data to be telemetered to the location(s) designated by Transmission Provider through use of a dedicated point-to-point data circuit(s) as indicated in Article 8.1. The communication protocol for the data circuit(s) shall be specified by Transmission Provider. Instantaneous bi-directional analog real power and reactive power flow information must be telemetered directly to the location(s) specified by Transmission Provider.

Each Party will promptly advise the other Party if it detects or otherwise learns of any metering, telemetry or communications equipment errors or malfunctions that require the attention and/or correction by the other Party. The Party owning such equipment shall correct such error or malfunction as soon as reasonably feasible.

8.3 No Annexation. Any and all equipment placed on the premises of a Party shall be and remain the property of the Party providing such equipment regardless of the mode and manner of annexation or attachment to real property, unless otherwise mutually agreed by the Parties.

8.4 Provision of Data from a Variable Energy Resource. The Interconnection Customer whose Generating Facility contains at least one Variable Energy Resource shall provide meteorological and forced outage data to the Transmission Provider to the extent necessary for the Transmission Provider's development and deployment of power production forecasts for that class of Variable Energy Resources. The Interconnection Customer with a Variable Energy Resource having wind as the energy source, at a minimum, will be required to provide the Transmission Provider with site-specific meteorological data including: temperature, wind speed, wind direction, and atmospheric pressure. The Interconnection Customer with a Variable Energy Resource having solar as the energy source, at a minimum, will be required to provide the Transmission Provider with site-specific meteorological data including: temperature, atmospheric pressure, and irradiance. The Transmission Provider and Interconnection Customer whose Generating Facility contains a Variable Energy Resource shall mutually agree to any additional meteorological data that are required for the development and deployment of a power production forecast. The Interconnection Customer whose Generating Facility contains a Variable Energy Resource also shall submit data to the Transmission Provider regarding all forced outages to the extent necessary for the Transmission Provider's development and deployment of power production forecasts for that class of Variable Energy Resources. The exact specifications of the meteorological and forced outage data to be provided by the Interconnection Customer to the Transmission Provider, including the frequency and timing of data submittals, shall be made taking into account the size and configuration of the Variable Energy Resource, its characteristics, location, and its importance in maintaining generation resource adequacy and transmission system reliability in its area. All requirements for meteorological and forced outage data must be commensurate with the power production forecasting employed by the Transmission Provider. Such requirements for meteorological and forced outage data are set forth in Appendix C, Interconnection Details, of this LGIA, as they may change from time to time.

Article 9. Operations

9.1 General. Each Party shall comply with the Electric Reliability Organization requirements. Each Party shall provide to the other Party all information that may reasonably be required by the other Party to comply with Applicable Laws and Regulations and Applicable Reliability Standards.

9.2 Balancing Authority Area Notification. At least three months before Initial Synchronization Date, Interconnection Customer shall notify Transmission Provider in writing of the Balancing Authority Area in which the Large Generating Facility will be located. If Interconnection Customer elects to locate the Large Generating Facility in a Balancing Authority Area other than the Balancing Authority Area in which the Large Generating Facility is physically located, and if permitted to do so by the relevant transmission tariffs, all necessary arrangements, including but not limited to those set forth in Article 7 and Article 8 of this LGIA, and remote Balancing Authority Area generator interchange agreements, if applicable, and the appropriate measures under such agreements, shall be executed and implemented prior to the placement of the Large Generating Facility in the other Balancing Authority Area.

9.3 Transmission Provider Obligations. Transmission Provider shall cause the Transmission System and Transmission Provider's Interconnection Facilities to be operated, maintained and controlled in a safe and reliable manner and in accordance with this LGIA. Transmission Provider may provide operating instructions to Interconnection Customer consistent with this LGIA and Transmission Provider's operating protocols and procedures as they may change from time to time. Transmission Provider will consider changes to its operating protocols and procedures proposed by Interconnection Customer.

9.4 Interconnection Customer Obligations. Interconnection Customer shall at its own expense operate, maintain, and control the Large Generating Facility and Interconnection Customer's Interconnection Facilities in a safe and reliable manner and in accordance with this LGIA. Interconnection Customer shall operate the Large Generating Facility and Interconnection Customer's Interconnection Facilities in accordance with all applicable requirements of the Balancing Authority Area of which it is part, as such requirements are set forth in Appendix C, Interconnection Details, of this LGIA. Appendix C, Interconnection Details, will be modified to reflect changes to the requirements as they may change from time to time. Either Party may request that the other Party provide copies of the requirements set forth in Appendix C, Interconnection Details, of this LGIA.

9.5 Start-Up and Synchronization. Consistent with the Parties' mutually acceptable procedures, Interconnection Customer is responsible for the proper synchronization of the Large Generating Facility to Transmission Provider's Transmission System.

9.6 Reactive Power and Primary Frequency Response.

9.6.1 Power Factor Design Criteria.

9.6.1.1 Synchronous Generation. Interconnection Customer shall design the Large Generating Facility to maintain a composite power delivery at continuous rated power output at the Point of Interconnection at a power factor within the range of 0.95 leading to 0.95 lagging, unless Transmission Provider has established different requirements that apply to all synchronous generators in the Balancing Authority Area on a comparable basis.

9.6.1.2 Non-Synchronous Generation. Interconnection Customer shall design the Large Generating Facility to maintain a composite power delivery at continuous rated power output at the

high-side of the generator substation at a power factor within the range of 0.95 leading to 0.95 lagging, unless Transmission Provider has established a different power factor range that applies to all non-synchronous generators in the Balancing Authority Area on a comparable basis. This power factor range standard shall be dynamic and can be met using, for example, power electronics designed to supply this level of reactive capability (taking into account any limitations due to voltage level, real power output, etc.) or fixed and switched capacitors, or a combination of the two. This requirement shall only apply to newly interconnecting non-synchronous generators that have not yet executed a Facilities Study Agreement as of the effective date of the Final Rule establishing this requirement (Order No. 827).

9.6.2 Voltage Schedules. Once Interconnection Customer has synchronized the Large Generating Facility with the Transmission System, Transmission Provider shall require Interconnection Customer to operate the Large Generating Facility to produce or absorb reactive power within the design limitations of the Large Generating Facility set forth in Article 9.6.1 (Power Factor Design Criteria). Transmission Provider's voltage schedules shall treat all sources of reactive power in the Balancing Authority Area in an equitable and not unduly discriminatory manner. Transmission Provider shall exercise Reasonable Efforts to provide Interconnection Customer with such schedules at least one (1) day in advance, and may make changes to such schedules as necessary to maintain the reliability of the Transmission System. Interconnection Customer shall operate the Large Generating Facility to maintain the specified output voltage or power factor at the Point of Interconnection within the design limitations of the Large Generating Facility set forth in Article 9.6.1 (Power Factor Design Criteria). If Interconnection Customer is unable to maintain the specified voltage or power factor, it shall promptly notify the System Operator.

9.6.2.1 Voltage Regulators. Whenever the Large Generating Facility is operated in parallel with the Transmission System and voltage regulators are capable of operation, Interconnection Customer shall operate the Large Generating Facility with its voltage regulators in automatic operation. If the Large Generating Facility's voltage regulators are not capable of such automatic operation, Interconnection Customer shall immediately notify Transmission Provider's system operator, or its designated representative, and ensure that such Large Generating Facility's reactive power production or absorption (measured in MVARs) are within the design capability of the Large Generating Facility's generating unit(s) and steady state stability limits. Interconnection Customer shall not cause its Large Generating Facility to disconnect automatically or instantaneously from the Transmission System or trip any generating unit comprising the Large Generating Facility for an under or over frequency condition unless the abnormal frequency condition persists for a time period beyond the limits set forth in ANSI/IEEE Standard C37.106, or such other standard as applied to other generators in the Balancing Authority Area on a comparable basis.

9.6.3 Payment for Reactive Power. Transmission Provider is required to pay Interconnection Customer for reactive power that Interconnection Customer provides or absorbs from the Large Generating Facility when Transmission Provider requests Interconnection Customer to operate its Large Generating Facility outside the range specified in Article 9.6.1, provided that if Transmission Provider pays its own or affiliated generators for reactive power service within the specified range, it must also pay Interconnection Customer. Payments shall be pursuant to Article 11.6 or such other agreement to which the Parties have otherwise agreed.

9.6.4 Primary Frequency Response. Interconnection Customer shall ensure the primary frequency response capability of its Large Generating Facility by installing, maintaining, and operating a functioning governor or equivalent controls. The term "functioning governor or equivalent controls" as used herein shall mean the required hardware and/or software that provides frequency responsive real power control with the ability to sense changes in system frequency and

autonomously adjust the Large Generating Facility's real power output in accordance with the droop and deadband parameters and in the direction needed to correct frequency deviations. Interconnection Customer is required to install a governor or equivalent controls with the capability of operating: (1) with a maximum 5 percent droop and ± 0.036 Hz deadband; or (2) in accordance with the relevant droop, deadband, and timely and sustained response settings from an approved Electric Reliability Organization reliability standard providing for equivalent or more stringent parameters. The droop characteristic shall be: (1) based on the nameplate capacity of the Large Generating Facility, and shall be linear in the range of frequencies between 59 to 61 Hz that are outside of the deadband parameter; or (2) based on an approved Electric Reliability Organization reliability standard providing for an equivalent or more stringent parameter. The deadband parameter shall be: the range of frequencies above and below nominal (60 Hz) in which the governor or equivalent controls is not expected to adjust the Large Generating Facility's real power output in response to frequency deviations. The deadband shall be implemented: (1) without a step to the droop curve, that is, once the frequency deviation exceeds the deadband parameter, the expected change in the Large Generating Facility's real power output in response to frequency deviations shall start from zero and then increase (for under-frequency deviations) or decrease (for over-frequency deviations) linearly in proportion to the magnitude of the frequency deviation; or (2) in accordance with an approved Electric Reliability Organization reliability standard providing for an equivalent or more stringent parameter.

Interconnection Customer shall notify Transmission Provider that the primary frequency response capability of the Large Generating Facility has been tested and confirmed during commissioning. Once Interconnection Customer has synchronized the Large Generating Facility with the Transmission System, Interconnection Customer shall operate the Large Generating Facility consistent with the provisions specified in Articles 9.6.4.1 and 9.6.4.2 of this Agreement. The primary frequency response requirements contained herein shall apply to both synchronous and non-synchronous Large Generating Facilities.

9.6.4.1 Governor or Equivalent Controls. Whenever the Large Generating Facility is operated in parallel with the Transmission System, Interconnection Customer shall operate the Large Generating Facility with its governor or equivalent controls in service and responsive to frequency. Interconnection Customer shall: (1) in coordination with Transmission Provider and/or the relevant balancing authority, set the deadband parameter to: (1) a maximum of ± 0.036 Hz and set the droop parameter to a maximum of 5 percent; or (2) implement the relevant droop and deadband settings from an approved Electric Reliability Organization reliability standard that provides for equivalent or more stringent parameters. Interconnection Customer shall be required to provide the status and settings of the governor or equivalent controls to Transmission Provider and/or the relevant balancing authority upon request. If Interconnection Customer needs to operate the Large Generating Facility with its governor or equivalent controls not in service, Interconnection Customer shall immediately notify Transmission Provider and the relevant balancing authority, and provide both with the following information: (1) the operating status of the governor or equivalent controls (i.e., whether it is currently out of service or when it will be taken out of service); (2) the reasons for removing the governor or equivalent controls from service; and (3) a reasonable estimate of when the governor or equivalent controls will be returned to service. Interconnection Customer shall make Reasonable Efforts to return its governor or equivalent controls into service as soon as practicable. Interconnection Customer shall make Reasonable Efforts to keep outages of the Large Generating Facility's governor or equivalent controls to a minimum whenever the Large Generating Facility is operated in parallel with the Transmission System.

9.6.4.2 Timely and Sustained Response. Interconnection Customer shall ensure that the Large Generating Facility's real power response to sustained frequency deviations outside of the deadband

setting is automatically provided and shall begin immediately after frequency deviates outside of the deadband, and to the extent the Large Generating Facility has operating capability in the direction needed to correct the frequency deviation. Interconnection Customer shall not block or otherwise inhibit the ability of the governor or equivalent controls to respond and shall ensure that the response is not inhibited, except under certain operational constraints including, but not limited to, ambient temperature limitations, physical energy limitations, outages of mechanical equipment, or regulatory requirements. The Large Generating Facility shall sustain the real power response at least until system frequency returns to a value within the deadband setting of the governor or equivalent controls. A Commission-approved reliability standard with equivalent or more stringent requirements shall supersede the above requirements.

9.6.4.3 Exemptions. Large Generating Facilities that are regulated by the United States Nuclear Regulatory Commission shall be exempt from Articles 9.6.4, 9.6.4.1, and 9.6.4.2 of this Agreement. Large Generating Facilities that are behind the meter generation that is sized-to-load (i.e., the thermal load and the generation are near-balanced in real-time operation and the generation is primarily controlled to maintain the unique thermal, chemical, or mechanical output necessary for the operating requirements of its host facility) shall be required to install primary frequency response capability in accordance with the droop and deadband capability requirements specified in Article 9.6.4, but shall be otherwise exempt from the operating requirements in Articles 9.6.4, 9.6.4.1, 9.6.4.2, and 9.6.4.4 of this Agreement.

9.6.4.4 Electric Storage Resources. Interconnection Customer interconnecting a Generating Facility that contains an electric storage resource shall establish an operating range in Appendix C of its LGIA that specifies a minimum state of charge and a maximum state of charge between which the electric storage resource will be required to provide primary frequency response consistent with the conditions set forth in Articles 9.6.4, 9.6.4.1, 9.6.4.2 and 9.6.4.3 of this Agreement. Appendix C shall specify whether the operating range is static or dynamic, and shall consider (1) the expected magnitude of frequency deviations in the interconnection; (2) the expected duration that system frequency will remain outside of the deadband parameter in the interconnection; (3) the expected incidence of frequency deviations outside of the deadband parameter in the interconnection; (4) the physical capabilities of the electric storage resource; (5) operational limitations of the electric storage resource due to manufacturer specifications; and (6) any other relevant factors agreed to by Transmission Provider and Interconnection Customer, and in consultation with the relevant transmission owner or balancing authority as appropriate. If the operating range is dynamic, then Appendix C must establish how frequently the operating range will be reevaluated and the factors that may be considered during its reevaluation.

Interconnection Customer's electric storage resource is required to provide timely and sustained primary frequency response consistent with Article 9.6.4.2 of this Agreement when it is online and dispatched to inject electricity to the Transmission System and/or receive electricity from the Transmission System. This excludes circumstances when the electric storage resource is not dispatched to inject electricity to the Transmission System and/or dispatched to receive electricity from the Transmission System. If Interconnection Customer's electric storage resource is charging at the time of a frequency deviation outside of its deadband parameter, it is to increase (for over-frequency deviations) or decrease (for under-frequency deviations) the rate at which it is charging in accordance with its droop parameter. Interconnection Customer's electric storage resource is not required to change from charging to discharging, or vice versa, unless the response necessitated by the droop and deadband settings requires it to do so and it is technically capable of making such a transition.

9.7 Outages and Interruptions.

9.7.1 Outages.

9.7.1.1 Outage Authority and Coordination. Each Party may in accordance with Good Utility Practice in coordination with the other Party remove from service any of its respective Interconnection Facilities or Network Upgrades that may impact the other Party's facilities as necessary to perform maintenance or testing or to install or replace equipment. Absent an Emergency Condition, the Party scheduling a removal of such facility(ies) from service will use Reasonable Efforts to schedule such removal on a date and time mutually acceptable to the Parties. In all circumstances, any Party planning to remove such facility(ies) from service shall use Reasonable Efforts to minimize the effect on the other Party of such removal.

9.7.1.2 Outage Schedules. Transmission Provider shall post scheduled outages of its transmission facilities on the OASIS. Interconnection Customer shall submit its planned maintenance schedules for the Large Generating Facility to Transmission Provider for a minimum of a rolling twenty- four month period. Interconnection Customer shall update its planned maintenance schedules as necessary. Transmission Provider may request Interconnection Customer to reschedule its maintenance as necessary to maintain the reliability of the Transmission System; provided, however, adequacy of generation supply shall not be a criterion in determining Transmission System reliability. Transmission Provider shall compensate Interconnection Customer for any additional direct costs that Interconnection Customer incurs as a result of having to reschedule maintenance, including any additional overtime, breaking of maintenance contracts or other costs above and beyond the cost Interconnection Customer would have incurred absent Transmission Provider's request to reschedule maintenance. Interconnection Customer will not be eligible to receive compensation, if during the twelve (12) months prior to the date of the scheduled maintenance, Interconnection Customer had modified its schedule of maintenance activities.

9.7.1.3 Outage Restoration. If an outage on a Party's Interconnection Facilities or Network Upgrades adversely affects the other Party's operations or facilities, the Party that owns or controls the facility that is out of service shall use Reasonable Efforts to promptly restore such facility(ies) to a normal operating condition consistent with the nature of the outage. The Party that owns or controls the facility that is out of service shall provide the other Party, to the extent such information is known, information on the nature of the Emergency Condition, an estimated time of restoration, and any corrective actions required. Initial verbal notice shall be followed up as soon as practicable with written notice explaining the nature of the outage.

9.7.2 Interruption of Service. If required by Good Utility Practice to do so, Transmission Provider may require Interconnection Customer to interrupt or reduce deliveries of electricity if such delivery of electricity could adversely affect Transmission Provider's ability to perform such activities as are necessary to safely and reliably operate and maintain the Transmission System. The following provisions shall apply to any interruption or reduction permitted under this Article 9.7.2:

9.7.2.1 The interruption or reduction shall continue only for so long as reasonably necessary under Good Utility Practice;

9.7.2.2 Any such interruption or reduction shall be made on an equitable, non-discriminatory basis with respect to all generating facilities directly connected to the Transmission System;

9.7.2.3 When the interruption or reduction must be made under circumstances which do not allow for advance notice, Transmission Provider shall notify Interconnection Customer by telephone as soon as practicable of the reasons for the curtailment, interruption, or reduction, and, if known, its expected duration. Telephone notification shall be followed by written notification as soon as

practicable;

9.7.2.4 Except during the existence of an Emergency Condition, when the interruption or reduction can be scheduled without advance notice, Transmission Provider shall notify Interconnection Customer in advance regarding the timing of such scheduling and further notify Interconnection Customer of the expected duration. Transmission Provider shall coordinate with Interconnection Customer using Good Utility Practice to schedule the interruption or reduction during periods of least impact to Interconnection Customer and Transmission Provider;

9.7.2.5 The Parties shall cooperate and coordinate with each other to the extent necessary in order to restore the Large Generating Facility, Interconnection Facilities, and the Transmission System to their normal operating state, consistent with system conditions and Good Utility Practice.

9.7.3 Ride Through Capability and Performance. The Transmission System is designed to automatically activate a load-shed program as required by the Electric Reliability Organization in the event of an under-frequency system disturbance. Interconnection Customer shall implement under-frequency and over-frequency relay set points for the Large Generating Facility as required by the Electric Reliability Organization to ensure frequency “ride through” capability of the Transmission System. Large Generating Facility response to frequency deviations of pre-determined magnitudes, both under-frequency and over-frequency deviations, shall be studied and coordinated with Transmission Provider in accordance with Good Utility Practice. Interconnection Customer shall also implement under-voltage and over-voltage relay set points, or equivalent electronic controls, as required by the Electric Reliability Organization to ensure voltage “ride through” capability of the Transmission System. The term “ride through” as used herein shall mean the ability of a Large Generating Facility to stay connected to and synchronized with the Transmission System during system disturbances within a range of under-frequency, over-frequency, under-voltage, and over-voltage conditions, in accordance with Good Utility Practice and consistent with any standards and guidelines that are applied to other Generating Facilities in the Balancing Authority Area on a comparable basis. For abnormal frequency conditions and voltage conditions within the “no trip zone” defined by Reliability Standard PRC- 024-3 or successor mandatory ride through reliability standards, the non- synchronous Large Generating Facility must ensure that, within any physical limitations of the Large Generating Facility, its control and protection settings are configured or set to (1) continue active power production during disturbance and post disturbance periods at pre- disturbance levels, unless providing primary frequency response or fast frequency response; (2) minimize reductions in active power and remain within dynamic voltage and current limits, if reactive power priority mode is enabled, unless providing primary frequency response or fast frequency response; (3) not artificially limit dynamic reactive power capability during disturbances; and (4) return to pre-disturbance active power levels without artificial ramp rate limits if active power is reduced, unless providing primary frequency response or fast frequency response.

9.7.4 System Protection and Other Control Requirements.

9.7.4.1 System Protection Facilities. Interconnection Customer shall, at its expense, install, operate, and maintain System Protection Facilities as a part of the Large Generating Facility or Interconnection Customer’s Interconnection Facilities. Transmission Provider shall install at Interconnection Customer’s expense any System Protection Facilities that may be required on Transmission Provider’s Interconnection Facilities or the Transmission System as a result of the interconnection of the Large Generating Facility and Interconnection Customer’s Interconnection Facilities.

9.7.4.2 Each Party’s protection facilities shall be designed and coordinated with other systems in

accordance with Good Utility Practice.

9.7.4.3 Each Party shall be responsible for protection of its facilities consistent with Good Utility Practice.

9.7.4.4 Each Party's protective relay design shall incorporate the necessary test switches to perform the tests required in Article 6. The required test switches will be placed such that they allow operation of lockout relays while preventing breaker failure schemes from operating and causing unnecessary breaker operations and/or the tripping of Interconnection Customer's units.

9.7.4.5 Each Party will test, operate, and maintain System Protection Facilities in accordance with Good Utility Practice.

9.7.4.6 Prior to the In-Service Date, and again prior to the Commercial Operation Date, each Party or its agent shall perform a complete calibration test and functional trip test of the System Protection Facilities. At intervals suggested by Good Utility Practice and following any apparent malfunction of the System Protection Facilities, each Party shall perform both calibration and functional trip tests of its System Protection Facilities. These tests do not require the tripping of any in-service generation unit. These tests do, however, require that all protective relays and lockout contacts be activated.

9.7.5 Requirements for Protection. In compliance with Good Utility Practice, Interconnection Customer shall provide, install, own, and maintain relays, circuit breakers and all other devices necessary to remove any fault contribution of the Large Generating Facility to any short circuit occurring on the Transmission System not otherwise isolated by Transmission Provider's equipment, such that the removal of the fault contribution shall be coordinated with the protective requirements of the Transmission System. Such protective equipment shall include, without limitation, a disconnecting device or switch with load-interrupting capability located between the Large Generating Facility and the Transmission System at a site selected upon mutual agreement (not to be unreasonably withheld, conditioned, or delayed) of the Parties. Interconnection Customer shall be responsible for protection of the Large Generating Facility and Interconnection Customer's other equipment from such conditions as negative sequence currents, over- or under-frequency, sudden load rejection, over- or under-voltage, and generator loss-of-field. Interconnection Customer shall be solely responsible to disconnect the Large Generating Facility and Interconnection Customer's other equipment if conditions on the Transmission System could adversely affect the Large Generating Facility.

9.7.6 Power Quality. Neither Party's facilities shall cause excessive voltage flicker nor introduce excessive distortion to the sinusoidal voltage or current waves as defined by ANSI Standard C84.1-1989, in accordance with IEEE Standard 519, or any applicable superseding electric industry standard. In the event of a conflict between ANSI Standard C84.1-1989, or any applicable superseding electric industry standard, ANSI Standard C84.1-1989, or the applicable superseding electric industry standard, shall control.

9.8 Switching and Tagging Rules. Each Party shall provide the other Party a copy of its switching and tagging rules that are applicable to the other Party's activities. Such switching and tagging rules shall be developed on a non-discriminatory basis. The Parties shall comply with applicable switching and tagging rules, as amended from time to time, in obtaining clearances for work or for switching operations on equipment.

9.9 Use of Interconnection Facilities by Third Parties.

9.9.1 Purpose of Interconnection Facilities. Except as may be required by Applicable Laws and Regulations, or as otherwise agreed to among the Parties, the Interconnection Facilities shall be constructed for the sole purpose of interconnecting the Large Generating Facility to the Transmission System and shall be used for no other purpose.

9.9.2 Third Party Users. If required by Applicable Laws and Regulations or if the Parties mutually agree, such agreement not to be unreasonably withheld, to allow one or more third parties to use Transmission Provider's Interconnection Facilities, or any part thereof, Interconnection Customer will be entitled to compensation for the capital expenses it incurred in connection with the Interconnection Facilities based upon the pro rata use of the Interconnection Facilities by Transmission Provider, all third party users, and Interconnection Customer, in accordance with Applicable Laws and Regulations or upon some other mutually agreed upon methodology. In addition, cost responsibility for ongoing costs, including operation and maintenance costs associated with the Interconnection Facilities, will be allocated between Interconnection Customer and any third party users based upon the pro rata use of the Interconnection Facilities by Transmission Provider, all third party users, and Interconnection Customer, in accordance with Applicable Laws and Regulations or upon some other mutually agreed upon methodology. If the issue of such compensation or allocation cannot be resolved through such negotiations, it shall be submitted to FERC for resolution.

9.10 Disturbance Analysis Data Exchange. The Parties will cooperate with one another in the analysis of disturbances to either the Large Generating Facility or Transmission Provider's Transmission System by gathering and providing access to any information relating to any disturbance, including information from oscillography, protective relay targets, breaker operations and sequence of events records, and any disturbance information required by Good Utility Practice.

Article 10. Maintenance

10.1 Transmission Provider Obligations. Transmission Provider shall maintain the Transmission System and Transmission Provider's Interconnection Facilities in a safe and reliable manner and in accordance with this LGIA.

10.2 Interconnection Customer Obligations. Interconnection Customer shall maintain the Large Generating Facility and Interconnection Customer's Interconnection Facilities in a safe and reliable manner and in accordance with this LGIA.

10.3 Coordination. The Parties shall confer regularly to coordinate the planning, scheduling, and performance of preventive and corrective maintenance on the Large Generating Facility and the Interconnection Facilities.

10.4 Secondary Systems. Each Party shall cooperate with the other in the inspection, maintenance, and testing of control or power circuits that operate below 600 volts, AC or DC, including, but not limited to, any hardware, control or protective devices, cables, conductors, electric raceways, secondary equipment panels, transducers, batteries, chargers, and voltage and current transformers that directly affect the operation of a Party's facilities and equipment which may reasonably be expected to impact the other Party. Each Party shall provide advance notice to the other Party before undertaking any work on such circuits, especially on electrical circuits involving circuit breaker trip and close contacts, current transformers, or potential transformers.

10.5 Operating and Maintenance Expenses. Subject to the provisions herein addressing the

use of facilities by others, and except for operations and maintenance expenses associated with modifications made for providing interconnection or transmission service to a third party and such third party pays for such expenses, Interconnection Customer shall be responsible for all reasonable expenses including overheads, associated with: (1) owning, operating, maintaining, repairing, and replacing Interconnection Customer's Interconnection Facilities; and (2) operation, maintenance, repair and replacement of Transmission Provider's Interconnection Facilities.

Article 11. Performance Obligation

11.1 Interconnection Customer Interconnection Facilities. Interconnection Customer shall design, procure, construct, install, own and/or control Interconnection Customer Interconnection Facilities described in Appendix A, Interconnection Facilities, Network Upgrades and Distribution Upgrades, at its sole expense.

11.2 Transmission Provider's Interconnection Facilities. Transmission Provider or Transmission Owner shall design, procure, construct, install, own and/or control the Transmission Provider's Interconnection Facilities described in Appendix A, Interconnection Facilities, Network Upgrades and Distribution Upgrades, at the sole expense of the Interconnection Customer.

11.3 Network Upgrades and Distribution Upgrades. Transmission Provider or Transmission Owner shall design, procure, construct, install, and own the Network Upgrades and Distribution Upgrades described in Appendix A, Interconnection Facilities, Network Upgrades and Distribution Upgrades. Interconnection Customer shall be responsible for all costs related to Distribution Upgrades. Unless Transmission Provider or Transmission Owner elects to fund the capital for the Network Upgrades, they shall be solely funded by Interconnection Customer.

11.4 Transmission Credits.

11.4.1 Repayment of Amounts Advanced for Network Upgrades. Interconnection Customer shall be entitled to a cash repayment, equal to the total amount paid to Transmission Provider and Affected System Operator, if any, for the Network Upgrades, including any tax gross-up or other tax-related payments associated with Network Upgrades, and not refunded to Interconnection Customer pursuant to Article 5.17.8 or otherwise, to be paid to Interconnection Customer on a dollar-for-dollar basis for the non-usage sensitive portion of transmission charges, as payments are made under Transmission Provider's Tariff and Affected System's Tariff for transmission services with respect to the Large Generating Facility. Any repayment shall include interest calculated in accordance with the methodology set forth in FERC's regulations at 18 C.F.R. § 35.19a(a)(2)(iii) from the date of any payment for Network Upgrades through the date on which the Interconnection Customer receives a repayment of such payment pursuant to this subparagraph. Interconnection Customer may assign such repayment rights to any person.

Notwithstanding the foregoing, Interconnection Customer, Transmission Provider, and Affected System Operator may adopt any alternative payment schedule that is mutually agreeable so long as Transmission Provider and Affected System Operator take one of the following actions no later than five years from the Commercial Operation Date: (1) return to Interconnection Customer any amounts advanced for Network Upgrades not previously repaid, or (2) declare in writing that Transmission Provider or Affected System Operator will continue to provide payments to Interconnection Customer on a dollar-for-dollar basis for the non-usage sensitive portion of transmission charges, or develop an alternative schedule that is mutually agreeable and provides

for the return of all amounts advanced for Network Upgrades not previously repaid; however, full reimbursement shall not extend beyond twenty (20) years from the Commercial Operation Date.

If the Large Generating Facility fails to achieve commercial operation, but it or another Generating Facility is later constructed and makes use of the Network Upgrades, Transmission Provider and Affected System Operator shall at that time reimburse Interconnection Customer for the amounts advanced for the Network Upgrades. Before any such reimbursement can occur, the Interconnection Customer, or the entity that ultimately constructs the Generating Facility, if different, is responsible for identifying the entity to which reimbursement must be made.

11.4.2 Special Provisions for Affected Systems. Unless Transmission Provider provides, under the LGIA, for the repayment of amounts advanced to Affected System Operator for Network Upgrades, Interconnection Customer and Affected System Operator shall enter into an agreement that provides for such repayment. The agreement shall specify the terms governing payments to be made by Interconnection Customer to the Affected System Operator as well as the repayment by the Affected System Operator.

11.4.3 Notwithstanding any other provision of this LGIA, nothing herein shall be construed as relinquishing or foreclosing any rights, including but not limited to firm transmission rights, capacity rights, transmission congestion rights, or transmission credits, that Interconnection Customer, shall be entitled to, now or in the future under any other agreement or tariff as a result of, or otherwise associated with, the transmission capacity, if any, created by the Network Upgrades, including the right to obtain cash reimbursements or transmission credits for transmission service that is not associated with the Large Generating Facility.

11.5 Provision of Security. At least thirty (30) Calendar Days prior to the commencement of the procurement, installation, or construction of a discrete portion of a Transmission Provider's Interconnection Facilities, Network Upgrades, or Distribution Upgrades, Interconnection Customer shall provide Transmission Provider, at Interconnection Customer's option, a guarantee, a surety bond, letter of credit or other form of security that is reasonably acceptable to Transmission Provider and is consistent with the Uniform Commercial Code of the jurisdiction identified in Article 14.2.1. Such security for payment, as specified in Appendix B of this LGIA, shall be in an amount sufficient to cover the costs for constructing, procuring, and installing the applicable portion of Transmission Provider's Interconnection Facilities, Network Upgrades, or Distribution Upgrades and shall be reduced on a dollar-for-dollar basis for payments made to Transmission Provider for these purposes. Transmission Provider must use the LGIA Deposit required in Section 11.3 of the LGIP before requiring Interconnection Customer to submit security in addition to that LGIA Deposit. Transmission Provider must specify, in Appendix B of this LGIA, the dates for which Interconnection Customer must provide additional security for construction of each discrete portion of Transmission Provider's Interconnection Facilities, Network Upgrades, or Distribution Upgrades and Interconnection Customer must provide such additional security.

In addition:

11.5.1 The guarantee must be made by an entity that meets the creditworthiness requirements of Transmission Provider, and contain terms and conditions that guarantee payment of any amount that may be due from Interconnection Customer, up to an agreed-to maximum amount.

11.5.2 The letter of credit must be issued by a financial institution reasonably acceptable to Transmission Provider and must specify a reasonable expiration date.

11.5.3 The surety bond must be issued by an insurer reasonably acceptable to Transmission

Provider and must specify a reasonable expiration date.

11.6 Interconnection Customer Compensation. If Transmission Provider requests or directs Interconnection Customer to provide a service pursuant to Articles 9.6.3 (Payment for Reactive Power), or 13.5.1 of this LGIA, Transmission Provider shall compensate Interconnection Customer in accordance with Interconnection Customer's applicable rate schedule then in effect unless the provision of such service(s) is subject to an RTO or ISO FERC-approved rate schedule. Interconnection Customer shall serve Transmission Provider or RTO or ISO with any filing of a proposed rate schedule at the time of such filing with FERC. To the extent that no rate schedule is in effect at the time the Interconnection Customer is required to provide or absorb any Reactive Power under this LGIA, Transmission Provider agrees to compensate Interconnection Customer in such amount as would have been due Interconnection Customer had the rate schedule been in effect at the time service commenced; provided, however, that such rate schedule must be filed at FERC or other appropriate Governmental Authority within sixty (60) Calendar Days of the commencement of service.

11.6.1 Interconnection Customer Compensation for Actions During Emergency Condition. Transmission Provider or RTO or ISO shall compensate Interconnection Customer for its provision of real and reactive power and other Emergency Condition services that Interconnection Customer provides to support the Transmission System during an Emergency Condition in accordance with Article 11.6.

Article 12. Invoice

12.1 General. Each Party shall submit to the other Party, on a monthly basis, invoices of amounts due for the preceding month. Each invoice shall state the month to which the invoice applies and fully describe the services and equipment provided. The Parties may discharge mutual debts and payment obligations due and owing to each other on the same date through netting, in which case all amounts a Party owes to the other Party under this LGIA, including interest payments or credits, shall be netted so that only the net amount remaining due shall be paid by the owing Party.

12.2 Final Invoice. Within six months after completion of the construction of Transmission Provider's Interconnection Facilities and the Network Upgrades, Transmission Provider shall provide an invoice of the final cost of the construction of Transmission Provider's Interconnection Facilities and the Network Upgrades and shall set forth such costs in sufficient detail to enable Interconnection Customer to compare the actual costs with the estimates and to ascertain deviations, if any, from the cost estimates. Transmission Provider shall refund to Interconnection Customer any amount by which the actual payment by Interconnection Customer for estimated costs exceeds the actual costs of construction within thirty (30) Calendar Days of the issuance of such final construction invoice.

12.3 Payment. Invoices shall be rendered to the paying Party at the address specified in Appendix F. The Party receiving the invoice shall pay the invoice within thirty (30) Calendar Days of receipt. All payments shall be made in immediately available funds payable to the other Party, or by wire transfer to a bank named and account designated by the invoicing Party. Payment of invoices by either Party will not constitute a waiver of any rights or claims either Party may have under this LGIA.

12.4 Disputes. In the event of a billing dispute between Transmission Provider and Interconnection Customer, Transmission Provider shall continue to provide Interconnection Service

under this LGIA as long as Interconnection Customer: (i) continues to make all payments not in dispute; and (ii) pays to Transmission Provider or into an independent escrow account the portion of the invoice in dispute, pending resolution of such dispute. If Interconnection Customer fails to meet these two requirements for continuation of service, then Transmission Provider may provide notice to Interconnection Customer of a Default pursuant to Article 17. Within thirty (30) Calendar Days after the resolution of the dispute, the Party that owes money to the other Party shall pay the amount due with interest calculated in accord with the methodology set forth in FERC's regulations at 18 CFR § 35.19a(a)(2)(iii).

Article 13. Emergencies

13.1 Definition. "Emergency Condition" shall mean a condition or situation: (i) that in the judgment of the Party making the claim is imminently likely to endanger life or property; or (ii) that, in the case of Transmission Provider, is imminently likely (as determined in a non-discriminatory manner) to cause a material adverse effect on the security of, or damage to the Transmission System, Transmission Provider's Interconnection Facilities or the Transmission Systems of others to which the Transmission System is directly connected; or (iii) that, in the case of Interconnection Customer, is imminently likely (as determined in a non-discriminatory manner) to cause a material adverse effect on the security of, or damage to, the Large Generating Facility or Interconnection Customer's Interconnection Facilities' System restoration and black start shall be considered Emergency Conditions; provided, that Interconnection Customer is not obligated by this LGIA to possess black start capability.

13.2 Obligations. Each Party shall comply with the Emergency Condition procedures of the applicable ISO/RTO, the Electric Reliability Organization, Applicable Laws and Regulations, and any emergency procedures agreed to by the Joint Operating Committee.

13.3 Notice. Transmission Provider shall notify Interconnection Customer promptly when it becomes aware of an Emergency Condition that affects Transmission Provider's Interconnection Facilities or the Transmission System that may reasonably be expected to affect Interconnection Customer's operation of the Large Generating Facility or Interconnection Customer's Interconnection Facilities. Interconnection Customer shall notify Transmission Provider promptly when it becomes aware of an Emergency Condition that affects the Large Generating Facility or Interconnection Customer's Interconnection Facilities that may reasonably be expected to affect the Transmission System or Transmission Provider's Interconnection Facilities. To the extent information is known, the notification shall describe the Emergency Condition, the extent of the damage or deficiency, the expected effect on the operation of Interconnection Customer's or Transmission Provider's facilities and operations, its anticipated duration and the corrective action taken and/or to be taken. The initial notice shall be followed as soon as practicable with written notice.

13.4 Immediate Action. Unless, in Interconnection Customer's reasonable judgment, immediate action is required, Interconnection Customer shall obtain the consent of Transmission Provider, such consent to not be unreasonably withheld, prior to performing any manual switching operations at the Large Generating Facility or Interconnection Customer's Interconnection Facilities in response to an Emergency Condition either declared by Transmission Provider or otherwise regarding the Transmission System.

13.5 Transmission Provider Authority.

13.5.1 General. Transmission Provider may take whatever actions or inactions with regard to the Transmission System or Transmission Provider's Interconnection Facilities it deems necessary during an Emergency Condition in order to (i) preserve public health and safety, (ii) preserve the reliability of the Transmission System or Transmission Provider's Interconnection Facilities, (iii) limit or prevent damage, and (iv) expedite restoration of service.

Transmission Provider shall use Reasonable Efforts to minimize the effect of such actions or inactions on the Large Generating Facility or Interconnection Customer's Interconnection Facilities. Transmission Provider may, on the basis of technical considerations, require the Large Generating Facility to mitigate an Emergency Condition by taking actions necessary and limited in scope to remedy the Emergency Condition, including, but not limited to, directing Interconnection Customer to shut-down, start-up, increase or decrease the real or reactive power output of the Large Generating Facility; implementing a reduction or disconnection pursuant to Article 13.5.2; directing Interconnection Customer to assist with blackstart (if available) or restoration efforts; or altering the outage schedules of the Large Generating Facility and Interconnection Customer's Interconnection Facilities. Interconnection Customer shall comply with all of Transmission Provider's operating instructions concerning Large Generating Facility real power and reactive power output within the manufacturer's design limitations of the Large Generating Facility's equipment that is in service and physically available for operation at the time, in compliance with Applicable Laws and Regulations.

13.5.2 Reduction and Disconnection. Transmission Provider may reduce Interconnection Service or disconnect the Large Generating Facility or Interconnection Customer's Interconnection Facilities, when such reduction or disconnection is necessary under Good Utility Practice due to Emergency Conditions. These rights are separate and distinct from any right of curtailment of Transmission Provider pursuant to Transmission Provider's Tariff. When Transmission Provider can schedule the reduction or disconnection in advance, Transmission Provider shall notify Interconnection Customer of the reasons, timing and expected duration of the reduction or disconnection. Transmission Provider shall coordinate with Interconnection Customer using Good Utility Practice to schedule the reduction or disconnection during periods of least impact to Interconnection Customer and Transmission Provider. Any reduction or disconnection shall continue only for so long as reasonably necessary under Good Utility Practice. The Parties shall cooperate with each other to restore the Large Generating Facility, the Interconnection Facilities, and the Transmission System to their normal operating state as soon as practicable consistent with Good Utility Practice.

13.6 Interconnection Customer Authority. Consistent with Good Utility Practice and the LGIA and the LGIP, Interconnection Customer may take actions or inactions with regard to the Large Generating Facility or Interconnection Customer's Interconnection Facilities during an Emergency Condition in order to (i) preserve public health and safety, (ii) preserve the reliability of the Large Generating Facility or Interconnection Customer's Interconnection Facilities, (iii) limit or prevent damage, and (iv) expedite restoration of service. Interconnection Customer shall use Reasonable Efforts to minimize the effect of such actions or inactions on the Transmission System and Transmission Provider's Interconnection Facilities. Transmission Provider shall use Reasonable Efforts to assist Interconnection Customer in such actions.

13.7 Limited Liability. Except as otherwise provided in Article 11.6.1 of this LGIA, neither Party shall be liable to the other for any action it takes in responding to an Emergency Condition so long as such action is made in good faith and is consistent with Good Utility Practice.

Article 14. Regulatory Requirements and Governing Law

14.1 Regulatory Requirements. Each Party's obligations under this LGIA shall be subject to its receipt of any required approval or certificate from one or more Governmental Authorities in the form and substance satisfactory to the applying Party, or the Party making any required filings with, or providing notice to, such Governmental Authorities, and the expiration of any time period associated therewith. Each Party shall in good faith seek and use its Reasonable Efforts to obtain such other approvals. Nothing in this LGIA shall require Interconnection Customer to take any action that could result in its inability to obtain, or its loss of, status or exemption under the Federal Power Act, the Public Utility Holding Company Act of 1935, as amended, or the Public Utility Regulatory Policies Act of 1978.

14.2 Governing Law.

14.2.1 The validity, interpretation, and performance of this LGIA and each of its provisions shall be governed by the laws of the state where the Point of Interconnection is located, without regard to its conflicts of law principles.

14.2.2 This LGIA is subject to all Applicable Laws and Regulations.

14.2.3 Each Party expressly reserves the right to seek changes in, appeal, or otherwise contest any laws, orders, rules, or regulations of a Governmental Authority.

Article 15. Notices.

15.1 General. Unless otherwise provided in this LGIA, any notice, demand or request required or permitted to be given by either Party to the other and any instrument required or permitted to be tendered or delivered by either Party in writing to the other shall be effective when delivered and may be so given, tendered or delivered, by recognized national courier, or by depositing the same with the United States Postal Service with postage prepaid, for delivery by certified or registered mail, addressed to the Party, or personally delivered to the Party, at the address set out in Appendix F, Addresses for Delivery of Notices and Billings.

Either Party may change the notice information in this LGIA by giving five (5) Business Days written notice prior to the effective date of the change.

15.2 Billings and Payments. Billings and payments shall be sent to the addresses set out in Appendix F.

15.3 Alternative Forms of Notice. Any notice or request required or permitted to be given by a Party to the other and not required by this Agreement to be given in writing may be so given by telephone, facsimile or email to the telephone numbers and email addresses set out in Appendix F.

15.4 Operations and Maintenance Notice. Each Party shall notify the other Party in writing of the identity of the person(s) that it designates as the point(s) of contact with respect to the implementation of Articles 9 and 10.

Article 16. Force Majeure

16.1 Force Majeure.

16.1.1 Economic hardship is not considered a Force Majeure event.

16.1.2 Neither Party shall be considered to be in Default with respect to any obligation hereunder, (including obligations under Article 4), other than the obligation to pay money when due, if prevented from fulfilling such obligation by Force Majeure. A Party unable to fulfill any obligation hereunder (other than an obligation to pay money when due) by reason of Force Majeure shall give notice and the full particulars of such Force Majeure to the other Party in writing or by telephone as soon as reasonably possible after the occurrence of the cause relied upon. Telephone notices given pursuant to this Article shall be confirmed in writing as soon as reasonably possible and shall specifically state full particulars of the Force Majeure, the time and date when the Force Majeure occurred and when the Force Majeure is reasonably expected to cease. The Party affected shall exercise due diligence to remove such disability with reasonable dispatch, but shall not be required to accede or agree to any provision not satisfactory to it in order to settle and terminate a strike or other labor disturbance.

Article 17. Default

17.1 Default

17.1.1 General. No Default shall exist where such failure to discharge an obligation (other than the payment of money) is the result of Force Majeure as defined in this LGIA or the result of an act of omission of the other Party. Upon a Breach, the non-breaching Party shall give written notice of such Breach to the breaching Party. Except as provided in Article 17.1.2, the breaching Party shall have thirty (30) Calendar Days from receipt of the Default notice within which to cure such Breach; provided however, if such Breach is not capable of cure within thirty (30) Calendar Days, the breaching Party shall commence such cure within thirty (30) Calendar Days after notice and continuously and diligently complete such cure within ninety (90) Calendar Days from receipt of the Default notice; and, if cured within such time, the Breach specified in such notice shall cease to exist.

17.1.2 Right to Terminate. If a Breach is not cured as provided in this article, or if a Breach is not capable of being cured within the period provided for herein, the non-breaching Party shall have the right to declare a Default and terminate this LGIA by written notice at any time until cure occurs, and be relieved of any further obligation hereunder and, whether or not that Party terminates this LGIA, to recover from the breaching Party all amounts due hereunder, plus all other damages and remedies to which it is entitled at law or in equity. The provisions of this Article will survive termination of this LGIA.

17.2 Violation of Operating Assumptions for Generating Facilities. If Transmission Provider requires Interconnection Customer to memorialize the operating assumptions for the charging behavior of a Generating Facility that includes at least one electric storage resource in Appendix H of this LGIA, Transmission Provider may consider Interconnection Customer to be in Breach of the LGIA if Interconnection Customer fails to operate the Generating Facility in accordance with those operating assumptions for charging behavior. However, if Interconnection Customer operates contrary to the operating assumptions for charging behavior specified in Appendix H of this LGIA at the direction of Transmission Provider, Transmission Provider shall not consider Interconnection Customer in Breach of this LGIA.

Article 18. Indemnity, Consequential Damages, and Insurance

18.1 Indemnity. The Parties shall at all times indemnify, defend, and hold the other Party harmless from, any and all damages, losses, claims, including claims and actions relating to injury to or death of any person or damage to property, demand, suits, recoveries, costs and expenses, court costs, attorney fees, and all other obligations by or to third parties, arising out of or resulting from the other Party's action or inactions of its obligations under this LGIA on behalf of the Indemnifying Party, except in cases of gross negligence or intentional wrongdoing by the indemnified Party.

18.1.1 Indemnified Person. If an Indemnified Person is entitled to indemnification under this Article 18 as a result of a claim by a third party, and the Indemnifying Party fails, after notice and reasonable opportunity to proceed under Article 18.1, to assume the defense of such claim, such Indemnified Person may at the expense of the Indemnifying Party contest, settle or consent to the entry of any judgment with respect to, or pay in full, such claim.

18.1.2 Indemnifying Party. If an Indemnifying Party is obligated to indemnify and hold any Indemnified Person harmless under this Article 18, the amount owing to the Indemnified Person shall be the amount of such Indemnified Person's actual Loss, net of any insurance or other recovery.

18.1.3 Indemnity Procedures. Promptly after receipt by an Indemnified Person of any claim or notice of the commencement of any action or administrative or legal proceeding or investigation as to which the indemnity provided for in Article 18.1 may apply, the Indemnified Person shall notify the Indemnifying Party of such fact. Any failure of or delay in such notification shall not affect a Party's indemnification obligation unless such failure or delay is materially prejudicial to the Indemnifying Party.

The Indemnifying Party shall have the right to assume the defense thereof with counsel designated by such Indemnifying Party and reasonably satisfactory to the Indemnified Person. If the defendants in any such action include one or more Indemnified Persons and the Indemnifying Party and if the Indemnified Person reasonably concludes that there may be legal defenses available to it and/or other Indemnified Persons which are different from or additional to those available to the Indemnifying Party, the Indemnified Person shall have the right to select separate counsel to assert such legal defenses and to otherwise participate in the defense of such action on its own behalf. In such instances, the Indemnifying Party shall only be required to pay the fees and expenses of one additional attorney to represent an Indemnified Person or Indemnified Persons having such differing or additional legal defenses.

The Indemnified Person shall be entitled, at its expense, to participate in any such action, suit or proceeding, the defense of which has been assumed by the Indemnifying Party. Notwithstanding the foregoing, the Indemnifying Party (i) shall not be entitled to assume and control the defense of any such action, suit or proceedings if and to the extent that, in the opinion of the Indemnified Person and its counsel, such action, suit or proceeding involves the potential imposition of criminal liability on the Indemnified Person, or there exists a conflict or adversity of interest between the Indemnified Person and the Indemnifying Party, in such event the Indemnifying Party shall pay the reasonable expenses of the Indemnified Person, and (ii) shall not settle or consent to the entry of any judgment in any action, suit or proceeding without the consent of the Indemnified Person, which shall not be reasonably withheld, conditioned or delayed.

18.2 Consequential Damages. Other than the Liquidated Damages heretofore described, in no event shall either Party be liable under any provision of this LGIA for any losses, damages, costs or expenses for any special, indirect, incidental, consequential, or punitive damages, including but not

limited to loss of profit or revenue, loss of the use of equipment, cost of capital, cost of temporary equipment or services, whether based in whole or in part in contract, in tort, including negligence, strict liability, or any other theory of liability; provided, however, that damages for which a Party may be liable to the other Party under another agreement will not be considered to be special, indirect, incidental, or consequential damages hereunder.

18.3 Insurance. Each party shall, at its own expense, maintain in force throughout the period of this LGIA, and until released by the other Party, the following minimum insurance coverages, with insurers authorized to do business in the state where the Point of Interconnection is located:

18.3.1 Employers' Liability and Workers' Compensation Insurance providing statutory benefits in accordance with the laws and regulations of the state in which the Point of Interconnection is located.

18.3.2 Commercial General Liability Insurance including premises and operations, personal injury, broad form property damage, broad form blanket contractual liability coverage (including coverage for the contractual indemnification) products and completed operations coverage, coverage for explosion, collapse and underground hazards, independent contractors coverage, coverage for pollution to the extent normally available and punitive damages to the extent normally available and a cross liability endorsement, with minimum limits of One Million Dollars (\$1,000,000) per occurrence/One Million Dollars (\$1,000,000) aggregate combined single limit for personal injury, bodily injury, including death and property damage.

18.3.3 Comprehensive Automobile Liability Insurance for coverage of owned and non-owned and hired vehicles, trailers or semi-trailers designed for travel on public roads, with a minimum, combined single limit of One Million Dollars (\$1,000,000) per occurrence for bodily injury, including death, and property damage.

18.3.4 Excess Public Liability Insurance over and above the Employers' Liability Commercial General Liability and Comprehensive Automobile Liability Insurance coverage, with a minimum combined single limit of Twenty Million Dollars (\$20,000,000) per occurrence/Twenty Million Dollars (\$20,000,000) aggregate.

18.3.5 The Commercial General Liability Insurance, Comprehensive Automobile Insurance and Excess Public Liability Insurance policies shall name the other Party, its parent, associated and Affiliate companies and their respective directors, officers, agents, servants, and employees ("Other Party Group") as additional insured. All policies shall contain provisions whereby the insurers waive all rights of subrogation in accordance with the provisions of this LGIA against the Other Party Group and provide thirty (30) Calendar Days advance written notice to the Other Party Group prior to anniversary date of cancellation or any material change in coverage or condition.

18.3.6 The Commercial General Liability Insurance, Comprehensive Automobile Liability Insurance and Excess Public Liability Insurance policies shall contain provisions that specify that the policies are primary and shall apply to such extent without consideration for other policies separately carried and shall state that each insured is provided coverage as though a separate policy had been issued to each, except the insurer's liability shall not be increased beyond the amount for which the insurer would have been liable had only one insured been covered. Each Party shall be responsible for its respective deductibles or retentions.

18.3.7 The Commercial General Liability Insurance, Comprehensive Automobile Liability Insurance and Excess Public Liability Insurance policies, if written on a Claims First Made Basis, shall be maintained in full force and effect for two (2) years after termination of this LGIA, which

coverage may be in the form of tail coverage or extended reporting period coverage if agreed by the Parties.

18.3.8 The requirements contained herein as to the types and limits of all insurance to be maintained by the Parties are not intended to and shall not in any manner, limit or qualify the liabilities and obligations assumed by the Parties under this LGIA.

18.3.9 Within ten (10) days following execution of this LGIA, and as soon as practicable after the end of each fiscal year or at the renewal of the insurance policy and in any event within ninety (90) days thereafter, each Party shall provide certification of all insurance required in this LGIA, executed by each insurer or by an authorized representative of each insurer.

18.3.10 Notwithstanding the foregoing, each Party may self-insure to meet the minimum insurance requirements of Articles 18.3.2 through 18.3.8 to the extent it maintains a self-insurance program; provided that, such Party's senior secured debt is rated at investment grade or better by Standard & Poor's and that its self-insurance program meets the minimum insurance requirements of Articles 18.3.2 through 18.3.8. For any period of time that a Party's senior secured debt is unrated by Standard & Poor's or is rated at less than investment grade by Standard & Poor's, such Party shall comply with the insurance requirements applicable to it under Articles 18.3.2 through 18.3.9. In the event that a Party is permitted to self-insure pursuant to this article, it shall notify the other Party that it meets the requirements to self-insure and that its self-insurance program meets the minimum insurance requirements in a manner consistent with that specified in Article 18.3.9.

18.3.11 The Parties agree to report to each other in writing as soon as practical all accidents or occurrences resulting in injuries to any person, including death, and any property damage arising out of this LGIA.

Article 19. Assignment

19.1 Assignment. This LGIA may be assigned by either Party only with the written consent of the other; provided that either Party may assign this LGIA without the consent of the other Party to any Affiliate of the assigning Party with an equal or greater credit rating and with the legal authority and operational ability to satisfy the obligations of the assigning Party under this LGIA; and provided further that Interconnection Customer shall have the right to assign this LGIA, without the consent of Transmission Provider, for collateral security purposes to aid in providing financing for the Large Generating Facility, provided that Interconnection Customer will promptly notify Transmission Provider of any such assignment. Any financing arrangement entered into by Interconnection Customer pursuant to this Article will provide that prior to or upon the exercise of the secured party's, trustee's or mortgagee's assignment rights pursuant to said arrangement, the secured creditor, the trustee or mortgagee will notify Transmission Provider of the date and particulars of any such exercise of assignment right(s), including providing the Transmission Provider with proof that it meets the requirements of Articles 11.5 and 18.3. Any attempted assignment that violates this Article is void and ineffective. Any assignment under this LGIA shall not relieve a Party of its obligations, nor shall a Party's obligations be enlarged, in whole or in part, by reason thereof. Where required, consent to assignment will not be unreasonably withheld, conditioned, or delayed.

Article 20. Severability

20.1 Severability. If any provision in this LGIA is finally determined to be invalid, void or

unenforceable by any court or other Governmental Authority having jurisdiction, such determination shall not invalidate, void or make unenforceable any other provision, agreement or covenant of this LGIA; provided that if Interconnection Customer (or any third party, but only if such third party is not acting at the direction of Transmission Provider) seeks and obtains such a final determination with respect to any provision of the Alternate Option (Article 5.1.2), or the Negotiated Option (Article 5.1.4), then none of these provisions shall thereafter have any force or effect and the Parties' rights and obligations shall be governed solely by the Standard Option (Article 5.1.1).

Article 21. Comparability

21.1 Comparability. The Parties will comply with all applicable comparability and code of conduct laws, rules, and regulations, as amended from time to time.

Article 22. Confidentiality

22.1 Confidentiality. Confidential Information shall include, without limitation, all information relating to a Party's technology, research and development, business affairs, and pricing, and any information supplied by either of the Parties to the other prior to the execution of this LGIA.

Information is Confidential Information only if it is clearly designated or marked in writing as confidential on the face of the document, or, if the information is conveyed orally or by inspection, if the Party providing the information orally informs the Party receiving the information that the information is confidential.

If requested by either Party, the other Party shall provide in writing, the basis for asserting that the information referred to in this Article 22 warrants confidential treatment, and the requesting Party may disclose such writing to the appropriate Governmental Authority. Each Party shall be responsible for the costs associated with affording confidential treatment to its information.

22.1.1 Term. During the term of this LGIA, and for a period of three (3) years after the expiration or termination of this LGIA, except as otherwise provided in this Article 22, each Party shall hold in confidence and shall not disclose to any person Confidential Information.

22.1.2 Scope. Confidential Information shall not include information that the receiving Party can demonstrate: (1) is generally available to the public other than as a result of a disclosure by the receiving Party; (2) was in the lawful possession of the receiving Party on a non-confidential basis before receiving it from the disclosing Party; (3) was supplied to the receiving Party without restriction by a third party, who, to the knowledge of the receiving Party after due inquiry, was under no obligation to the disclosing Party to keep such information confidential; (4) was independently developed by the receiving Party without reference to Confidential Information of the disclosing Party; (5) is, or becomes, publicly known, through no wrongful act or omission of the receiving Party or Breach of this LGIA; or (6) is required, in accordance with Article 22.1.7 of the LGIA, Order of Disclosure, to be disclosed by any Governmental Authority or is otherwise required to be disclosed by law or subpoena, or is necessary in any legal proceeding establishing rights and obligations under this LGIA. Information designated as Confidential Information will no longer be deemed confidential if the Party that designated the information as confidential notifies the other Party that it no longer is confidential.

22.1.3 Release of Confidential Information. Neither Party shall release or disclose

Confidential Information to any other person, except to its Affiliates (limited by the Standards of Conduct requirements), subcontractors, employees, consultants, or to parties who may be or considering providing financing to or equity participation with Interconnection Customer, or to potential purchasers or assignees of Interconnection Customer, on a need-to-know basis in connection with this LGIA, unless such person has first been advised of the confidentiality provisions of this Article 22 and has agreed to comply with such provisions. Notwithstanding the foregoing, a Party providing Confidential Information to any person shall remain primarily responsible for any release of Confidential Information in contravention of this Article 22.

22.1.4 Rights. Each Party retains all rights, title, and interest in the Confidential Information that each Party discloses to the other Party. The disclosure by each Party to the other Party of Confidential Information shall not be deemed a waiver by either Party or any other person or entity of the right to protect the Confidential Information from public disclosure.

22.1.5 No Warranties. By providing Confidential Information, neither Party makes any warranties or representations as to its accuracy or completeness. In addition, by supplying Confidential Information, neither Party obligates itself to provide any particular information or Confidential Information to the other Party nor to enter into any further agreements or proceed with any other relationship or joint venture.

22.1.6 Standard of Care. Each Party shall use at least the same standard of care to protect Confidential Information it receives as it uses to protect its own Confidential Information from unauthorized disclosure, publication, or dissemination. Each Party may use Confidential Information solely to fulfill its obligations to the other Party under this LGIA or its regulatory requirements.

22.1.7 Order of Disclosure. If a court or a Government Authority or entity with the right, power, and apparent authority to do so requests or requires either Party, by subpoena, oral deposition, interrogatories, requests for production of documents, administrative order, or otherwise, to disclose Confidential Information, that Party shall provide the other Party with prompt notice of such request(s) or requirement(s) so that the other Party may seek an appropriate protective order or waive compliance with the terms of this LGIA. Notwithstanding the absence of a protective order or waiver, the Party may disclose such Confidential Information which, in the opinion of its counsel, the Party is legally compelled to disclose. Each Party will use Reasonable Efforts to obtain reliable assurance that confidential treatment will be accorded any Confidential Information so furnished.

22.1.8 Termination of Agreement. Upon termination of this LGIA for any reason, each Party shall, within ten (10) Calendar Days of receipt of a written request from the other Party, use Reasonable Efforts to destroy, erase, or delete (with such destruction, erasure, and deletion certified in writing to the other Party) or return to the other Party, without retaining copies thereof, any and all written or electronic Confidential Information received from the other Party.

22.1.9 Remedies. The Parties agree that monetary damages would be inadequate to compensate a Party for the other Party's Breach of its obligations under this Article 22. Each Party accordingly agrees that the other Party shall be entitled to equitable relief, by way of injunction or otherwise, if the first Party Breaches or threatens to Breach its obligations under this Article 22, which equitable relief shall be granted without bond or proof of damages, and the receiving Party shall not plead in defense that there would be an adequate remedy at law. Such remedy shall not be deemed an exclusive remedy for the Breach of this Article 22, but shall be in addition to all other remedies available at law or in equity. The Parties further acknowledge and agree that the covenants

contained herein are necessary for the protection of legitimate business interests and are reasonable in scope. No Party, however, shall be liable for indirect, incidental, or consequential or punitive damages of any nature or kind resulting from or arising in connection with this Article 22.

22.1.10 Disclosure to FERC, its Staff, or a State. Notwithstanding anything in this Article 22 to the contrary, and pursuant to 18 CFR Section 1b.20, if FERC or its staff, during the course of an investigation or otherwise, requests information from one of the Parties that is otherwise required to be maintained in confidence pursuant to this LGIA, the Party shall provide the requested information to FERC or its staff, within the time provided for in the request for information. In providing the information to FERC or its staff, the Party must, consistent with 18 CFR Section 388.112, request that the information be treated as confidential and non-public by FERC and its staff and that the information be withheld from public disclosure. Parties are prohibited from notifying the other Party to this LGIA prior to the release of the Confidential Information to FERC or its staff. The Party shall notify the other Party to the LGIA when it is notified by FERC or its staff that a request to release Confidential Information has been received by FERC, at which time either of the Parties may respond before such information would be made public, pursuant to 18 CFR section 388.112. Requests from a state regulatory body conducting a confidential investigation shall be treated in a similar manner if consistent with the applicable state rules and regulations.

22.1.11 Subject to the exception in Article 22.1.10, any information that a Party claims is competitively sensitive, commercial or financial information under this LGIA (“Confidential Information”) shall not be disclosed by the other Party to any person not employed or retained by the other Party, except to the extent disclosure is (i) required by law; (ii) reasonably deemed by the disclosing Party to be required to be disclosed in connection with a dispute between or among the Parties, or the defense of litigation or dispute; (iii) otherwise permitted by consent of the other Party, such consent not to be unreasonably withheld; or (iv) necessary to fulfill its obligations under this LGIA or as a transmission service provider or a Balancing Authority Area operator including disclosing the Confidential Information to an RTO or ISO or to a regional or national reliability organization. The Party asserting confidentiality shall notify the other Party in writing of the information it claims is confidential. Prior to any disclosures of the other Party’s Confidential Information under this subparagraph, or if any third party or Governmental Authority makes any request or demand for any of the information described in this subparagraph, the disclosing Party agrees to promptly notify the other Party in writing and agrees to assert confidentiality and cooperate with the other Party in seeking to protect the Confidential Information from public disclosure by confidentiality agreement, protective order or other reasonable measures.

Article 23. Environmental Releases

23.1 Each Party shall notify the other Party, first orally and then in writing, of the release of any Hazardous Substances, any asbestos or lead abatement activities, or any type of remediation activities related to the Large Generating Facility or the Interconnection Facilities, each of which may reasonably be expected to affect the other Party. The notifying Party shall: (i) provide the notice as soon as practicable, provided such Party makes a good faith effort to provide the notice no later than twenty-four hours after such Party becomes aware of the occurrence; and (ii) promptly furnish to the other Party copies of any publicly available reports filed with any Governmental Authorities addressing such events.

Article 24. Information Requirements

24.1 Information Acquisition. Transmission Provider and Interconnection Customer shall submit specific information regarding the electrical characteristics of their respective facilities to each other as described below and in accordance with Applicable Reliability Standards.

24.2 Information Submission by Transmission Provider. The initial information submission by Transmission Provider shall occur no later than one hundred eighty (180) Calendar Days prior to Trial Operation and shall include Transmission System information necessary to allow Interconnection Customer to select equipment and meet any system protection and stability requirements, unless otherwise agreed to by the Parties. On a monthly basis Transmission Provider shall provide Interconnection Customer a status report on the construction and installation of Transmission Provider's Interconnection Facilities and Network Upgrades, including, but not limited to, the following information: (1) progress to date; (2) a description of the activities since the last report (3) a description of the action items for the next period; and (4) the delivery status of equipment ordered.

24.3 Updated Information Submission by Interconnection Customer. The updated information submission by Interconnection Customer, including manufacturer information, shall occur no later than one hundred eighty (180) Calendar Days prior to the Trial Operation. Interconnection Customer shall submit a completed copy of the Large Generating Facility data requirements contained in Appendix 1 to the LGIP. It shall also include any additional information provided to Transmission Provider for the Cluster Study and Facilities Study. Information in this submission shall be the most current Large Generating Facility design or expected performance data. Information submitted for stability models shall be compatible with Transmission Provider standard models. If there is no compatible model, Interconnection Customer will work with a consultant mutually agreed to by the Parties to develop and supply a standard model and associated information.

If Interconnection Customer's data is materially different from what was originally provided to Transmission Provider pursuant to the Interconnection Study Agreement between Transmission Provider and Interconnection Customer, then Transmission Provider will conduct appropriate studies to determine the impact on Transmission Provider Transmission System based on the actual data submitted pursuant to this Article 24.3. Interconnection Customer shall not begin Trial Operation until such studies are completed.

24.4 Information Supplementation. Prior to the Operation Date, the Parties shall supplement their information submissions described above in this Article 24 with any and all "as-built" Large Generating Facility information or "as-tested" performance information that differs from the initial submissions or, alternatively, written confirmation that no such differences exist. The Interconnection Customer shall conduct tests on the Large Generating Facility as required by Good Utility Practice such as an open circuit "step voltage" test on the Large Generating Facility to verify proper operation of the Large Generating Facility's automatic voltage regulator.

Unless otherwise agreed, the test conditions shall include: (1) Large Generating Facility at synchronous speed; (2) automatic voltage regulator on and in voltage control mode; and (3) a five percent change in Large Generating Facility terminal voltage initiated by a change in the voltage regulators reference voltage.

Interconnection Customer shall provide validated test recordings showing the responses of Large Generating Facility terminal and field voltages. In the event that direct recordings of these voltages is impractical, recordings of other voltages or currents that mirror the response of the Large Generating Facility's terminal or field voltage are acceptable if information necessary to translate these alternate quantities to actual Large Generating Facility terminal or field voltages is provided.

Large Generating Facility testing shall be conducted and results provided to Transmission Provider for each individual generating unit in a station.

Subsequent to the Operation Date, Interconnection Customer shall provide Transmission Provider any information changes due to equipment replacement, repair, or adjustment. Transmission Provider shall provide Interconnection Customer any information changes due to equipment replacement, repair, or adjustment in the directly connected substation or any adjacent Transmission Provider-owned substation that may affect Interconnection Customer's Interconnection Facilities equipment ratings, protection, or operating requirements. The Parties shall provide such information no later than thirty (30) Calendar Days after the date of the equipment replacement, repair or adjustment.

Article 25. Information Access and Audit Rights

25.1 Information Access. Each Party (the "disclosing Party") shall make available to the other Party information that is in the possession of the disclosing Party and is necessary in order for the other Party to: (i) verify the costs incurred by the disclosing Party for which the other Party is responsible under this LGIA; and (ii) carry out its obligations and responsibilities under this LGIA. The Parties shall not use such information for purposes other than those set forth in this Article 25.1 and to enforce their rights under this LGIA.

25.2 Reporting of Non-Force Majeure Events. Each Party (the "notifying Party") shall notify the other Party when the notifying Party becomes aware of its inability to comply with the provisions of this LGIA for a reason other than a Force Majeure event. The Parties agree to cooperate with each other and provide necessary information regarding such inability to comply, including the date, duration, reason for the inability to comply, and corrective actions taken or planned to be taken with respect to such inability to comply. Notwithstanding the foregoing, notification, cooperation, or information provided under this Article shall not entitle the Party receiving such notification to allege a cause for anticipatory breach of this LGIA.

25.3 Audit Rights. Subject to the requirements of confidentiality under Article 22 of this LGIA, each Party shall have the right, during normal business hours, and upon prior reasonable notice to the other Party, to audit at its own expense the other Party's accounts and records pertaining to either Party's performance or either Party's satisfaction of obligations under this LGIA. Such audit rights shall include audits of the other Party's costs, calculation of invoiced amounts, Transmission Provider's efforts to allocate responsibility for the provision of reactive support to the Transmission System, Transmission Provider's efforts to allocate responsibility for interruption or reduction of generation on the Transmission System, and each Party's actions in an Emergency Condition. Any audit authorized by this Article shall be performed at the offices where such accounts and records are maintained and shall be limited to those portions of such accounts and records that relate to each Party's performance and satisfaction of obligations under this LGIA. Each Party shall keep such accounts and records for a period equivalent to the audit rights periods described in Article 25.4.

25.4 Audit Rights Periods.

25.4.1 Audit Rights Period for Construction-Related Accounts and Records. Accounts and records related to the design, engineering, procurement, and construction of Transmission Provider's Interconnection Facilities and Network Upgrades shall be subject to audit for a period of twenty-four months following Transmission Provider's issuance of a final invoice in accordance with Article 12.2.

25.4.2 Audit Rights Period for All Other Accounts and Records. Accounts and records related to either Party's performance or satisfaction of all obligations under this LGIA other than those described in Article 25.4.1 shall be subject to audit as follows: (i) for an audit relating to cost obligations, the applicable audit rights period shall be twenty-four months after the auditing Party's receipt of an invoice giving rise to such cost obligations; and (ii) for an audit relating to all other obligations, the applicable audit rights period shall be twenty-four months after the event for which the audit is sought.

25.5 Audit Results. If an audit by a Party determines that an overpayment or an underpayment has occurred, a notice of such overpayment or underpayment shall be given to the other Party together with those records from the audit which support such determination.

Article 26. Subcontractors

26.1 General. Nothing in this LGIA shall prevent a Party from utilizing the services of any subcontractor as it deems appropriate to perform its obligations under this LGIA; provided, however, that each Party shall require its subcontractors to comply with all applicable terms and conditions of this LGIA in providing such services and each Party shall remain primarily liable to the other Party for the performance of such subcontractor.

26.2 Responsibility of Principal. The creation of any subcontract relationship shall not relieve the hiring Party of any of its obligations under this LGIA. The hiring Party shall be fully responsible to the other Party for the acts or omissions of any subcontractor the hiring Party hires as if no subcontract had been made; provided, however, that in no event shall Transmission Provider be liable for the actions or inactions of Interconnection Customer or its subcontractors with respect to obligations of Interconnection Customer under Article 5 of this LGIA. Any applicable obligation imposed by this LGIA upon the hiring Party shall be equally binding upon, and shall be construed as having application to, any subcontractor of such Party.

26.3 No Limitation by Insurance. The obligations under this Article 26 will not be limited in any way by any limitation of subcontractor's insurance.

Article 27. Disputes

27.1 Submission. In the event either Party has a dispute, or asserts a claim, that arises out of or in connection with this LGIA or its performance, such Party (the "disputing Party") shall provide the other Party with written notice of the dispute or claim ("Notice of Dispute"). Such dispute or claim shall be referred to a designated senior representative of each Party for resolution on an informal basis as promptly as practicable after receipt of the Notice of Dispute by the other Party. In the event the designated representatives are unable to resolve the claim or dispute through unassisted or assisted negotiations within thirty (30) Calendar Days of the other Party's receipt of the Notice of Dispute, such claim or dispute may, upon mutual agreement of the Parties, be submitted to arbitration and resolved in accordance with the arbitration procedures set forth below. In the event the Parties do not agree to submit such claim or dispute to arbitration, each Party may exercise whatever rights and remedies it may have in equity or at law consistent with the terms of this LGIA.

27.2 External Arbitration Procedures. Any arbitration initiated under this LGIA shall be conducted before a single neutral arbitrator appointed by the Parties. If the Parties fail to agree

upon a single arbitrator within ten (10) Calendar Days of the submission of the dispute to arbitration, each Party shall choose one arbitrator who shall sit on a three-member arbitration panel. The two arbitrators so chosen shall within twenty (20) Calendar Days select a third arbitrator to chair the arbitration panel. In either case, the arbitrators shall be knowledgeable in electric utility matters, including electric transmission and bulk power issues, and shall not have any current or past substantial business or financial relationships with any party to the arbitration (except prior arbitration). The arbitrator(s) shall provide each of the Parties an opportunity to be heard and, except as otherwise provided herein, shall conduct the arbitration in accordance with the Commercial Arbitration Rules of the American Arbitration Association (“Arbitration Rules”) and any applicable FERC regulations or RTO rules; provided, however, in the event of a conflict between the Arbitration Rules and the terms of this Article 27, the terms of this Article 27 shall prevail.

27.3 Arbitration Decisions. Unless otherwise agreed by the Parties, the arbitrator(s) shall render a decision within ninety (90) Calendar Days of appointment and shall notify the Parties in writing of such decision and the reasons therefor. The arbitrator(s) shall be authorized only to interpret and apply the provisions of this LGIA and shall have no power to modify or change any provision of this Agreement in any manner. The decision of the arbitrator(s) shall be final and binding upon the Parties, and judgment on the award may be entered in any court having jurisdiction. The decision of the arbitrator(s) may be appealed solely on the grounds that the conduct of the arbitrator(s), or the decision itself, violated the standards set forth in the Federal Arbitration Act or the Administrative Dispute Resolution Act. The final decision of the arbitrator must also be filed with FERC if it affects jurisdictional rates, terms and conditions of service, Interconnection Facilities, or Network Upgrades.

27.4 Costs. Each Party shall be responsible for its own costs incurred during the arbitration process and for the following costs, if applicable: (1) the cost of the arbitrator chosen by the Party to sit on the three member panel and one half of the cost of the third arbitrator chosen; or (2) one half the cost of the single arbitrator jointly chosen by the Parties.

Article 28. Representations, Warranties, and Covenants

28.1 General. Each Party makes the following representations, warranties, and covenants:

28.1.1 Good Standing. Such Party is duly organized, validly existing and in good standing under the laws of the state in which it is organized, formed, or incorporated, as applicable; that it is qualified to do business in the state or states in which the Large Generating Facility, Interconnection Facilities and Network Upgrades owned by such Party, as applicable, are located; and that it has the corporate power and authority to own its properties, to carry on its business as now being conducted and to enter into this LGIA and carry out the transactions contemplated hereby and perform and carry out all covenants and obligations on its part to be performed under and pursuant to this LGIA.

28.1.2 Authority. Such Party has the right, power, and authority to enter into this LGIA, to become a Party hereto and to perform its obligations hereunder. This LGIA is a legal, valid, and binding obligation of such Party, enforceable against such Party in accordance with its terms, except as the enforceability thereof may be limited by applicable bankruptcy, insolvency, reorganization, or other similar laws affecting creditors’ rights generally and by general equitable principles (regardless of whether enforceability is sought in a proceeding in equity or at law).

28.1.3 No Conflict. The execution, delivery, and performance of this LGIA does not violate or conflict with the organizational or formation documents, or bylaws or operating agreement, of such Party, or any judgment, license, permit, order, material agreement or instrument applicable to or binding upon such Party or any of its assets.

28.1.4 Consent and Approval. Such Party has sought or obtained, or, in accordance with this LGIA will seek or obtain, each consent, approval, authorization, order, or acceptance by any Governmental Authority in connection with the execution, delivery and performance of this LGIA, and it will provide to any Governmental Authority notice of any actions under this LGIA that are required by Applicable Laws and Regulations.

Article 29. Joint Operating Committee

29.1 Joint Operating Committee. Except in the case of ISOs and RTOs, Transmission Provider shall constitute a Joint Operating Committee to coordinate operating and technical considerations of Interconnection Service. At least six (6) months prior to the expected Initial Synchronization Date, Interconnection Customer and Transmission Provider shall each appoint one representative and one alternate to the Joint Operating Committee. Each Interconnection Customer shall notify Transmission Provider of its appointment in writing. Such appointments may be changed at any time by similar notice. The Joint Operating Committee shall meet as necessary, but not less than once each calendar year, to carry out the duties set forth herein. The Joint Operating Committee shall hold a meeting at the request of either Party, at a time and place agreed upon by the representatives. The Joint Operating Committee shall perform all of its duties consistent with the provisions of this LGIA. Each Party shall cooperate in providing to the Joint Operating Committee all information required in the performance of the Joint Operating Committee's duties. All decisions and agreements, if any, made by the Joint Operating Committee, shall be evidenced in writing. The duties of the Joint Operating Committee shall include the following:

29.1.1 Establish data requirements and operating record requirements.

29.1.2 Review the requirements, standards, and procedures for data acquisition equipment, protective equipment, and any other equipment or software.

29.1.3 Annually review the one (1) year forecast of maintenance and planned outage schedules of Transmission Provider's and Interconnection Customer's facilities at the Point of Interconnection.

29.1.4 Coordinate the scheduling of maintenance and planned outages on the Interconnection Facilities, the Large Generating Facility and other facilities that impact the normal operation of the interconnection of the Large Generating Facility to the Transmission System.

29.1.5 Ensure that information is being provided by each Party regarding equipment availability.

29.1.6 Perform such other duties as may be conferred upon it by mutual agreement of the Parties.

Article 30. Miscellaneous

30.1 Binding Effect. This LGIA and the rights and obligations hereof, shall be binding upon and shall inure to the benefit of the successors and assigns of the Parties hereto.

30.2 Conflicts. In the event of a conflict between the body of this LGIA and any attachment, Appendices or exhibits hereto, the terms and provisions of the body of this LGIA shall prevail and be deemed the final intent of the Parties.

30.3 Rules of Interpretation. This LGIA, unless a clear contrary intention appears, shall be construed and interpreted as follows: (1) the singular number includes the plural number and vice versa; (2) reference to any person includes such person's successors and assigns but, in the case of a Party, only if such successors and assigns are permitted by this LGIA, and reference to a person in a particular capacity excludes such person in any other capacity or individually; (3) reference to any agreement (including this LGIA), document, instrument or tariff means such agreement, document, instrument, or tariff as amended or modified and in effect from time to time in accordance with the terms thereof and, if applicable, the terms hereof; (4) reference to any Applicable Laws and Regulations means such Applicable Laws and Regulations as amended, modified, codified, or reenacted, in whole or in part, and in effect from time to time, including, if applicable, rules and regulations promulgated thereunder; (5) unless expressly stated otherwise, reference to any Article, Section or Appendix means such Article of this LGIA or such Appendix to this LGIA, or such Section to the LGIP or such Appendix to the LGIP, as the case may be; (6) "hereunder", "hereof", "herein", "hereto" and words of similar import shall be deemed references to this LGIA as a whole and not to any particular Article or other provision hereof or thereof; (7) "including" (and with correlative meaning "include") means including without limiting the generality of any description preceding such term; and (8) relative to the determination of any period of time, "from" means "from and including", "to" means "to but excluding" and "through" means "through and including".

30.4 Entire Agreement. This LGIA, including all Appendices and Schedules attached hereto, constitutes the entire agreement between the Parties with reference to the subject matter hereof, and supersedes all prior and contemporaneous understandings or agreements, oral or written, between the Parties with respect to the subject matter of this LGIA. There are no other agreements, representations, warranties, or covenants which constitute any part of the consideration for, or any condition to, either Party's compliance with its obligations under this LGIA.

30.5 No Third Party Beneficiaries. This LGIA is not intended to and does not create rights, remedies, or benefits of any character whatsoever in favor of any persons, corporations, associations, or entities other than the Parties, and the obligations herein assumed are solely for the use and benefit of the Parties, their successors in interest and, where permitted, their assigns.

30.6 Waiver. The failure of a Party to this LGIA to insist, on any occasion, upon strict performance of any provision of this LGIA will not be considered a waiver of any obligation, right, or duty of, or imposed upon, such Party.

Any waiver at any time by either Party of its rights with respect to this LGIA shall not be deemed a continuing waiver or a waiver with respect to any other failure to comply with any other obligation, right, duty of this LGIA. Termination or Default of this LGIA for any reason by Interconnection Customer shall not constitute a waiver of Interconnection Customer's legal rights to obtain an interconnection from Transmission Provider. Any waiver of this LGIA shall, if requested, be provided in writing.

30.7 Headings. The descriptive headings of the various Articles of this LGIA have been inserted for convenience of reference only and are of no significance in the interpretation or construction of this LGIA.

30.8 Multiple Counterparts. This LGIA may be executed in two or more counterparts, each of which is deemed an original but all constitute one and the same instrument.

30.9 Amendment. The Parties may by mutual agreement amend this LGIA by a written instrument duly executed by the Parties.

30.10 Modification by the Parties. The Parties may by mutual agreement amend the Appendices to this LGIA by a written instrument duly executed by the Parties. Such amendment shall become effective and a part of this LGIA upon satisfaction of all Applicable Laws and Regulations.

30.11 Reservation of Rights. Transmission Provider shall have the right to make a unilateral filing with FERC to modify this LGIA with respect to any rates, terms and conditions, charges, classifications of service, rule or regulation under Section 205 or any other applicable provision of the Federal Power Act and FERC's rules and regulations thereunder, and Interconnection Customer shall have the right to make a unilateral filing with FERC to modify this LGIA pursuant to Section 206 or any other applicable provision of the Federal Power Act and FERC's rules and regulations thereunder; provided that each Party shall have the right to protest any such filing by the other Party and to participate fully in any proceeding before FERC in which such modifications may be considered. Nothing in this LGIA shall limit the rights of the Parties or of FERC under Sections 205 or 206 of the Federal Power Act and FERC's rules and regulations thereunder, except to the extent that the Parties otherwise mutually agree as provided herein.

30.12 No Partnership. This LGIA shall not be interpreted or construed to create an association, joint venture, agency relationship, or partnership between the Parties or to impose any partnership obligation or partnership liability upon either Party. Neither Party shall have any right, power, or authority to enter into any agreement or undertaking for, or act on behalf of, or to act as or be an agent or representative of, or to otherwise bind, the other Party.

IN WITNESS WHEREOF, the Parties have executed this Amended and Restated LGIA in duplicate originals, each of which shall constitute and be an original effective Agreement between the Parties.

Duke Energy Florida, LLC, as Transmission Provider

By: Mark D. McKeage
Mark D. McKeage, PE
Director, Interconnection Programs
Approved by Nelson Peeler, SVP
Date: Nov 25, 2024

Placid Solar II, LLC, as Interconnection Customer

By: Felice Basile
Name: Felice Basile
Title: Authorized Signatory
Date: Nov 1, 2024


Appendix A to LGIA

Interconnection Facilities, Network Upgrades and Distribution Upgrades

NOTE: The facilities described in this Appendix are based on the studies conducted in response to the DEF FERC Q259 Interconnection Request. In the event that other Interconnection Customers suspend, terminate or request unexecuted filing of their LGIAs, then additional studies may be required that could result in changes to the Interconnection Facilities and the Network Upgrades and in changes to Interconnection Customer's cost obligations for those facilities.


1. Interconnection Facilities:

- (a) Interconnection Customer's Interconnection Facilities** to be designed, procured, constructed, installed, owned and maintained by Interconnection Customer at its sole expense:





- (b) Transmission Provider's Interconnection Facilities**, which will be designed, procured, constructed, installed, maintained, and owned and/or controlled by Transmission Owner, but which will be paid for by Interconnection Customer at Interconnection Customer's sole expense, include:

Transmission











2. Network Upgrades:

(a) Substation Network Upgrades: only required for a single Interconnection Customer in the Cluster and no other Interconnection Customer in that Cluster is required to interconnect to the same Substation Network Upgrades:

Substation




Protection and Control







Telecommunications



- **Stand Alone Substation Network Upgrades:** Substation Network Upgrades that are not part of an Affected System that an Interconnection Customer may construct without affecting day-to-day operations of the Transmission System during their construction: 

(b) System Network Upgrades: only required for a single Interconnection Customer in the Cluster: 

- **Stand Alone System Network Upgrades:** System Network Upgrades that are not part of an Affected System that an Interconnection Customer may construct without affecting day-to-day operations of the Transmission System during their construction: 

Schedule durations may be impacted by outage availability and time of the year the work is planned. Outage availability may have a significant impact on schedule.


- (c) Contingent Facilities:** those unbuilt Interconnection Facilities and Network Upgrades upon which the Interconnection Request's costs, timing, and study findings are dependent, and if delayed or not built, could cause a need for Re-Studies of the Interconnection Request or a reassessment of the Interconnection Facilities and/or Network Upgrades and/or costs and timing:


the fiber at the Point of Change of Ownership, and the Transmission Provider will be responsible for bringing the fiber from the Point of Change of Ownership, into the DEF Fisheating Creek 230 kV Substation, through the Point of Interconnection and into the CEE. The Interconnection Customer will install, own, and maintain all facilities from the Point of Change of Ownership back to the proposed Solar PV Station, including the Solar PV generator lead line.

7. Point of Interconnection:

The Point of Interconnection will be the Interconnection Customer's side of the disconnect switch between the Network Upgrades and the Transmission Provider's Interconnection Facilities, inside the DEF Fisheating Creek 230 kV Switching Station.

8. Higher-Queued Interconnection Requests:






Appendix B to LGIA

Milestones

The table below identifies completion timeframes for major activities for this project with an expected ISD shown below.

[illegible]



*Required Security shall be in the form of Cash or a Letter of Credit issued by an entity not affiliated with the Interconnection Customer, in a form acceptable to Duke Energy. Security amount may change proportionately with any Contingent Facilities that ultimately get assigned to Q259.


Site Control

Check box if applicable []

Interconnection Customer with qualifying regulatory limitations must demonstrate 100% Site Control by September 28, 2024 or the LGIA may be terminated per Article 17 (Default) of this LGIA and the Interconnection Customer may be subject to Withdrawal Penalties per Section 3.7.1.1 of the Transmission Provider's LGIP (Calculation of the Withdrawal Penalty).

Appendix C to LGIA

Interconnection Details



Facility Connection Requirements (FCR)

The Facility Connection Requirements (FCR) establish the minimum requirements for all generating facilities connecting with the Transmission Provider's Transmission System. The FCR is subject to revision from time to time. The Interconnection Customer's Generating Facility shall remain in compliance with the most recently revised FCR in effect at any given time while the Generating Facility is in service. The FCR is publicly available on Transmission Provider's OASIS site.

Duke Energy Transmission Connected IBR Technical Interconnection Requirements (TIR)

The purpose of these requirements is to establish the technical (capability and performance) requirements for all IBR Generating Facilities connecting with the Transmission Provider's Transmission System. The location of the interconnection and its impacts on the Transmission System or other interconnected systems of Transmission Provider determine the specific requirements. These technical requirements are designed to ensure the safe operation and reliability of the Transmission Provider's Transmission System. These requirements will be adhered to for all interconnections, including those owned by the Transmission Provider. These requirements are publicly available on Transmission Provider's OASIS site.

Duke Energy Transmission Connected IBR Interconnection Commissioning Document

This document provides an overview of the process, requirements, and timeline for commissioning of an IBR Generating Facility connecting to the Transmission Provider's Transmission system. This document reflects the Transmission Provider's currently effective requirements, but Transmission Provider reserves the right to update, modify, or otherwise change these requirements at any time. This document is publicly available on Transmission Provider's OASIS site.

Duke Energy IBR Plant Coordination Document

This coordination document is intended to aid with the implementation of best practices for reliable interconnection of IBR with the Transmission Provider's Transmission System. The topics covered in this document have been identified in the Transmission Provider's IBR Interconnection Technical Requirement, NERC Reliability Standards & Guidelines, NERC Event Reports, and the IEEE 2800 standard.

5. Network Upgrades and Transmission Provider's Interconnection Facilities are based on application of industry standard equipment. All new and rebuilt facilities will be designed and built according to Transmission Provider's current practice. These facilities will become a part of the Transmission Provider's network Transmission System. Therefore, in addition to having sufficient capacity to accept the proposed Solar PV station generation, these facilities must also have the capacity to carry the power flows to upstream loads. As such, the total energy handling capability of the proposed Interconnection Facilities could potentially accommodate energy flows greater than the requested 74.9 MW. However, in the event that the Interconnection Customer decides to designate additional capacity, a new request will be required to evaluate the impacts. Any constraints that may result will be identified as part of the new study request.
6. Any required outages necessary to support construction of the Interconnection Facilities must be coordinated with the Transmission Provider's Energy Control Center ("ECC"). If an outage of sufficient duration cannot be obtained to support any of the required construction activities, alternative solutions such as new or temporary facilities may have to be constructed to maintain integrity of the grid. No provisions have been made for alternate or temporary work in the estimates provided herein.
7. The proposed protection schemes to be installed by the Transmission Provider at the Associated Facilities are intended to protect the Transmission Provider's Transmission System.
8. Estimates are considered to be good faith estimates represented in present day dollars as of the date of the agreement. The estimates do not include upgrade costs for third party facilities. The cost estimates provided use currently available pricing in Duke Energy's estimating system. The estimated budget has been computed with an expected accuracy of $\pm 20\%$. Costs may fluctuate due to inflation or changes in market price. The estimates are further premised on being able to perform work during normal business hours with minimum overtime or weekend work. The estimates assume no changes in scope or design from that provided in previous studies.

9. Cost estimates are inclusive of engineering, material (equipment, structures, conductors, OPGW, etc.), survey, geotechnical, access, clearing, siting, environmental, construction and removal.
10. The scope of work, durations, clarifications, assumptions and cost estimates apply to the core work associated for Network Resource Interconnection Service (NRIS).
11. Outage availability may have a significant impact on cost and schedule.
12. The project generating units and associated facilities will meet applicable NERC Standards and Guidelines. Abnormal system conditions may result in tripping of the interconnected facilities.
13. An inspection certificate is required from the governing electrical inspector before the Transmission Provider will install the export revenue meter or allow operation of the Generating Facility. If the governing electrical inspector indicates that the installation is exempt from inspection authority, a written, signed statement from the governing electrical inspector for the specific installation will be required before the Transmission Provider will place the export revenue meter or allow operation of the Generating Facility. The inspection certificate or appropriate statement shall be sent to the Transmission Provider's Designated Operating Representative as detailed in this document.
14. The Interconnection Customer must provide the Transmission Provider's ECC with updated operational contact information at all times, specifically at least one name and telephone number that can be contacted 24 hours per day regarding any operational or safety issues regarding the interconnection or operation of the generating facility as directed by the ECC System Operator. This contact individual should be capable of receiving instructions regarding plant output and voltage/MVAR schedule requirements, report operational issues, and make plant adjustments as directed by the ECC. This contact individual can be located at a remote location as long as this individual can carry out instructions as directed by the ECC.
15. Transmission Provider will provide a voltage/var schedule to be followed by the Solar Generating Facility. The Solar Generating Facility shall follow the provided voltage/var schedule in accordance with the requirements of NERC Reliability Standard VAR-002. The Solar Generating Facility shall also comply with directions from the ECC System Operator to deviate from this voltage/var schedule as may be necessary to accommodate transmission system conditions.
16. Unless otherwise specified by the Transmission Provider, the Transmission Provider will require the Solar Generating Facility to operate in automatic voltage controlling mode in accordance with NERC Reliability Standard VAR-002. Automatic voltage control mode is defined as that mode of operation such that the plant inverters/plant controller would automatically respond to voltage deviations, caused by normal transmission system voltage variations or transmission system disturbances such as faults, by adjusting the inverters' reactive power output to restore the voltage to the scheduled level.
17. The Solar Generating Facility shall be operated in such a manner as to maintain the capability to deliver MVARS continuously to the POI over the full range of MW output, subject to plant equipment voltage limits, based on the ± 0.95 power factor requirement at the POI.
18. The Solar Generating Facility inverter control equipment shall be set such that the voltage and frequency ride-through capability is in accordance with NERC Reliability Standard PRC-024 Attachment 1 (for frequency) and Attachment 2 (for voltage). Anti-islanding schemes shall not be employed unless they meet the specified voltage and frequency ride-through requirements.
19. The main step up transformer(s) connecting the Solar Generating Facility to the transmission POI shall have the taps set on the setting provided by Transmission Provider. Transformers

internal to the solar plant (such as the inverter to collector field transformers) shall be set to maintain the required MVAR capability without creating plant equipment over or under voltage conditions.

20. Transmission Provider's Transmission System could experience increased harmonics due to the installation of a capacitor bank. If unacceptable levels of harmonics are experienced, the Transmission Provider will seek mitigation to eliminate or reduce the harmonics to acceptable levels.

21. The Transmission Provider intends to allow the Interconnection Customer to continue to operate its Generating Facility when a Hot Line Tag is placed on the transmission line circuit breakers. The Transmission Provider retains the right to (1) use special settings or logic at the interconnection site during Hot Line Tag conditions and/or (2) require the Interconnection Customer to shut down its Generating Facility during Hot Line Tag or clearance conditions on any device on the transmission line (or other transmission line if a transmission tie condition is in effect) if Transmission Provider staff dictates that special conditions warrant.

22. The Transmission Provider requires a single lockable and visible disconnecting means by which the generation source can be isolated from any and all parts of the Transmission Provider's Transmission System when necessary. The disconnecting means are owned by either the Interconnection Customer or by the Transmission Provider; however, in either case they must be visible, accessible, and operable by Transmission Provider personnel. Disconnecting means controlled at ground level shall have locking mechanisms to allow Transmission Provider personnel to place a padlock in the open position.

23. The Interconnection Customer will be required to contact the ECC dispatcher prior to synchronization and paralleling of the Interconnection Customer's generators with the Transmission Provider's Transmission System. This notice should be done each time when the entire plant is off-line, and the Interconnection Customer is bringing on the first generator. ECC Dispatcher contact is not required for subsequent generator synchronization during that operation cycle.

24. **UTILITY-OWNED INTERCONNECTION PROTECTION:** Applicable only when an interconnection protection relay, used with either a utility circuit breaker, or configured to trip Generating Facility circuit breaker(s), located at the Point of Interconnection, is owned by the Transmission Provider:

- a. The Transmission Provider will operate the interconnection relay as a "one-shot" device; i.e., it is not configured to automatically reclose after tripping on overcurrent elements for faults on the generator side of the breaker. An interconnection protection relay exists primarily for interconnection protection, and the Transmission Provider will configure the device to trip for voltage and frequency excursions and faults as detected on the Transmission Provider side of the interconnection.

- b. The Transmission Provider may still configure the relay, upon a return of normal frequency and voltage on the Transmission Provider system, to either (1) "release" its trip signal to the Generating Facility's circuit breaker(s) or (2) configure a Transmission Provider-owned circuit breaker to automatically close and reconnect the Generating Facility to the Transmission Provider system.

- c. In case of equipment failure associated with the interconnection relay (and/or utility circuit breaker), primary metering, or other associated facilities, the Generating Facility must remain offline until repairs are made. The interconnection breaker cannot be bypassed during this condition.

d. In the event that the Transmission Provider relay is in a “locked out” state and is holding the Generating Facility’s circuit breaker(s) or the Transmission Provider circuit breaker in an open state, the Interconnection Customer must attempt to locate the source of the fault that caused the relay to trip before contacting the Transmission Provider.

e. Once the fault is corrected, whether the fault was on Generating Facility equipment or Transmission Provider equipment, the Interconnection Customer must then initiate a request to be reconnected to the Transmission Provider system. The Transmission Provider requires that when the Interconnection Customer desires the Transmission Provider to release the relay trip signal or to close the interconnection breaker, requests to do so must be routed via telephone to the ECC Dispatcher. The Interconnection Customer, prior to contacting the ECC, must have checked their facilities. The Interconnection Customer must state clearly to the ECC that “they have all personnel and equipment in the clear and are ready for Transmission Provider to close the interconnection breaker.” If remote control of the interconnection breaker is available to the ECC, the interconnection breaker will be closed via remote communications at that time. If remote control is not available to the ECC, the ECC will dispatch field personnel to travel to the Interconnection Customer breaker. The ECC will require further telephone contact with the Interconnection Customer when field personnel are at the site and preparing to close the breaker, at which time the Interconnection Customer must again state clearly to the ECC that “they have all personnel and equipment in the clear and are ready for Transmission Provider to close the interconnection breaker.”

25. On occasion, Transmission Provider will be required to perform routine maintenance activities on the circuit breaker protecting the Generating Facility. Transmission Provider employees will be required to take the breaker out of service which will disconnect the Generating Facility from the transmission grid. Transmission Provider will notify the Interconnection Customer at least 2 weeks in advance of this scheduled maintenance activity.

26. If an Emergency Condition exists at the Interconnection Customer’s Generating Facility, the Transmission Provider will disconnect the Generating Facility from the transmission grid until the Emergency Condition is corrected.

27. Real and Reactive Power Testing (similar to MOD-025 testing for traditional generation) – Transmission Planning and System Operations Engineering

a. It is recommended that the verification include the following four points where maximum MW is between 90% to 100% of MW capacity output and minimum MW is between 20% to 50% of MW capacity output

1. Maximum MW and maximum lagging (providing) MVAR
2. Maximum MW and maximum leading (absorbing) MVAR
3. Minimum MW and maximum lagging (providing) MVAR
4. Minimum MW and maximum leading (absorbing) MVAR

28. Reimbursement Pursuant to Article 11.4.1 - In accordance with Article 11.4.1, Transmission Provider will reimburse Interconnection Customer for the cost of Network Upgrades funded by Interconnection Customer and identified in Appendix A in a one-time, lump sum payment to be paid within five (5) years of the Generating Facility’s Commercial Operation Date for Network Resource Interconnection Service.

29. The Transmission Provider may conduct an Electromagnetic Transient Study after LGIA execution. In alignment with cost responsibility for all other types of generator interconnection studies, the Interconnection Customer will be responsible for the cost of the Electromagnetic

Transient Study. If the study results show the need for any Transmission Provider Interconnection Facilities or Network Upgrades, the cost responsibility for such facilities and/or upgrades shall be allocated to Interconnection Customer in alignment with the applicable terms and conditions of the LGIA.

Appendix D to LGIA

Security Arrangements Details

Infrastructure security of Transmission System equipment and operations and control hardware and software is essential to ensure day-to-day Transmission System reliability and operational security. FERC will expect all Transmission Providers, market participants, and Interconnection Customers interconnected to the Transmission System to comply with the recommendations offered by the President's Critical Infrastructure Protection Board and, eventually, best practice recommendations from the electric reliability authority. All public utilities will be expected to meet basic standards for system infrastructure and operational security, including physical, operational, and cyber- security practices.

Appendix E to LGIA

Commercial Operation Date

This Appendix E is a part of the LGIA between Transmission Provider and Interconnection Customer. Interconnection Customer will use this form to notify the Transmission Provider of the Commercial Operation by selecting the appropriate service, consistent with the milestone schedule in Appendix B and the Interconnection Details in Appendix C.

[Date]

Duke Energy Florida, LLC
Director, System Operations
6565 38Th Ave. N. (EC37)
St. Petersburg, FL 33710

Re: Q259 Large Generating Facility

Dear _____:

On [Date] Gwinn Solar Farm, LLC has completed Trial Operation of Unit No. Q259. This letter confirms that Gwinn Solar Farm, LLC commenced Commercial Operation of Unit No. Q259 at the Large Generating Facility, effective as of [Date plus one day]. Commercial Operation for Network Resource Interconnection Service commenced as of [Date plus one day].

Thank you.

[Signature]

[Interconnection Customer Representative]

Appendix F to LGIA

Addresses for Delivery of Notices and Billings

Notices:

Transmission Provider:

Duke Energy Florida, LLC
Director, Interconnection Programs
299 First Avenue North (FL-15B)
St. Petersburg, FL 33701
(727) 820-4593

With a Copy to:
Duke Energy Corporation
525 S. Tryon Street, (9th Floor)
Charlotte, NC 28202
Attn: FERC Counsel

Interconnection Customer:

Placid Solar II, LLC
251 Little Falls Dr
Wilmington, DE

With Copy to:
NextEnergy Capital
75 Grosvenor Street
London W1K 3JS
Attn: Kevin Mclelland

Billings and Payments:

Transmission Provider:

Duke Energy Florida, LLC
Manager Accounting, Duke Energy Business Services
525 South Tryon St.
Mail Code DEP-16C
Charlotte, NC 28202

Interconnection Customer:

Placid Solar, LLC
Project: Highland North
Highlands County, Florida.
c/o: NEXTPOWER III US HOLDCO INC.

Alternative Forms of Delivery of Notices (telephone or email):

Transmission Provider:

Mark.McKeage@duke-energy.com

Interconnection Customer:

kevin.mclelland@nextenergycapital.com

matthew.alison@nextenergycapital.com

Appendix G to LGIA

INTERCONNECTION REQUIREMENTS FOR A WIND GENERATING PLANT

Appendix G sets forth requirements and provisions specific to a wind generating plant. All other requirements of this LGIA continue to apply to wind generating plant interconnections.

A. Technical Standards Applicable to a Wind Generating Plant

i. Low Voltage Ride-Through (LVRT) Capability

A wind generating plant shall be able to remain online during voltage disturbances up to the time periods and associated voltage levels set forth in the standard below. The LVRT standard provides for a transition period standard and a post-transition period standard.

Transition Period LVRT Standard

The transition period standard applies to wind generating plants subject to FERC Order 661 that have either: (i) interconnection agreements signed and filed with the Commission, filed with the Commission in unexecuted form, or filed with the Commission as non-conforming agreements between January 1, 2006 and December 31, 2006, with a scheduled in-service date no later than December 31, 2007, or (ii) wind generating turbines subject to a wind turbine procurement contract executed prior to December 31, 2005, for delivery through 2007.

1. Wind generating plants are required to remain in-service during three-phase faults with normal clearing (which is a time period of approximately 4 – 9 cycles) and single line to ground faults with delayed clearing, and subsequent post-fault voltage recovery to prefault voltage unless clearing the fault effectively disconnects the generator from the system. The clearing time requirement for a three-phase fault will be specific to the wind generating plant substation location, as determined by and documented by the transmission provider. The maximum clearing time the wind generating plant shall be required to withstand for a three-phase fault shall be 9 cycles at a voltage as low as 0.15 p.u., as measured at the high side of the wind generating plant step-up transformer (*i.e.* the transformer that steps the voltage up to the transmission interconnection voltage or “GSU”), after which, if the fault remains following the location-specific normal clearing time for three-phase faults, the wind generating plant may disconnect from the transmission system.

2. This requirement does not apply to faults that would occur between the wind generator terminals and the high side of the GSU or to faults that would result in a voltage lower than 0.15 per unit on the high side of the GSU serving the facility.

3. Wind generating plants may be tripped after the fault period if this action is intended as part of a special protection system.

4. Wind generating plants may meet the LVRT requirements of this standard by the performance of the generators or by installing additional equipment (*e.g.*, Static VAR Compensator, etc.) within the wind generating plant or by a combination of generator performance and additional equipment.

5. Existing individual generator units that are, or have been, interconnected to the network at the same location at the effective date of the Appendix G LVRT Standard are exempt from meeting the Appendix G

LVRT Standard for the remaining life of the existing generation equipment. Existing individual generator units that are replaced are required to meet the Appendix G LVRT Standard.

Post-transition Period LVRT Standard

All wind generating plants subject to FERC Order No. 661 and not covered by the transition period described above must meet the following requirements:

1. Wind generating plants are required to remain in-service during three-phase faults with normal clearing (which is a time period of approximately 4 – 9 cycles) and single line to ground faults with delayed clearing, and subsequent post-fault voltage recovery to prefault voltage unless clearing the fault effectively disconnects the generator from the system. The clearing time requirement for a three-phase fault will be specific to the wind generating plant substation location, as determined by and documented by the transmission provider. The maximum clearing time the wind generating plant shall be required to withstand for a three-phase fault shall be 9 cycles after which, if the fault remains following the location-specific normal clearing time for three-phase faults, the wind generating plant may disconnect from the transmission system. A wind generating plant shall remain interconnected during such a fault on the transmission system for a voltage level as low as zero volts, as measured at the high voltage side of the wind GSU.
2. This requirement does not apply to faults that would occur between the wind generator terminals and the high side of the GSU.
3. Wind generating plants may be tripped after the fault period if this action is intended as part of a special protection system.
4. Wind generating plants may meet the LVRT requirements of this standard by the performance of the generators or by installing additional equipment (e.g., Static VAr Compensator) within the wind generating plant or by a combination of generator performance and additional equipment.
5. Existing individual generator units that are, or have been, interconnected to the network at the same location at the effective date of the Appendix G LVRT Standard are exempt from meeting the Appendix G LVRT Standard for the remaining life of the existing generation equipment. Existing individual generator units that are replaced are required to meet the Appendix G LVRT Standard.

ii. Power Factor Design Criteria (Reactive Power)

The following reactive power requirements apply only to a newly interconnecting wind generating plant that has executed a Facilities Study Agreement as of the effective date of the Final Rule establishing the reactive power requirements for non-synchronous generators in section 9.6.1 of this LGIA (Order No. 827). A wind generating plant to which this provision applies shall maintain a power factor within the range of 0.95 leading to 0.95 lagging, measured at the Point of Interconnection as defined in this LGIA, if the Transmission Provider's Cluster Study shows that such a requirement is necessary to ensure safety or reliability. The power factor range standard can be met by using, for example, power electronics designed to supply this level of reactive capability (taking into account any limitations due to voltage level, real power output, etc.) or fixed and switched capacitors if agreed to by the Transmission Provider, or a combination of the two. The Interconnection Customer shall not disable power factor equipment while the wind plant is in operation. Wind plants shall also be able to provide sufficient dynamic voltage support in lieu of the power system stabilizer and automatic voltage regulation at the generator excitation system if the System Impact Study shows this to be required for system safety or reliability.

iii. Supervisory Control and Data Acquisition (SCADA) Capability

The wind plant shall provide SCADA capability to transmit data and receive instructions from the Transmission Provider to protect system reliability. The Transmission Provider and the wind plant Interconnection Customer shall determine what SCADA information is essential for the proposed wind plant, taking into account the size of the plant and its characteristics, location, and importance in maintaining generation resource adequacy and transmission system reliability in its area.

Appendix H to LGIA

OPERATING ASSUMPTIONS FOR GENERATING FACILITY

Check box if applicable []

Operating Assumptions:

{insert operating assumptions that reflect the charging behavior of the Generating Facility that includes at least one electric storage resource}